

LT8711 Micropower Synchronous Sepic Converter

DESCRIPTION

Demonstration circuit 2234A is a synchronous sepic converter featuring the LT[®]8711 multitopology switching controller. The LT8711 is a current mode PWM DC/DC controller with a dual input LDO to optimize gate driver efficiency. Ultralow 15 μ A quiescent current in low noise Burst Mode[®] operation achieves high efficiency at very light loads and helps extend the run-time in battery powered applications when in standby mode. The LT8711 switching frequency can be programmed either via oscillator resistor or external clock over a 100kHz to 750kHz range.

The demo board regulates a 12V, 4A output from a 4.5V to 40V input source, and operates at 200kHz switching frequency. The rated maximum load current is 4A, while derating is necessary for certain input voltage and thermal conditions.

The SYNC pin on the demo board is grounded (JP1 at BURST position) by default for low ripple high efficiency Burst Mode operation at light load. To synchronize to an external clock, move JP1 to SYNC and apply the external clock to the SYNC turret. Force continuous conduction mode can be selected by moving JP1 shunt to FCM position.

The DC2234A can be modified from a SEPIC converter to other topologies. Synchronous BOOST and some other schematics are provided in the data sheet. Please consult the factory or LT8711 data sheet for details regarding how to customize the DC2234A or how to design different topologies for custom specifications.

The LT8711 includes many other features such as user configurable under voltage lockout, soft-start, input voltage feedforward regulation, and it is easily configured as synchronous buck, boost, SEPIC or nonsynchronous buck-boost converter.

The data sheet gives a complete description of the device, operation and application information. The data sheet must be read in conjunction with this demo manual for DC2234A. The LT8711 is assembled in a 20-lead plastic TSSOP package with a thermally enhanced ground pad. Proper board layout is essential for maximum thermal performance. See the Layout Considerations section in the data sheet.

Design files for this circuit board are available at <http://www.linear.com/demo/DC2234A>

LT, LT, LTC, LTM, Linear Technology, Burst Mode and the Linear logo are registered trademarks of Analog Devices, Inc. All other trademarks are the property of their respective owners.

PERFORMANCE SUMMARY Specifications are at T_A = 25°C

| SYMBOL | PARAMETER | CONDITIONS | MIN | TYP | MAX | UNITS |
|------------------|------------------------|---|------|----------------------------|------|------------------|
| V _{IN} | Input Voltage Range | | 4.5 | | 40 | V |
| V _{OUT} | Output Voltage | | 11.6 | 12 | 12.4 | V |
| I _{OUT} | Maximum Output Current | Derating is Necessary for Certain V _{IN} and Thermal Conditions | 4 | | | A |
| t _{SW} | Switching Frequency | | 185 | 200 | 215 | kHz |
| EFF | Efficiency at DC | V _{IN} = 5V, I _{OUT} = 1A V _{IN} = 12V, I _{OUT} = 2A V _{IN} = 24V, I _{OUT} = 4A V _{IN} = 36V, I _{OUT} = 4A | | 91.9 92 91.4 90.2 | | % % % % |

QUICK START PROCEDURE

DC2234A is easy to set up to evaluate the performance of the LT8711. Refer to Figure 3 for proper measurement equipment setup and follow the procedure below:

NOTE: When measuring the input or output voltage ripple, care must be taken to avoid a long ground lead on the oscilloscope probe. See Figure 4 for the proper scope technique.

1. Set an input power supply that is capable of 40V/12A. Then turn off the supply.
2. With power off, connect the supply to the input terminals V_{IN} and GND.
3. Turn on the power at the input.

NOTE: Make sure that the input voltage never exceeds 40V.

4. Check for the proper output voltage of 12V. Turn off the power at the input.
5. Once the proper output voltage is established, connect a variable load capable of sinking 4A at 12V to the output terminals V_{OUT} and GND. Set the current for 0A.
 - a. If efficiency measurements are desired, an ammeter can be put in series with the output load in order to measure the DC2234A's output current.

- b. A voltmeter can be placed across the output terminals in order to get an accurate output voltage measurement.

6. Turn on the power at the input.

NOTE: If there is no output, temporarily disconnect the load to make sure that the load is not set too high.

7. Once the proper output voltage is again established, adjust the load and/or input within the operating range and observe the output voltage regulation, ripple voltage, efficiency and other desired parameters.
8. An external clock can be added to the SYNC terminal when SYNC function is used (JP1 on the SYNC position). Please ensure that the chosen RT sets the LT8711 switching frequency to equal or below the lowest SYNC frequency. See the data sheet section, Clock Synchronization.

QUICK START PROCEDURE




Figure 1. Efficiency vs Load Current at 200kHz Switching Frequency




Figure 2. DC2234A Temperature Rising vs Input Voltage

QUICK START PROCEDURE




Figure 3. Proper Measurement Equipment Setup




Figure 4. Measuring Output Ripple




Figure 5. DC2234A 12V Input 2A to 4A Load Transient

PARTS LIST


| ITEM | QTY | REFERENCE | PART DESCRIPTION | MANUFACTURER/PART NUMBER |
|---|-----|--------------------------------|---------------------------------------|---------------------------------|
| Required Circuit Components | | | | |
| 1 | 6 | C2, C3, C4, CIN2, CIN3, CIN4 | CAP, X7R, 10µF, 50V, 10% 1210 | MURATA, GRM32ER71H106KA12L |
| 2 | 1 | C01 | ALUM, POLYMER, 270µF, 16V, 20% | PANASONIC, 16SVPC270M |
| 3 | 3 | C02, C03, C04 | CAP, X7R, 22µF, 25V, 10% 1210 | MURATA, GRM32ER71E226KE15L |
| 4 | 1 | C07 | CAP, X7R, 10µF, 25V, 10% 1206 | MURATA, GRM31CR71E106KA12L |
| 5 | 1 | C7 | CAP, X7R, 10nF, 25V, 10% 0603 | MURATA, GRM188R71E103KA01D |
| 6 | 4 | C11, C14, C18, C22 | CAP, X7R, 2.2µF, 16V, 10% 0805 | MURATA, GRM21BR71C225KA12L |
| 7 | 1 | C13 | CAP, X7R, 4.7µF, 50V, 10% 1206 | TDK, C3216X7R1H475K160AC |
| 8 | 1 | C15 | CAP, X7R, 4.7nF, 25V, 10% 0603 | MURATA, GRM188R71E472KA01D |
| 9 | 1 | C16 | CAP, C0G, 100pF, 50V, 5% 0603 | TDK, C1608C0G1H101J080AA |
| 10 | 1 | C17 | CAP, X7R, 0.47µF 16V 10% 0603 | MURATA, GRM188R71C474KA88D |
| 11 | 1 | C19 | CAP, X7R, 1000pF, 100V, 10% 1206 | MURATA, GRM319R72A102KA01D |
| 12 | 1 | D1 | DIODE, 60V, 2A, POWERDI-123 | DIODES INC, DFLS260-7 |
| 13 | 1 | D2 | DIODE, 80V, 125mA, SOD-523 | DIODES INC, 1N4148WT-7 |
| 14 | 1 | L2 | IND, 8.2µH | COILCRAFT, XAL1510-822MEB |
| 15 | 1 | L3 | IND, 15µH | COILCRAFT, XAL1510-153MEB |
| 16 | 1 | MN1 | N-MOSFET, 80V, POWERPAK SO-8 | VISHAY, SIR826ADP-T1-GE3 |
| 17 | 1 | MP1 | P-MOSFET, 60V, POWERFLAT 5x6 | STMicroelectronics, STL42P6LLF6 |
| 18 | 2 | R1, R3 | RES, SENSE, 0.002Ω, 1.5W, 2%, KRL3216 | SUSUMU, KRL3216E-C-R002-G-T5 |
| 19 | 6 | R5, R9, R12, R14, R18, R19 | RES, CHIP, 0Ω, 0.1W, 0603 | NIC, NRC06ZOTRF |
| 20 | 1 | R6 | RES, CHIP, 3.3Ω, 0.1W, 1%, 0603 | VISHAY, CRCW06033R30FKEA |
| 21 | 2 | R7, R15 | RES, CHIP, 10Ω, 0.1W, 1%, 0603 | VISHAY, CRCW060310R0FKEA |
| 22 | 1 | R13 | RES, CHIP, 1M, 0.1W, 1%, 0603 | VISHAY, CRCW06031M00FKEA |
| 23 | 1 | R16 | RES, CHIP, 71.5k, 0.1W, 1%, 0603 | VISHAY, CRCW060371K5FKEA |
| 24 | 2 | R17,R23 | RES, CHIP, 100k, 0.1W, 1%, 0603 | NIC, NRC06F1003TRF |
| 25 | 1 | R21 | RES, CHIP, 118k, 0.1W, 1%, 0603 | NIC, NRC06F1183TRF |
| 26 | 1 | R22 | RES, CHIP, 49.9k, 0.1W, 1%, 0603 | VISHAY, CRCW060349K9FKEA |
| 27 | 1 | R24 | RES, CHIP, 3.3Ω, 1/2W, 5%, 1210 | VISHAY, CRCW12103R30JNEA |
| 28 | 1 | U1 | IC, LT8711EFE 20-LEAD TSSOP | LINEAR TECH, LT8711EFE#PBF |
| Additional Demo Board Circuit Components | | | | |
| 1 | 1 | CIN1 | EP-CAP, 56µF, 50V, HVH SERIES | SUN ELECT, 50HVH56M |
| 2 | 0 | CIN5, CIN6, C05, C06, C20(OPT) | CAP, 1210 | |
| 3 | 0 | C1 (OPT) | CAP, 2220 | |
| 4 | 0 | C6, C8, C9, C10, C12, C21(OPT) | CAP, 0603 | |
| 5 | 0 | L1 (OPT) | IND, 8.2µH | |
| 6 | 0 | MN2 (OPT) | N-MOSFET, POWERPAK SO-8 | |
| 7 | 0 | MP2 (OPT) | P-MOSFET, POWERFLAT 5x6 | |
| 8 | 0 | R4 (OPT) | RES, 1210 | |
| 9 | 0 | R20 (OPT) | RES, 0603 | |

DEMO MANUAL DC2234A

PARTS LIST

| ITEM | QTY | REFERENCE | PART DESCRIPTION | MANUFACTURER/PART NUMBER |
|--------------------------------------|-----|------------|--------------------------------|-----------------------------------|
| Hardware: For Demo Board Only | | | | |
| 1 | 11 | E1 TO E11 | TESTPOINT, TURRET, 0.094" | MILL-MAX, 2501-2-00-80-00-00-07-0 |
| 2 | 1 | JP1 | DOUBLE ROW HEADER 2 x 3 0.079" | WURTH ELEKTRONIK, 62000621121 |
| 3 | 1 | XJP1 | SHUNT, 0.079" CENTER | WURTH ELEKTRONIK, 60800213421 |
| 4 | 4 | MH1 TO MH4 | STAND-OFF, NYLON 0.50" TALL | KEYSTONE, 8833 (SNAP ON) |

SCHEMATIC DIAGRAM



NOTE: UNLESS OTHERWISE SPECIFIED
 1. ALL RESISTORS ARE 0603.
 ALL SMD CAPACITORS ARE 0603.

DEMO MANUAL DC2234A

DEMONSTRATION BOARD IMPORTANT NOTICE

Linear Technology Corporation (LTC) provides the enclosed product(s) under the following **AS IS** conditions:

This demonstration board (DEMO BOARD) kit being sold or provided by Linear Technology is intended for use for **ENGINEERING DEVELOPMENT OR EVALUATION PURPOSES ONLY** and is not provided by LTC for commercial use. As such, the DEMO BOARD herein may not be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including but not limited to product safety measures typically found in finished commercial goods. As a prototype, this product does not fall within the scope of the European Union directive on electromagnetic compatibility and therefore may or may not meet the technical requirements of the directive, or other regulations.

If this evaluation kit does not meet the specifications recited in the DEMO BOARD manual the kit may be returned within 30 days from the date of delivery for a full refund. **THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY THE SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THIS INDEMNITY, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.**

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user releases LTC from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge. Also be aware that the products herein may not be regulatory compliant or agency certified (FCC, UL, CE, etc.).

No License is granted under any patent right or other intellectual property whatsoever. **LTC assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or any other intellectual property rights of any kind.**

LTC currently services a variety of customers for products around the world, and therefore this transaction **is not exclusive**.

Please read the DEMO BOARD manual prior to handling the product. Persons handling this product must have electronics training and observe good laboratory practice standards. **Common sense is encouraged.**

This notice contains important safety information about temperatures and voltages. For further safety concerns, please contact a LTC application engineer.

Mailing Address:

Linear Technology
1630 McCarthy Blvd.
Milpitas, CA 95035

Copyright © 2004, Linear Technology Corporation

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: ocean@oceanchips.ru

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А