

- ◆ 2ch DC/DC Controller (Step-Down + Inverting)
- ◆ Input Voltage Range 2.0V ~ 10.0V
- ◆ Output Voltage Externally Set-Up
- ◆ Oscillation Frequency 180kHz ( $\pm 15\%$ )
- ◆ Max Duty Ratio Step-Down : 100%  
Inverting : 80% (Typ.)
- ◆ PWM, PWM/PFM Switching Control
- ◆ MSOP-10 Package

## ■ Applications

- PDAs
- Palm Top Computers
- Portable Audio Systems
- Various Multi-function Power Supplies

## ■ Features

### 2ch. DC/DC Controllers

Output 1: Step-Down DC/DC Controller  
Output 2: Inverting DC/DC Controller

**Power Supply Voltage Range** 2.0V ~ 10V

### Output Voltage Range

Output 1: 0.9V ~ 6.0V  
(Step-Down DC/DC Controller) Can be set freely with 0.9V( $\pm 2.0\%$ ) of reference voltage supply & external components

Output 2: -30V ~ 0V  
(Inverting DC/DC Controller) Can be set freely with 0.9V( $\pm 2.0\%$ ) of reference voltage & external components

### Oscillation Frequency

180kHz  $\pm 15\%$

300kHz & 500kHz are available as custom

**Output Current** Output 1 : more than 1000mA (VIN=5.0V,VOUT=3.3V)  
Output 2 : more than - 100mA (VIN=5.0V,VOUT=-7.5V)


### Soft-Start Internally Set-Up (Output 1)

**Stand-By Current** 3.0 $\mu$ A (MAX)

## ■ Typical Performance Characteristics

XC9505B092A (180kHz,VOUT1:3.3V,VOUT2:-7.5V)

Tr1,Tr2:XP162A12A6P, CL1, CL2=92uF(Tantalum),SD1:CMS02  
SD2:MA2Q737,L1=47uH(CDRH6D28),L2=22uH(CDRH5D28)



## ■ General Description

The XC9505 series are PWM control, PWM/PFM switching, 2 channel (step-down and inverting) DC/DC controller ICs. With 0.9V of standard voltage supply internal, and using externally connected components, the output 1 voltage (step-down DC/DC controller) can be set freely within a range of 0.9V ~ 6.0V. Since output 2 (inverting DC/DC controller) has a built-in 0.9V reference voltage (accuracy  $\pm 2\%$ ), a negative voltage can be set with the external components.

With a 180kHz frequency, the size of the external components can be reduced. Switching frequencies of 300kHz and 500kHz are also available as custom-designed products.

The control of the XC9505 series can be switched between PWM control and PWM/PFM automatic switching control using external signals. Control switches from PWM to PFM during light loads when automatic switching is selected and the series is highly efficient from light loads through to large output currents. Noise is easily reduced with PWM control since the frequency is fixed.


The series gives freedom of control selection so that control suited to the application can be selected.

Soft-start time is internally set to 10msec (output 1)


which offers protection against rush currents and voltage overshoot when the power is switched on .

## ■ Typical Application

(XC9505B092A Input: 2 Cell, Output ①: 3.3V, Output ②: -7.5V )



## ■ Pin Configuration



MSOP-10  
(TOP VIEW)

## ■ Pin Assignment


PIN NUMBER	PIN NAME	FUNCTIONS
1	EXT 1	Channel 1: External Transistor Drive Pin <Connected to Pch Power MOSFET Gate>
2	VDD	Supply Voltage
3	FB1	Channel 1 : Output Voltage Monitor Feedback Pin <Threshold value : 0.9V. Output voltage can be set freely by connecting split resistors between VOUT1 and Ground.>
4	PWM1	Channel 1 : PWM/PFM Switching Pin <Control Output 1. PWM control when connected to VDD, PWM / PFM auto switching when connected to Ground. >
5	EN1	Channel 1 : Enable Pin <Connected to Ground when Output 1 is in stand-by mode. Connected to VDD when Output 1 is active. EXT1 is high when in stand-by mode.>
6	EN2	Channel 2 : Enable Pin <Connected to Ground when Output 2 is in stand-by mode. Connected to VDD when Output 2 is active. EXT2/ is high when in stand-by mode.>
7	PWM2	Channel 2 : PWM/PFM Switching Pin <Control Output 2. PWM control when connected to VDD, PWM / PFM auto switching when connected to Ground.>
8	FB2	Channel 2 : Output Voltage Monitor Feedback Pin <Threshold value : 0.9V. Output voltage can be set freely by connecting split resistors between VOUT2 and VOUT1.>
9	GND	Ground
10	EXT2/	Channel 2 : External Transistor Drive Pin <Connected to Pch Power MOSFET Gate>

## ■ Ordering Information

XC9505①②③④⑤⑥

DESIGNATOR	SYMBOL	DESCRIPTION	
①	B	Standard (10 Pin)	
②	0	FB Voltage	
③	9	0.9V	
④		Oscillation Frequency	
	2	180kHz	
	3	300kHz (custom)	
	5	500kHz (custom)	
⑤	A	Package	MSOP-10
⑥	R	Embossed Tape	Standard Feed
	L	Embossed Tape	Reverse Feed

## ■ Block Diagram



## ■ Absolute Maximum Ratings

Ta=25°C			
PARAMETER	SYMBOL	RATINGS	UNITS
VDD Pin Voltage	VDD	- 0.3 ~ 12	V
FB1, 2 Pin Voltage	VFB	- 0.3 ~ 12	V
EN1, 2 Pin Voltage	VEN	- 0.3 ~ 12	V
PWM1,2 Pin Voltage	VPWM	- 0.3 ~ 12	V
EXT1, 2 Pin Voltage	VEXT	- 0.3 ~ VDD + 0.3	V
EXT1, 2 Pin Current	IEXT	± 100	mA
Power Dissipation	Pd	150	mW
Operating Ambient Temperature	Topr	- 40 ~ + 85	°C
Storage Temperature	Tstg	- 55 ~ + 125	°C

## ■ Electrical Characteristics

XC9505B092A		Common Characteristics		Ta=25°C				
PARAMETER	SYMBOL	CONDITIONS		MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT
Supply Voltage	VDD			2.0	-	10.0	V	
Output Voltage Range (note 1)	VOUTSET	VDD ≥ 2.0V, IOUT1, 2=1mA	VOUT1	0.9	-	VIN	V	①
			VOUT2	-	-	0.0		
Supply Current 1	IDD1	FB=0V, FB2=1.2V		-	80	160	μA	②
Supply Current 1-1	IDD1-1	EN1=3.0V, EN2=0, FB1=0V		-	50	110	μA	②
Supply Current 1-2	IDD1-2	EN2=3.0V, EN1=0, FB2=1.2V		-	60	120	μA	②
Supply Current 1-3	IDD1-3	FB1=0V, FB2=0V		-	70	120	μA	②
Supply Current 1-4	IDD1-4	FB1=1.2V, FB2=1.2V		-	80	150	μA	②
Supply Current 2	IDD2	FB1=1.2V, FB2=0V		-	70	130	μA	②
Stand-by Current	ISTB	Same as IDD1, EN1=EN2=0V		-	1.0	3.0	μA	②
Oscillation Frequency	FOSC	Same as IDD1		153	180	207	kHz	②
EN1, 2 "High" Voltage	VENH	FB1=0V, FB2=3.0V		0.65	-	-	V	②
EN1, 2 "Low" Voltage	VENL	FB1=0V, FB2=3.0V		-	-	0.20	V	②
EN1, 2 "High" Current	IENH	FB1=3.0V, FB2=0V		-	-	0.50	μA	②
EN1, 2 "Low" Current	IENL	EN1, 2=0V, FB1=3.0V, FB2=0V		-	-	-0.50	μA	②
PWM1, 2 "High" Current	IPWMH	FB1=3.0V, FB2=0V, PWM1, 2=3.0V		-	-	0.50	μA	②
PWM1, 2 "Low" Current	IPWML	FB1=3.0V, FB2=0V, PWM1, 2=0V		-	-	-0.50	μA	②
FB1, 2 "High" Current	IFBH	FB1=3.0V, FB2=0.8V		-	-	0.50	μA	②
FB1, 2 "Low" Current	VFB1	FB1=1.0V, FB2=0V		-	-	-0.50	μA	②

Unless otherwise stated, VDD=3.0V, PWM1, 2=3.0V, EN1, 2 = 3.0V

Output 1 Characteristics		Step-Down Controller					Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT	
FB1 Voltage	VFB1	VDD=3.0V, VIN=1.5V, IOUT1=10mA	0.882	0.900	0.918	V	③	
Minimum Operating Voltage	VINmin1		-	-	2	V	①	
Maximum Duty Ratio1	MINDTY1	Same as IDD1	100	-	-	%	②	
Minimum Duty Ratio1	MAXDTY2	Same as IDD2	-	-	-	%	②	
PFM Duty Ratio1	PFMDTY1	No Load, VPWM1=0V	22	30	38	%	④	
Efficiency1 (note 2)	EFFI1	IOUT1= 250mA, Pch MOSFET: XP162A12A6P	-	92	-	%	④	
Soft-Start Time1	TSS1	VOUT1 × 0.95V, EN1=0V→0.65V	5.0	10.0	20.0	msec	④	
EXT1 "High" ON Resistance	REXTBH1	FB1=0V, EXT1=VDD -0.4V	-	28	47	Ω	⑤	
EXT1 "Low" ON Resistance	REXTBL1	EN1=FB1=1.2V, EXT1=0.4V	-	22	30	Ω	⑤	
PWM1 "High" Voltage	VPWMH1	No Load	0.65	-	-	V	④	
PWM1 "Low" Voltage	VPWML1	No Load	-	-	0.20	V	④	

Unless otherwise stated, VDD=EN1=PWM1=3.0V, EN2=PWM2=GND, EXT2=OPEN, FB2=OPEN, VIN=1.8V

Output 2 Characteristics		Inverting DC/DC Controller					Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT	
FB2 Voltage	VFB2	VDD=3.0V	0.882	0.900	0.918	V	②	
Operation Start-up Voltage2	VST1-2	IOUT2=1.0mA, RFB11=200kΩ, RFB12=75kΩ	-	-	2.0	V	①	
		RFB21=17.5kΩ, RFB22=10kΩ, EN1=PWM1=3.0V						
Oscillation Start-up Voltage2	VST2-2	FB2=1.2V	-	-	2.0	V	②	
Maximum Duty Ratio2	MAXDTY2	Same as IDD1	75	80	87	%	②	
Minimum Duty Ratio2	MINDTY3	Same as IDD2	-	-	0	%	②	
PFM Duty Ratio2	PFMDTY2	No Load, VPWM2=0V	22	30	38	%	⑥	
Efficiency2 (Note 2)	EFFI2	IOUT2= -150mA, Pch MOSFET: XP162A12A6P	-	76	-	%	⑥	
EXT2 "High" ON Resistance	REXTBH2	EN2=FB2= 0V, EXT2=VDD-0.4V	-	28	47	Ω	⑤	
EXT2 "Low" ON Resistance	REXTBL2	FB2=3.0V, EXT2=0.4V	-	22	30	Ω	⑤	
PWM2 "High" Voltage	VPWMH2	No Load	0.65	-	-	V	⑥	
PWM2 "Low" Voltage	VPWML2	No Load	-	-	0.20	V	⑥	

Unless otherwise stated, VDD=EN2=PWM2=3.0V, PWM1=EN1=GND, EXT1=OPEN, FB1=OPEN, VIN=3.0V

3) Please be careful not to exceed the breakdown voltage level of the peripheral parts.

4)  $EFFI1, 2 = \{ [(\text{Output voltage}) \times (\text{Output current})] / [(\text{Input voltage}) \times (\text{Input Current})] \} \times 100$

## ■ Electrical Characteristics

XC9505B093A		Common Characteristics				Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT
Supply Voltage	VDD		2.0	-	10.0	V	
Output Voltage Range (note 1)	VOUTSET	VDD ≥ 2.0V, IOUT1, 2=1mA	VOUT1	0.9	-	VIN	①
			VOUT2	-	-	0.0	
Supply Current 1	IDD1	FB=0V, FB2=1.2V	-	100	190	μA	②
Supply Current 1-1	IDD1-1	EN1=3.0V, EN2=0, FB1=0V	-	60	120	μA	②
Supply Current 1-2	IDD1-2	EN2=3.0V, EN1=0, FB2=1.2V	-	80	150	μA	②
Supply Current 1-3	IDD1-3	FB1=0V, FB2=0V	-	80	140	μA	②
Supply Current 1-4	IDD1-4	FB1=1.2V, FB2=1.2V	-	100	180	μA	②
Supply Current 2	IDD2	FB1=1.2V, FB2=0V	-	80	150	μA	②
Stand-by Current	ISTB	Same as IDD1, EN1=EN2=0V	-	1.0	3.0	μA	②
Oscillation Frequency	FOSC	Same as IDD1	255	300	345	KHz	②
EN1, 2 "High" Voltage	VENH	FB1=0V, FB2=3.0V	0.65	-	-	V	②
EN1, 2 "Low" Voltage	VENL	FB1=0V, FB2=3.0V	-	-	0.20	V	②
EN1, 2 "High" Current	IENH	FB1=3.0V, FB2=0V	-	-	0.50	μA	②
EN1, 2 "Low" Current	IENL	EN1, 2=0V, FB1=3.0V, FB2=0V	-	-	-0.50	μA	②
PWM1, 2 "High" Current	IPWMH	FB1=3.0V, FB2=0V, PWM1, 2=3.0V	-	-	0.50	μA	②
PWM1, 2 "Low" Current	IPWML	FB1=3.0V, FB2=0V, PWM1, 2=0V	-	-	-0.50	μA	②
FB1, 2 "High" Current	IFBH	FB1=3.0V, FB2=0.8V	-	-	0.50	μA	②
FB1, 2 "Low" Current	VFB1	FB1=1.0V, FB2=0V	-	-	-0.50	μA	②

Unless otherwise stated, VDD=3.0V, PWM1, 2=3.0V, EN1, 2 = 3.0V

Output 1 Characteristics		Step-Down Controller				Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT
FB1 Voltage	VFB1	VDD=3.0V, VIN=1.5V, IOUT1=10mA	0.882	0.900	0.918	V	③
Minimum Operating Voltage	VINmin1		-	-	2.0	V	①
Maximum Duty Ratio1	MINDTY1	Same as IDD1	-	-	100	%	②
Minimum Duty Ratio1	MAXDTY2	Same as IDD2	-	-	-	%	②
PFM Duty Ratio1	PFMDTY1	No Load, VPWM1=0V	22	30	38	%	④
Efficiency1 (note 2)	EFFI1	IOUT1= 250mA, Pch MOSFET: XP162A12A6P	-	92	-	%	④
Soft-Start Time1	TSS1	VOUT1 × 0.95V, EN1=0V→0.65V	5.0	10.0	20.0	msec	④
EXT1 "High" ON Resistance	REXTBH1	FB1=0V, EXT1=VDD -0.4V	-	28	47	Ω	⑤
EXT1 "Low" ON Resistance	REXTBL1	EN1=FB1=1.2V, EXT1=0.4V	-	22	30	Ω	⑤
PWM1 "High" Voltage	VPWMH1	No Load	0.65	-	-	V	④
PWM1 "Low" Voltage	VPWML1	No Load	-	-	0.20	V	④

Unless otherwise stated, VDD=EN1=PWM1=3.0V, EN2=PWM2=GND, EXT2=OPEN, FB2=OPEN, VIN=1.8V

Output 2 Characteristics		Inverting DC/DC Controller				Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT
FB2 Voltage	VFB2	VDD=3.0V	0.882	0.900	0.918	V	②
Operation Start-up Voltage2	VST1-2	IOUT2=1.0mA, RFB11=200kΩ, RFB12=75kΩ	-	-	2.0	V	①
		RFB21=17.5kΩ, RFB22=10kΩ, EN1=PWM1=3.0V					
Oscillation Start-up Voltage2	VST2-2	FB2=1.2V	-	-	2.0	V	②
Maximum Duty Ratio2	MAXDTY2	Same as IDD1	75	80	87	%	②
Minimum Duty Ratio2	MINDTY3	Same as IDD2	-	-	0	%	②
PFM Duty Ratio2	PFMDTY2	No Load, VPWM2=0V	22	30	38	%	⑥
Efficiency2 (Note 2)	EFFI2	IOUT2= -150mA, Pch MOSFET: XP162A12A6P	-	75	-	%	⑥
EXT2 "High" ON Resistance	REXTBH2	EN2=FB2= 0V, EXT2=VDD-0.4V	-	28	47	Ω	⑤
EXT2 "Low" ON Resistance	REXTBL2	FB2=3.0V, EXT2=0.4V	-	22	30	Ω	⑤
PWM2 "High" Voltage	VPWMH2	No Load	0.65	-	-	V	⑥
PWM2 "Low" Voltage	VPWML2	No Load	-	-	0.20	V	⑥

Unless otherwise stated, VDD=EN2=PWM2=3.0V, PWM1=EN1=GND, EXT1=OPEN, FB1=OPEN, VIN=3.0V

3) Please be careful not to exceed the breakdown voltage level of the peripheral parts.

4)  $EFFI1, 2 = \{ [(\text{Output voltage}) \times (\text{Output current})] / [(\text{Input voltage}) \times (\text{Input Current})] \} \times 100$

## ■ Electrical Characteristics

XC9505B095A		Common Characteristics				Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT
Supply Voltage	VDD		2.0	-	10.0	V	
Output Voltage Range (note 1)	VOUTSET	VDD ≥ 2.0V, IOUT1, 2=1mA	VOUT1	0.9	-	-	①
			VOUT2	-	-	0.0	
Supply Current 1	IDD1	FB=0V, FB2=1.2V	-	130	250	μA	②
Supply Current 1-1	IDD1-1	EN1=3.0V, EN2=0, FB1=0V	-	80	150	μA	②
Supply Current 1-2	IDD1-2	EN2=3.0V, EN1=0, FB2=1.2V	-	110	220	μA	②
Supply Current 1-3	IDD1-3	FB1=0V, FB2=0V	-	100	170	μA	②
Supply Current 1-4	IDD1-4	FB1=1.2V, FB2=1.2V	-	140	230	μA	②
Supply Current 2	IDD2	FB1=1.2V, FB2=0V	-	100	190	μA	②
Stand-by Current	ISTB	Same as IDD1, EN1=EN2=0V	-	1.0	3.0	μA	②
Oscillation Frequency	FOSC	Same as IDD1	425	500	575	KHz	②
EN1, 2 "High" Voltage	VENH	FB1=0V, FB2=3.0V	0.65	-	-	V	②
EN1, 2 "Low" Voltage	VENL	FB1=0V, FB2=3.0V	-	-	0.20	V	②
EN1, 2 "High" Current	IENH	FB1=3.0V, FB2=0V	-	-	0.50	μA	②
EN1, 2 "Low" Current	IENL	EN1, 2=0V, FB1=3.0V, FB2=0V	-	-	-0.50	μA	②
PWM1, 2 "High" Current	IPWMH	FB1=3.0V, FB2=0V, PWM1, 2=3.0V	-	-	0.50	μA	②
PWM1, 2 "Low" Current	IPWML	FB1=3.0V, FB2=0V, PWM1, 2=0V	-	-	-0.50	μA	②
FB1, 2 "High" Current	IFBH	FB1=3.0V, FB2=0.8V	-	-	0.50	μA	②
FB1, 2 "Low" Current	VFB1	FB1=1.0V, FB2=0V	-	-	-0.50	μA	②

Unless otherwise stated, VDD=3.0V, PWM1, 2=3.0V, EN1, 2 = 3.0V

Output 1 Characteristics		Step-Down Controller				Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT
FB1 Voltage	VFB1	VDD=3.0V, VIN=1.5V, IOUT1=10mA	0.882	0.900	0.918	V	③
Minimum Operating Voltage	VINmin1		-	-	2.0	V	①
Maximum Duty Ratio1	MINDTY1	Same as IDD1		-	100	%	②
Minimum Duty Ratio1	MAXDTY2	Same as IDD2	-	-	-	%	②
PFM Duty Ratio1	PFMDTY1	No Load, VPWM1=0V	22	30	38	%	④
Efficiency1 (note 2)	EFFI1	IOUT1= 250mA, Pch MOSFET: XP162A12A6P	-	91	-	%	④
Soft-Start Time1	TSS1	VOUT1 × 0.95V, EN1=0V→0.65V	5.0	10.0	20.0	msec	④
EXT1 "High" ON Resistance	REXTBH1	FB1=0V, EXT1=VDD -0.4V	-	28	47	Ω	⑤
EXT1 "Low" ON Resistance	REXTBL1	EN1=FB1=1.2V, EXT1=0.4V	-	22	30	Ω	⑤
PWM1 "High" Voltage	VPWMH1	No Load	0.65	-	-	V	④
PWM1 "Low" Voltage	VPWML1	No Load	-	-	0.20	V	④

Unless otherwise stated, VDD=EN1=PWM1=3.0V, EN2=PWM2=GND, EXT2=OPEN, FB2=OPEN, VIN=1.8V

Output 2 Characteristics		Inverting DC/DC Controller				Ta=25°C	
PARAMETER	SYMBOL	CONDITIONS	MIN.	TYP.	MAX.	UNITS	TEST CIRCUIT
FB2 Voltage	VFB2	VDD=3.0V	0.882	0.900	0.918	V	②
Operation Start-up Voltage2	VST1-2	IOUT2=1.0mA, RFB11=200kΩ, RFB12=75kΩ	-	-	2.0	V	①
		RFB21=17.5kΩ, RFB22=10kΩ, EN1=PWM1=3.0V					
Oscillation Start-up Voltage2	VST2-2	FB2=1.2V	-	-	2.0	V	②
Maximum Duty Ratio2	MAXDTY2	Same as IDD1	75	80	87	%	②
Minimum Duty Ratio2	MINDTY3	Same as IDD2	-	-	0	%	②
PFM Duty Ratio2	PFMDTY2	No Load, VPWM2=0V	22	30	38	%	⑥
Efficiency2 (Note 2)	EFFI2	IOUT2= -150mA, Pch MOSFET: XP162A12A6P	-	71	-	%	⑥
EXT2 "High" ON Resistance	REXTBH2	EN2=FB2= 0V, EXT2=VDD-0.4V	-	28	47	Ω	⑤
EXT2 "Low" ON Resistance	REXTBL2	FB2=3.0V, EXT2=0.4V	-	22	30	Ω	⑤
PWM2 "High" Voltage	VPWMH2	No Load	0.65	-	-	V	⑥
PWM2 "Low" Voltage	VPWML2	No Load	-	-	0.20	V	⑥

Unless otherwise stated, VDD=EN2=PWM2=3.0V, PWM1=EN1=GND, EXT1=OPEN, FB1=OPEN, VIN=3.0V

3) Please be careful not to exceed the breakdown voltage level of the peripheral parts.

4)  $EFFI1, 2 = \{ [(\text{Output voltage}) \times (\text{Output current})] / [(\text{Input voltage}) \times (\text{Input Current})] \} \times 100$

## ■ Operational Description

The XC9505 series are dual DC/DC (step-down + inverting) converter controller ICs with built-in high speed, low ON resistance buffers.

### <Error Amp. 1>

Error Amplifier 1 is designed to monitor the output voltage and it compares the feedback voltage 1 (FB1) with the reference voltage Vref1. In response to feedback of a voltage lower than the reference voltage Vref1, the output voltage of the error amp. decreases.

### <Error Amp. 2>

Error Amplifier 2 is designed to monitor the output voltage and it compares the feedback voltage 2 (FB2) with the reference voltage Vref 2. In response to feedback of a voltage lower than the reference voltage Vref2, the output voltage of the error amp. decreases.

### <OSC Generator>

This circuit generates the internal reference clock.

### <Ramp Wave Generator 1, 2>

The Ramp Wave Generator generates a saw-tooth waveform based on outputs from the OSC Generator.

### <PWM Comparator 1, 2>

The PWM Comparator compares outputs from the Error Amp. and saw-tooth waveform. When the voltage from the Error Amp's output is low, the external switch will be set to ON.

### <PWM/PFM Controller 1, 2>

This circuit generates PFM pulses.

Control can be switched between PWM control and PWM/PFM automatic switching control using external signals.

The PFM/PWM automatic switching mode is selected when the voltage of the PWM1 (2) pin is less than 0.2V, and the control switches between PWM and PFM automatically depending on the load. As the PFM circuit generates pulses based on outputs from the PWM Comparator, shifting between modes occurs smoothly. PWM control mode is selected when the voltage of the PWM1 (2) pin is more than 0.65V. Noise is easily reduced with PWM control since the switching frequency is fixed.

Control suited to the application can easily be selected which is useful in audio applications, for example, where traditionally, efficiencies have been sacrificed during stand-by as a result of using PWM control (due to the noise problems associated with the PFM mode in stand-by).

### <Vref 1 with Soft Start 1>

The reference voltage, Vref1(FB1 pin voltage)=0.9V, is adjusted and fixed by laser trimming (for output voltage settings, please refer to the functional settings notes on page 9.). To protect against inrush current, when the power is switched on, and also to protect against voltage overshoot, soft-start time is set internally to 10ms. It should be noted, however, that this circuit does not protect the load capacitor (CL) from inrush current. With the Vref voltage limited, and depending upon the input to error amp 1, the operation maintains a balance between the two inputs of error amps and controls the EXT pin's ON time so that it doesn't increase more than is necessary.

### <Vref 2>

The reference voltage, Vref2 (FB2 pin voltage)=0.9V, is adjusted and fixed by laser trimming.

### <Enable Function 1,2>

This function controls the operation and shutdown of the IC. When the voltage of the EN1 or EN2 pins is 0.2V or less, the mode will be disable, the channel's operations will stop and the EXT1 and the EXT2 pin will be kept at a high level (the external P-type MOSFET will be OFF). When both EN1 and EN2 are in a state of chip disable, current consumption will be no more than 3.0 $\mu$ A. When the EN1 or EN2 pin's voltage is 0.65V or more, the mode will be enable and operations will recommence. With channel one (output 1) soft-start, 95% of the set output voltage will be reached within 10msec (TYP) from the moment of enable.

## ■ Functional Settings

### < Output Voltage Setting, Ch.1 (Step-up DC/DC Converter Controller) >

Output voltage can be set by adding external split resistors. Output voltage is determined by the following equation, based on the values of RFB11 and RFB12. The sum of RFB11 and RFB12 should normally be 1 MΩ or less.

$$VOUT1 = 0.9 \times (RFB11 + RFB12) / RFB12$$

The speed-up capacitor for phase compensation's (CFB1) value should be adjusted using the formula  $fzfb1 = 1/(2\pi \times CFB1 \times RFB11)$  so that it equals 12kHz. Depending on the application, the inductance value L, and the load capacity value CL, adjustments to this value are suggested so that the value is somewhere between 1kHz to 50kHz.

#### [Calculation Example]

When  $RFB11=220k\Omega$  and  $RFB12=75k\Omega$  :  $VOUT1=0.9 \times (200k+75k) / 75k=3.3V$ .

#### [Typical Example]

VOUT (V)	RFB11 (kΩ)	RFB12 (kΩ)	CFB1 (pF)	VOUT (V)	RFB11 (kΩ)	RFB12 (kΩ)	CFB1 (pF)
1.0	30	270	430	2.5	390	220	33
1.5	220	330	62	2.7	360	180	33
1.8	220	220	62	3.0	560	240	24
2.0	330	270	39	3.3	200	75	62
2.2	390	270	33	5.0	82	18	160

### < Output Voltage Setting, Ch.2 (Inverting DC/DC Converter) >

Output voltage can be set by adding reference voltage and split resistors externally. Output voltage is determined using the following equation and is based on the values of RFB21 and RFB22. The sum of RFB21 and RFB22 should normally be 500kΩ or less. The equation uses Ch 1's (VOUT1) output voltage calculation method for the reference voltage.

$$VOUT2 = (0.9 - VOUT1) \times (RFB21 / RFB22) + 0.9V$$

#### [Calculation Example]

When  $RFB21=17.5k\Omega$ ,  $RFB22=10k\Omega$ ,  $VOUT1=3.3V$ ,  $VOUT2= - 3.3V$

The value of speed-up capacitor for phase compensation CFB21 :

#### [Conditions: Heavy load (when coil current is continuous.)]

$$fzfb2 = 1/2 \times \pi \times CFB21 \times RFB21 = 10kHz$$


Depending on the application, the inductance value L, and the load capacity value CL, adjustments to this value are suggested so that the value is somewhere between 1kHz to 50kHz.

#### [Conditions: Light load (when coil current is discontinuous.)]

$$\text{Less than } CFB21=0.1\mu F$$


Depending on the application, the inductance value L, and the load capacity value CL, adjustments to this value are suggested.

### > Example Circuit 1 : Using voltage of Ch 1 (Step-Down)



Channel 1 (Step-Down) circuits should be enable by setting EN1 to High level so that a stable voltage is provided. Inrush current to the inverter when the supply voltage VDD of the IC is 2.0 V or higher can be controlled by setting EN 1 and EN 2 to enable ("H" level) simultaneously.

### > Example Circuit 1 : Using a positive regulator



A stable positive voltage produced by a positive-voltage regulator or by other means is usable.

$$VOUT2 = (0.9 - VR\_OUT) \times (RFB21 / RFB22) + 0.9V$$

## ■ External Components

**Conditions : Light load (when coil current is discontinuous.)**  
**Channel One (Step-Down DC/DC Converter Controller)**

**Tr 1 :** \* **MOSFET**  
XP152A12C0 (TOREX P-Channel Power MOSFET)  
Note : VGS Breakdown Voltage of this Tr. is 12V so please be careful with the power supply voltage.

SD 1 : CRS02 (Schottky , TOSHIBA)  
L1 : 10 $\mu$ H (SUMIDA, CDRH4D18C, TOKO, D412F, FOSC = 500kHz)  
15 $\mu$ H (SUMIDA, CDRH4D18C, TOKO, D412F, FOSC = 300kHz)  
22 $\mu$ H (SUMIDA, CDRH4D18C, TOKO, D412F, FOSC = 180kHz)  
CL1 : Please set so that the coil current is discontinuous.  
10V, 4.7 $\mu$ F (Ceramic)

\* **PNP Tr**  
RB1 : 2SA1213 (TOSHIBA)  
500 $\Omega$  Adjust in accordance with load & Tr.'s HFE  
RB1 $\leq$  (VIN-0.7) x (hFE/IC-REXTBL)  
CB1 : 2200pF (Ceramic)  
CB1 $\leq$  (2 $\pi$  x RB2 x FOSC x 0.7)

**Conditions: Heavy load (when coil current is continuous.)**  
**Channel One (Step-Down DC/DC Converter Controller)**

**Tr 1 :** \* **MOSFET**  
XP162A12A6P (TOREX P-Channel Power MOSFET)  
Note : VGS Breakdown Voltage of this Tr. is 12V so please be careful with the power supply voltage.

SD 1 : MA2Q737 (Schottky , MATSUSHITA)  
CMS02 (Schottky , TOSHIBA)  
L1 : 10 $\mu$ H (SUMIDA, CDRH5D28, FOSC = 500kHz)  
22 $\mu$ H (SUMIDA, CDRH5D28, FOSC = 300kHz)  
47 $\mu$ H (SUMIDA, CDRH5D28, FOSC = 180kHz)  
CL1 : 16V, 47 $\mu$ F (Tantalum)  
Increase capacity according to the equation below when the step-up voltage ratio is large and output current is high.

$$CL = (CL \text{ standard value}) \times (IOUT1 (\text{mA}) / 500\text{mA} \times VOUT1 / VIN)$$

\* **PNP Tr**  
RB1 : 2SA1213 (TOSHIBASANYO)  
500 $\Omega$  Adjust in accordance with load & Tr.'s HFE  
RB1 $\leq$  (VIN-0.7) x (hFE/IC-REXTBL)  
CB1 : 2200pF (Ceramic)  
CB1 $\leq$  (2 $\pi$  x RB2 x FOSC x 0.7)

## Channel Two (Inverter DC/DC Controller)

**Tr 2 :** \* **MOSFET**  
XP152A12C0 (TOREX P-Channel Power MOSFET)  
Note : VGS Breakdown Voltage of this Tr. is 12V so please be careful with the power supply voltage.

SD 2 : CRS02 (Schottky, TOSHIBA)  
L2 : 10 $\mu$ H (SUMIDA, CDRH4D18C, TOKO, D412F, FOSC = 500kHz)  
15 $\mu$ H (SUMIDA, CDRH4D18C, TOKO, D412F, FOSC = 300kHz)  
22 $\mu$ H (SUMIDA, CDRH4D18C, TOKO, D412F, FOSC = 180kHz)  
CL2 : Please set so that the coil current is discontinuous.  
10V, 4.7 $\mu$ F (Ceramic)

\* **PNP Tr**  
RB 2 : 2SA1213 (TOSHIBA)  
500 $\Omega$  Adjust in accordance with load & Tr.'s HFE  
RB2 $\leq$  (VIN-0.7) x (hFE/IC-REXTBL)  
CB 2 : 2200pF (Ceramic)  
CB2 $\leq$  (2 $\pi$  x RB2 x FOSC x 0.7)

## Channel Two (Inverter DC/DC Controller)

**Tr 2 :** \* **MOSFET**  
XP162A12A6P (TOREX P-Channel Power MOSFET)  
Note : VGS Breakdown Voltage of this Tr. is 12V so please be careful with the power supply voltage.

SD 2 : MA2Q737 (Schottky, MATSUSHITA)  
CRS02, CMS02 (Schottky , TOSHIBA)  
L2 : 10 $\mu$ H (SUMIDA, CDRH5D28, FOSC = 500kHz)  
15 $\mu$ H (SUMIDA, CDRH5D28, FOSC = 300kHz)  
22 $\mu$ H (SUMIDA, CDRH5D28, FOSC = 180kHz)  
CL2 : 16V, 47 $\mu$ F (Tantalum)  
Increase capacity according to the equation below when the step-up voltage ratio is large and output current is high.

$$CL = (CL \text{ standard value}) \times (IOUT2 (\text{mA}) / 150\text{mA} \times VOUT2 / VIN)$$

\* **PNP Tr**  
RB 2 : 2SA1213 (TOSHIBA)  
500 $\Omega$  Adjust in accordance with load & Tr.'s HFE  
RB2 $\leq$  (VIN-0.7) x (hFE/IC-REXTBL)  
CB 2 : 2200pF (Ceramic)  
CB2 $\leq$  (2 $\pi$  x RB2 x FOSC x 0.7)

## ■ Notes on how to use


### ○ Hint on application

#### 1. Channel 2 ( Inverting )      Soft start circuit

Channel 2 (inverting) is subject to the overshoot of output voltage 2 (VOUT 2) at start-up. It is possible to control the overshoot of output voltage 2 (VOUT 2), as shown by circuit example 1 in "Output Voltage Settings for Channel 2" in "Function Settings." In this circuit configuration, EN 1 and EN 2 are enabled (set to "H" level) simultaneously. This lets output voltage 1 (VOUT 1) of channel 1 increase gently as soft start, thereby controlling the overshoot.

> Example of typical application circuit : Improved Soft start

This example is effective when EN 1 and EN 2 are enabled with different timings under light load condition (the coil current being discontinuous).



Time to make soft start time is calculated by the equation below.

$$Time_{SS2} = -R_{FB21} \times C_{CFB21} / L_n \left[ 1 - \frac{(0.9 - V_{OUT2}) \times R_{FB22}}{(V_{OUT1} - 0.9) \times R_{FB21}} \right]$$

Example )

When VOUT1 = 3.3V and VOUT2 = -7.5V,

RFB21 = 350kΩ, RFB22 = 100kΩ by the equation below.

$$VOUT2 = (0.9 - VOUT1) \times (RFB21 / RFB22) + 0.9$$

When the light load, CFB21=0.1μF or lower value can be used.

Therefore, when CFB21=0.027μF,

$$Time_{ss2} = 5.0\text{mS}$$

and VOUT2 = 95% of setting value

#### 2. Channel 2 (Inverting)      Withstand voltage of transistor

The voltage applied between the drain and source is the sum of VIN and VOUT 2.


Select a transistor with an absolute VDSS rating that is suitable for your operating conditions.

Example: The voltage applied across VDS of a transistor will be 20.0V if VIN = 5.0 V and VOUT 2 = -15.0 V.


Under this condition, a transistor with VDSS higher than 20.0V should be selected. (Use a transistor with VDSS that is 1.5 times the applied voltage or more, as a standard.)

## ■ Test Circuits


Circuit 1




Circuit 2




Circuit 3




Circuit 4



Circuit 5



Circuit 6



■ External Components of the Test Circuits

**Circuits 1**

L1, L2: 22 $\mu$ H (SUMIDA CDRH5D28) : XC9505B092A  
 15 $\mu$ H (SUMIDA CDRH5D28) : XC9505B093A  
 10 $\mu$ H (SUMIDA CDRH5D28) : XC9505B095A  
 SD1, SD2 : CRS02 (Schottky, TOSHIBA)  
 EC10QS06 (Schottky, NIHON INTER)  
 CL1, CL2 : 16MCE476MD2 (Tantalum, NIHON CHEMICON)  
 35MCE335MB x 3 (Tantalum, NIHON CHEMICON)  
 CIN : 16MCE476MD2  
 PNP Tr 1 : 2SA1213 (TOSHIBA)  
 PNP Tr 2 : 2SA1213 (TOSHIBA)  
 RFB : Please use by the conditions as below.  
 RFB11 + RFB12  $\leq$  1M $\Omega$   
 RFB21 + RFB22  $\leq$  1M $\Omega$   
 RFB11 / RFB12 = (Setting Output Voltage / 0.9) - 1  
 $V_{OUT2} = (0.9 - V_{OUT1}) / (RFB21 / RFB22) + 0.9V$   
 CFB :  $f_{ZFB} = 1 / (2 \times \pi \times CFB1 \times RFB11) = 1\text{kHz}$  to 50kHz (12kHz usual)  
 $f_{ZFB} = 1 / (2 \times \pi \times CFB2 \times RFB21) = 1\text{kHz}$  to 50kHz (12kHz usual).

**Circuits 3**

L1 : 22 $\mu$ H (SUMIDA CDRH5D28)  
 SD 1 : MA2Q737 (Schottky, MATSUSHITA)  
 CL 1 : 16MCE476MD2 (Tantalum, NIHONCHEMICON)  
 CIN : 16MCE476MD2 (Tantalum, NIHONCHEMICON)  
 Pch MOSFET : XP162A12A6P (TOREX)

**Circuits 4**

L1 : 22 $\mu$ H (SUMIDA CDRH5D28) : XC9505B092A  
 15 $\mu$ H (SUMIDA CDRH5D28) : XC9505B093A  
 10 $\mu$ H (SUMIDA CDRH5D28) : XC9505B095A  
 SD 1 : MA2Q737 (Schottky, MATSUSHITA)  
 CL 1 : 16MCE476MD2 (Tantalum, NIHONCHEMICON)  
 CIN : 16MCE476MD2 (Tantalum, NIHONCHEMICON)  
 Pch MOSFET : XP162A12A6P (TOREX)

**Circuits 6**

L2 : 22 $\mu$ H (SUMIDA CDRH5D28) : XC9505B092A  
 15 $\mu$ H (SUMIDA CDRH5D28) : XC9505B093A  
 10 $\mu$ H (SUMIDA CDRH5D28) : XC9505B095A  
 SD 2 : MA2Q737 (Schottky, MATSUSHITA)  
 CL 2 : 16MCE476MD2 (Tantalum, NIHONCHEMICON)  
 CIN : 16MCE476MD2 (Tantalum, NIHONCHEMICON)  
 Pch MOSFET : XP162A12A6P (TOREX)

**■ Note on Use****1. Checking for Intermittent Oscillation**

The XC9505 series is subject to intermittent oscillation in the proximity of the maximum duty if the step-down ratio is low (e.g., from 4.2 V to 3.3 V) or a heavy load is applied where the duty ratio becomes high. Check waveforms at EXT under your operating conditions. A remedy for this problem is to raise the inductance of coil L or increase the load capacitance CL.

**2. PWM/PFM Automatic Switching**

If PWM/PFM automatic switching control is selected and the step-down ratio is high (e.g., from 10.0 V to 1.0 V), the control mode remains in PFM setting over the whole load range, since the duty ratio under continuous-duty condition is smaller than the PFM duty ratio of the XC9505series. The output voltage's ripple voltage becomes substantially high under heavy load conditions, with the XC9505 series appearing to be producing an abnormal oscillation. If this operation becomes a concern, set pins PWM to High to set the control mode to PWM setting. For use under the above-mentioned condition, measured data of PWM/PFM automatic switching control shown on the data sheets are available up to  $I_{OUT} = 100\text{ mA}$ .

**3. Ratings**


Use the XC9505 series and peripheral components within the limits of their ratings.

■ Typical Performance Characteristics


< 1ch Step-Down DC/DC Controller >

(1) Output Voltage vs. Output Current


**FOSC=180kHz, VOUT1=1.0V**




**FOSC=180kHz, VOUT1=1.0V**




**FOSC=180kHz, VOUT1=3.3V**




**FOSC=180kHz, VOUT1=5.0V**



**FOSC=300kHz, VOUT1=1.0V**









**FOCS=300kHz, VOUT1=1.0V**



\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)

## &lt; 1ch Step-Down DC/DC Controller &gt;







(1) Output Voltage vs. Output Current (Continued)

**FOSC=300kHz, VOUT1=1.8V****FOSC=300kHz, VOUT1=1.8V****FOSC=300kHz, VOUT1=2.5V****FOSC=300kHz, VOUT1=2.5V****FOSC=300kHz, VOUT1=3.3V****FOSC=300kHz, VOUT1=3.3V**

\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)

## &lt; 1ch Step-Down DC/DC Controller &gt;


(1) Output Voltage vs. Output Current (Continued)

**FOSC=300kHz, VOUT1=5.0V****FOSC=300kHz, VOUT1=5.0V****FOSC=500kHz, VOUT1=1.0V****FOSC=500kHz, VOUT1=1.0V****FOSC=500kHz, VOUT1=3.3V****FOSC=500kHz, VOUT1=3.3V**

\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)

## &lt; 1ch Step-Down DC/DC Controller &gt;

(1) Output Voltage vs. Output Current (Continued)


**FOSC=500kHz, VOUT1=5.0V**

\* When setting  $V_{OUT1}=1.0V$ ,  $V_{IN}=8.0V$  or  $10.0V$ ,  
 $CL=94\mu F$  (Tantalum) +  $100\mu F$  (OS Capacitor)


## &lt; 1ch Step-Down DC/DC Controller &gt;

(2) Efficiency vs. Output Current


FOSC=180kHz, VOUT1=1.0V




FOSC=180kHz, VOUT1=1.0V




FOSC=180kHz, VOUT1=3.3V




FOSC=180kHz, VOUT1=5.0V



FOSC=300kHz, VOUT1=1.0V



FOSC=300kHz, VOUT1=1.0V




\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)


## &lt; 1ch Step-Down DC/DC Controller &gt;

(2) Efficiency vs. Output Current (Continued)


FOSC=300kHz, VOUT1=1.8V




FOSC=300kHz, VOUT1=1.8V




FOSC=300kHz, VOUT1=2.5V




FOSC=300kHz, VOUT1=2.5V



FOSC=300kHz, VOUT1=3.3V



FOSC=300kHz, VOUT1=5.0V




\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)


## &lt; 1ch Step-Down DC/DC Controller &gt;

(2) Efficiency vs. Output Current (Continued)


FOSC=500kHz, VOUT1=1.0V




FOSC=500kHz, VOUT1=1.0V



FOSC=500kHz, VOUT1=3.3V









FOSC=500kHz, VOUT1=3.3V



\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)

## &lt; 1ch Step-Down DC/DC Controller &gt;







(3) Ripple Voltage vs. Output Current

**FOSC=180kHz, VOUT1=1.0V****FOSC=180kHz, VOUT1=1.0V****FOSC=180kHz, VOUT1=3.3V****FOSC=180kHz, VOUT1=3.3V****FOSC=180kHz, VOUT1=5.0V****FOSC=180kHz, VOUT1=5.0V**

\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)

## &lt; 1ch Step-Down DC/DC Controller &gt;







(3) Ripple Voltage vs. Output Current (Continued)

**FOSC=300kHz, VOUT1=1.0V****FOSC=300kHz, VOUT1=1.0V****FOSC=300kHz, VOUT1=1.8V****FOSC=300kHz, VOUT1=1.8V****FOSC=300kHz, VOUT1=2.5V****FOSC=300kHz, VOUT1=2.5V**

\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)

## &lt; 1ch Step-Down DC/DC Controller &gt;





(3) Ripple Voltage vs. Output Current (Continued)

**FOSC=300kHz, VOUT1=3.3V****FOSC=300kHz, VOUT1=3.3V****FOSC=300kHz, VOUT1=5.0V****FOSC=300kHz, VOUT1=5.0V****FOSC=500kHz, VOUT1=1.0V****FOSC=500kHz, VOUT1=1.0V**

\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)

## &lt; 1ch Step-Down DC/DC Controller &gt;

(3) Ripple Voltage vs. Output Current (Continued)

**FOSC=500kHz, VOUT1=3.3V****FOSC=500kHz, VOUT1=3.3V****FOSC=500kHz, VOUT1=5.0V****FOSC=500kHz, VOUT1=5.0V**

\* When setting VOUT1=1.0V, VIN=8.0V or 10.0V,  
CL=94 $\mu$ F (Tantalum) + 100 $\mu$ F (OS Capacitor)


### ■ Typical Performance Characteristics

#### <2ch. Inverting DC/DC Controller >


(4) Output Voltage vs. Output Current

<Ceramic Capacitor and Compact Inductor use>


**FOSC=180kHz, VOUT2= -7.5V**



**FOSC=180kHz, VOUT2= -10.0V**







**FOSC=300kHz, VOUT2= -7.5V**



## &lt;2ch. Inverting DC/DC Controller&gt;

(4) Output Voltage vs. Output Current


&lt;Ceramic Capacitor use&gt;

**FOSC=180kHz, VOUT2= -7.5V****FOSC=180kHz, VOUT2= -10.0V****FOSC=180kHz, VOUT2= -7.5V****FOSC=180kHz, VOUT2= -10.0V**


### <2ch. Inverting DC/DC Controller>

(4) Output Voltage vs. Output Current


**FOSC=180kHz, VOUT2= -7.5V**




**FOSC=180kHz, VOUT2= -10.0V**




**FOSC=300kHz, VOUT2= -5.0V**




**FOSC=300kHz, VOUT2= -7.5V**



**FOSC=300kHz, VOUT2= -10.0V**



**FOSC=300kHz, VOUT2= -15.0V**




## &lt;2ch. Inverting DC/DC Controller&gt;


(5) Efficiency vs. Output Current

&lt;Ceramic Capacitor and Compact Inductor use&gt;


FOSC=180kHz, VOUT2= -7.5V



FOSC=180kHz, VOUT2= -10.0V



FOSC=300kHz, VOUT2= -7.5V




## &lt;2ch. Inverting DC/DC Controller&gt;


(5) Efficiency vs. Output Current (Continued)

&lt;Ceramic Capacitor use&gt;


FOSC=180kHz, VOUT2= -7.5V




FOSC=180kHz, VOUT2= -10.0V



FOSC=180kHz, VOUT2= -7.5V









FOSC=180kHz, VOUT2= -10.0V



## &lt;2ch. Inverting DC/DC Controller&gt;

(5) Efficiency vs. Output Current (Continued)

&lt;Tantalum Capacitor use&gt;


**FOSC=180kHz, VOUT2= -7.5V****FOSC=180kHz, VOUT2= -10.0V****FOSC=300kHz, VOUT2= -5.0V****FOSC=300kHz, VOUT2= -7.5V****FOSC=300kHz, VOUT2= -10.0V****FOSC=300kHz, VOUT2= -15.0V**

## &lt;2ch. Inverting DC/DC Controller &gt;


(6) Ripple Voltage vs. Output Current

&lt;Ceramic Capacitor and Compact Inductor use&gt;


FOSC=180kHz, VOUT2= -7.5V



FOSC=180kHz, VOUT2= -10.0V



FOSC=300kHz, VOUT2= -7.5V




## &lt;2ch. Inverting DC/DC Controller&gt;


(6) Ripple Voltage vs. Output Current (Continued)

&lt;Ceramic Capacitor use&gt;


FOSC=180kHz, VOUT2= -7.5V




FOSC=180kHz, VOUT2= -10.0V



FOSC=180kHz, VOUT2= -7.5V









FOSC=180kHz, VOUT2= -10.0V



## &lt;2ch. Inverting DC/DC Controller&gt;


(6) Ripple Voltage vs. Output Current (Continued)

&lt;Tantalum Capacitor use&gt;


**FOSC=180kHz, VOUT2= -7.5V****FOSC=180kHz, VOUT2= -10.0V****FOSC=300kHz, VOUT2= -5.0V****FOSC=300kHz, VOUT2= -7.5V****FOSC=300kHz, VOUT2= -10.0V****FOSC=180kHz, VOUT2= -15.0V**

<2ch. Inverting DC/DC Controller>  
(7) Breakdown of Output Voltage


FOSC=300kHz, VIN= 3.3V




FOSC=300kHz, VIN= 3.3V




FOSC=300kHz, VIN= 3.3V




FOSC=300kHz, VIN= 3.3V



FOSC=500kHz, VIN= 3.3V




FOSC=500kHz, VIN= 3.3V




< 2ch. Inverting DC/DC Controller >  
 (8) Breakdown of Coil Inductance Value

FOSC=300kHz, VIN=3.3V, Output2= -7.5V




FOSC=300kHz, VIN=3.3V, Output2= -7.5V




## ■ Typical Performance Characteristics (Continued)


(9) Supply Current 1 vs. Supply Voltage




(10) Supply Current 1-1 vs. Supply Voltage




(11) Supply Current 1-2 vs. Supply Voltage




(12) Supply Current 1-3 vs. Supply Voltage




(13) Supply Current 1-4 vs. Supply Voltage




(14) Supply Current 2 vs. Supply Voltage




(15) Stand-by Current vs. Supply Voltage




(16) Oscillation Frequency vs. Supply Voltage




(17) PWM1, 2 'H'L' Voltage vs. Supply Voltage




(18) EN1, 2 'H'L' Voltage vs. Supply Voltage




(19) Maximum Duty Ratio 2 vs. Supply Voltage




(20) Soft-start Time vs. Supply Voltage




(21) EXT1, 2 High ON Resistance vs. Supply Voltage




(22) EXT1, 2 Low ON Resistance vs. Supply Voltage



(23) Output Voltage vs. Ambient Temperature



(24) PFM Duty Ratio1, 2 vs. Supply Voltage




■ Load Transient Response

< 1 ch. Step-Up DC/DC Controller >


< VOUT1 = 3.3V, VIN = 5.0V      IOUT1 = 100 $\mu$ A  $\leftrightarrow$  300mA >

○ PWM Control

FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=100 $\mu$ A  $\rightarrow$  300mA




FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=300mA  $\rightarrow$  100 $\mu$ A




○ PWM/PFM Switching Control

FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=100 $\mu$ A  $\rightarrow$  300mA





FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=300mA  $\rightarrow$  100 $\mu$ A





&lt; 1 ch. Step-Up DC/DC Controller &gt;

&lt; VOUT1 = 3.3V, VIN = 5.0V      IOUT1 = 10mA → 300mA &gt;

## ○ PWM Control

FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=10mA→ 300mAFOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=300mA→10mA



## ○ PWM/PFM Switching Control

FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=10mA→ 300mAFOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=300mA→10mA



&lt; 1 ch. Step-Up DC/DC Controller &gt;

&lt; VOUT1 = 0.9V, VIN = 3.3V      IOUT1 = 100µA ↔ 300mA &gt;

## ○ PWM Control

FOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=100µA→ 300mAFOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=300mA→100µA

## ○ PWM/PFM Switching Control


FOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=100µA→ 300mAFOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=300mA→100µA

< 1 ch. Step-Up DC/DC Controller >


< VOUT1 = 0.9V, VIN = 3.3V      IOUT1 = 10mA → 300mA >

○ PWM Control

FOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=10mA→ 300mA




FOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=300mA→ 10mA




○ PWM/PFM Switching Control

FOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=10mA→ 300mA




FOSC=300kHz, VOUT1=0.9V  
VIN=3.3V, IOUT1=300mA→ 10mA




&lt; 1 ch. Step-Up DC/DC Controller &gt;

&lt; PWM Control ⇔ PWM / PFM Switching Control &gt;

FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=5mA PWM1 'L'→'H'




FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=5A PWM1 'H'→'L'




&lt; Soft-Start Wave Form &gt;

FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=300mA  
EN1 'L'→'H', CIN=47μF



FOSC=300kHz, VOUT1=3.3V  
VIN=5.0V, IOUT1=100mA  
EN1 'L'→'H', CIN=47μF




&lt; 2 ch. Inverting DC/DC Controller &gt;


&lt; VOUT2 = -7.5V, VIN = 3.3V      IOUT2 = -100µA ↔ -50mA &gt;      (Tantalum Capacitor use)

## ○ PWM Control

FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-100µA → -50mA




FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-50mA → -100µA




## ○ PWM/PFM Switching Control

FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-100µA → -50mA



FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-50mA → -100µA




&lt; 2 ch. Inverting DC/DC Controller &gt;

&lt; VOUT2 = -7.5V, VIN = 3.3V IOUT2 = -100µA ↔ -20mA &gt;


(Ceramic Capacitor use when coil current is discontinued.)

## ○ PWM Control

FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-100µA → -20mA




FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-20mA → -100µA




## ○ PWM/PFM Switching Control

FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-100µA → -20mA



FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-20mA → -100µA




< 2 ch. Inverting DC/DC Controller >

< VOUT2 = -7.5V, VIN = 3.3V IOUT2 = -1mA → -20mA >


○ PWM Control

FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-1mA→ -20mA



CH1:VOUT2 , AC-COUPLED, 20mV/div  
CH2:IOUT2 , 10mA/div


FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-20mA→ -1mA



CH1:VOUT2 , AC-COUPLED, 20mV/div  
CH2:IOUT2 , 10mA/div


○ PWM / PFM Switching Control

FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-1mA→ -20mA



CH1:VOUT2 , AC-COUPLED, 20mV/div  
CH2:IOUT2 , 10mA/div

FOSC=180kHz, VOUT2=-7.5V  
VIN=3.3V, IOUT2=-20mA→ -1mA




CH1:VOUT2 , AC-COUPLED, 20mV/div  
CH2:IOUT2 , 10mA/div

&lt; 2 ch. Inverting DC/DC Controller &gt;

&lt; PWM Control ⇔ PWM / PFM Switching Control &gt;


FOSC=180kHz, VOUT2=-7.5V

VIN=3.3V, IOUT2= - 5mA PWM2 'L'→'H'

CH1:VOUT<sub>2</sub> , AC-COUPLED ,20mV/div  
CH2:PWM<sub>2</sub> , 0.5V/div

FOSC=180kHz, VOUT2=-7.5V

VIN=3.3V, IOUT2= - 5mA PWM2 'H'→'L'

CH1:VOUT<sub>2</sub> , AC-COUPLED ,20mV/div  
CH2:PWM<sub>2</sub> , 0.5V/div



## Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

### Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибутором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибутором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: ocean@oceanchips.ru

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А