

# HA1631S01/02/03/04 Series

Single CMOS Comparator  
(Push Pull/Open Drain Output)

R03DS0085EJ0500

Rev.5.00

Jul 01, 2015

## Description

The HA1631S01/02/03/04 are low power single CMOS Comparator featuring low voltage operation with typical current supply of 5  $\mu$ A/50  $\mu$ A. They are designed to operate from a single power supply. HA1631S01/02 have push-pull full swing outputs that allow direct connections to logic devices. The Open Drain version HA1631S03/04 enable Output Level shifting through external pull up resistors. Available in an ultra-small CMPAK-5 package, they occupy only 1/8 the area of the SOP-8 package.


## Features

- Low supply current  
 HA1631S01/03 :  $I_{DDtyp} = 5 \mu A$  ( $V_{DD} = 3.0 V$ )  
 HA1631S02/04 :  $I_{DDtyp} = 50 \mu A$  ( $V_{DD} = 3.0 V$ )
- Low voltage operation :  $V_{DD} = 1.8$  to  $5.5 V$
- Low input offset voltage :  $V_{IOmax} = 5 mV$
- Low input bias current :  $I_{IBtyp} = 1 pA$
- Maximum output voltage :  $V_{OHmin} = 2.9 V$  (at  $V_{DD} = 3.0 V$ )
- Input common voltage range includes ground
- On-chip ESD protection
- Available in CMPAK-5 and MPAK-5 package using Pb free lead frame


## Ordering Information

| Type No.    | Package Name | Package Code |
|-------------|--------------|--------------|
| HA1631S01CM | CMPAK-5      | PTSP0005ZC-A |
| HA1631S02CM |              |              |
| HA1631S03CM |              |              |
| HA1631S04CM |              |              |
| HA1631S01LP | MPAK-5       | PLSP0005ZB-A |
| HA1631S02LP |              |              |
| HA1631S03LP |              |              |
| HA1631S04LP |              |              |

## Pin Arrangement



## Equivalent Circuit



## Absolute Maximum Ratings

(Ta = 25°C)

| Item                       | Symbol                | Ratings                              | Unit | Remarks        |
|----------------------------|-----------------------|--------------------------------------|------|----------------|
| Supply voltage             | V <sub>DD</sub>       | 7.0                                  | V    |                |
| Differential input voltage | V <sub>IN(diff)</sub> | -V <sub>DD</sub> to +V <sub>DD</sub> | V    | Note 1         |
| Input voltage              | V <sub>IN</sub>       | -0.1 to +V <sub>DD</sub>             | V    |                |
| Output current             | I <sub>OUT</sub>      | 28                                   | mA   | Note 2         |
| Power dissipation          | P <sub>T</sub>        | 80/120                               | mW   | CMPAK-5/MPAK-5 |
| Operating temperature      | T <sub>opr</sub>      | -40 to +85                           | °C   |                |
| Storage temperature        | T <sub>stg</sub>      | -55 to +125                          | °C   |                |

- Notes: 1. Do not apply input voltage exceeding V<sub>DD</sub> or 7 V.  
 2. The maximum output current is the maximum allowable value for continuous operation.

## Electrical Characteristics

(Ta = 25°C, V<sub>DD</sub> = 3.0 V, V<sub>SS</sub> = 0 V)







| Item  | Symbol               | Min                  | Typ   | Max    | Unit | Test Conditions  |   |
|---|----------------------|----------------------|-------|--------|------|--|---|
| Input offset voltage                              | V <sub>IO</sub>      | —                    | —     | 5      | mV   | V <sub>IN</sub> = V <sub>DD</sub> /2, R <sub>L</sub> = 1MΩ           |   |
| Input bias current                                | I <sub>IB</sub>      | —                    | (1)   | 100    | pA   | V <sub>IN</sub> = V <sub>DD</sub> /2                                 |   |
| Input offset current                              | I <sub>IO</sub>      | —                    | (1)   | 100    | pA   | V <sub>IN</sub> = V <sub>DD</sub> /2                                 |   |
| Common mode input voltage range                   | V <sub>CM</sub>      | -0.1                 | —     | 2.1    | V    |  |   |
| Supply current                                    | HA1631S01/03         | I <sub>DD</sub>      | —     | 5      | 10   | μA   | V <sub>DD</sub> = 3V, V <sub>IN+</sub> = 1V,<br>V <sub>IN-</sub> = 0V |
|   | HA1631S02/04         |                      | —     | 50     | 100  | μA   |   |
| Response time                                     | HA1631S01            | TP <sub>LH</sub>     | —     | (1.20) | —    | μs   | 1V DC bias,<br>100mV overdrive,<br>C <sub>L</sub> = 15pF              |
|   | HA1631S01/03         | TP <sub>HL</sub>     | —     | (0.55) | —    | μs   |   |
|   | HA1631S01            | t <sub>r</sub>       | —     | (24)   | —    | ns   |   |
|   | HA1631S01/03         | t <sub>f</sub>       | —     | (7)    | —    | ns   |   |
|   | HA1631S02            | TP <sub>LH</sub>     | —     | (0.33) | —    | μs   |   |
|   | HA1631S02/04         | TP <sub>HL</sub>     | —     | (0.17) | —    | μs   |   |
|   | HA1631S02            | t <sub>r</sub>       | —     | (12)   | —    | ns   |   |
| Output source current<br>(HA1631S01/02)           | I <sub>OSOURCE</sub> | 6                    | 13    | —      | mA   | V <sub>out</sub> = 2.5V  |   |
|   |                      | 7                    | 14    | —      | mA   | V <sub>out</sub> = 0.5V  |   |
| Common mode<br>rejection ratio                    | HA1631S01/03         | CMRR                 | 60    | 80     | —    | dB   | V <sub>IN1</sub> = 0V, V <sub>IN2</sub> = 2V                          |
|   | HA1631S02/04         |                      | 50    | 70     | —    | dB   |   |
| Power supply rejection ratio                      | PSRR                 | 60                   | 80    | —      | dB   | V <sub>DD1</sub> = 1.8V, V <sub>DD2</sub> = 5.5V                     |   |
| Output voltage high                               | V <sub>OH</sub>      | V <sub>DD</sub> -0.1 | —     | —      | V    | R <sub>L</sub> = 10kΩ to V <sub>SS</sub>                             |   |
| Output voltage low                                | V <sub>OL</sub>      | —                    | —     | 0.1    | V    | R <sub>L</sub> = 10kΩ to V <sub>DD</sub>                             |   |
| Output leakage current<br>(Only for HA1631S03/04) | I <sub>LO</sub>      | —                    | (0.1) | —      | nA   | V <sub>IN+</sub> = 1V, V <sub>IN-</sub> = 0V,<br>V <sub>O</sub> = 3V |   |
| Operating voltage range                           | V <sub>opr</sub>     | 1.8                  | —     | 5.5    | V    |  |   |







Note: ( ): Design specification

## Table of Graphs

| Electrical Characteristics      |               |                           | HA1631S01<br>Figure | HA1631S02<br>Figure | HA1631S03<br>Figure | HA1631S04<br>Figure | Test<br>Circuit No. |
|---------------------------------|---------------|---------------------------|---------------------|---------------------|---------------------|---------------------|---------------------|
| Supply current                  | $I_{DD}$      | vs. Supply voltage(Out H) | 1-1                 | 2-1                 | 3-1                 | 4-1                 | 1                   |
|                                 |               | vs. Supply voltage(Out L) | 1-2                 | 2-2                 | 3-2                 | 4-2                 | 2                   |
|                                 |               | vs. Temperature(Out H)    | 1-3                 | 2-3                 | 3-3                 | 4-3                 | 1                   |
| Output high voltage             | $V_{OH}$      | vs. Rload                 | 1-18                | 2-18                | 3-4                 | 4-4                 | 4                   |
| Output source current           | $I_{OSOURCE}$ | vs. Output high voltage   | 1-4                 | 2-4                 | —                   | —                   | 5                   |
| Output low voltage              | $V_{OL}$      | vs. Rload                 | 1-17                | 2-17                | 3-14                | 4-14                | 6                   |
| Output sink current             | $I_{OSINK}$   | vs. Output low voltage    | 1-5                 | 2-5                 | 3-4                 | 4-4                 | 5                   |
| Input offset voltage            | $V_{IO}$      | vs. Supply voltage        | 1-6                 | 2-6                 | 3-5                 | 4-5                 | 8                   |
|                                 |               | vs. Temperature           | 1-7                 | 2-7                 | 3-6                 | 4-6                 | 7                   |
| Common mode input voltage range | $V_{CM}$      | vs. Temperature           | 1-8                 | 2-8                 | 3-7                 | 4-7                 | 9                   |
| Power supply rejection ratio    | PSRR          | vs. Supply voltage        | 1-9                 | 2-9                 | 3-8                 | 4-8                 | 11                  |
| Common mode rejection ratio     | CMRR          | vs. Input voltage         | 1-10                | 2-10                | 3-9                 | 4-9                 | 12                  |
| Input bias current              | $I_{IB}$      | vs. Temperature           | 1-11                | 2-11                | 3-10                | 4-10                | 10                  |
|                                 |               | vs. Input voltage         | 1-12                | 2-12                | 3-11                | 4-11                | 10                  |
| Falling time                    | $t_f$         | vs. Temperature           | 1-13                | 2-13                | 3-12                | 4-12                | 13                  |
|                                 |               | vs. Cload                 | 1-15                | 2-15                | 3-13                | 4-13                | 13                  |
|                                 |               | Time waveform             | 1-20                | 2-20                | 3-15                | 4-15                | 13                  |
| Rising time                     | $t_r$         | vs. Temperature           | 1-14                | 2-14                | —                   | —                   | 13                  |
|                                 |               | vs. Cload                 | 1-16                | 2-16                | —                   | —                   | 13                  |
|                                 |               | Time waveform             | 1-19                | 2-19                | —                   | —                   | 13                  |
| Propagation delay time          | $TP_{LH}$     | Time waveform             | 1-21                | 2-21                | —                   | —                   | 13                  |
|                                 | $TP_{HL}$     | Time waveform             | 1-22                | 2-22                | 3-16, 3-17          | 4-16, 4-17          | 13                  |

Main Characteristics













Figure 1-19 HA1631S01  
Rising Time,  $t_r$   
(Overdrive =  $\pm 0.1V_{p-p}$ )




Figure 1-20 HA1631S01  
Falling Time,  $t_f$   
(Overdrive =  $\pm 0.1V_{p-p}$ )




Figure 1-21 HA1631S01  
 $TP_{LH}$  Transient Response  
(Overdrive =  $\pm 0.1V_{p-p}$ )




Figure 1-22 HA1631S01  
 $TP_{HL}$  Transient Response  
(Overdrive =  $\pm 0.1V_{p-p}$ )






Figure 2-1 HA1631S02  
Supply Current vs. Supply Voltage  
(Output High)




Figure 2-2 HA1631S02  
Supply Current vs. Supply Voltage  
(Output Low)




Figure 2-3 HA1631S02  
Supply Current vs. Ambient Temperature




Figure 2-4 HA1631S02  
Output High Voltage vs. Output Source Current




Figure 2-5 HA1631S02  
Output Low Voltage vs. Output Sink Current











Figure 2-6 HA1631S02  
Input Offset Voltage vs. Supply Voltage













Figure 2-19 HA1631S02  
Rising Time,  $t_r$   
(Overdrive =  $\pm 0.1V_{p-p}$ )




Figure 2-20 HA1631S02  
Falling Time,  $t_f$   
(Overdrive =  $\pm 0.1V_{p-p}$ )




Figure 2-21 HA1631S02  
 $TP_{LH}$  Transient Response  
(Overdrive =  $\pm 0.1V_{p-p}$ )




Figure 2-22 HA1631S02  
 $TP_{HL}$  Transient Response  
(Overdrive =  $\pm 0.1V_{p-p}$ )




Figure 3-1 HA1631S03  
Supply Current vs. Supply Voltage  
(Output High)




Figure 3-2 HA1631S03  
Supply Current vs. Supply Voltage  
(Output Low)




Figure 3-3 HA1631S03  
Supply Current vs. Ambient Temperature




Figure 3-4 HA1631S03  
Output Low Voltage vs. Output Sink Current




Figure 3-5 HA1631S03  
Input Offset Voltage vs. Supply Voltage











Figure 3-6 HA1631S03  
Input Offset Voltage vs. Ambient Temperature












Figure 4-1 HA1631S04  
Supply Current vs. Supply Voltage  
(Output High)




Figure 4-2 HA1631S04  
Supply Current vs. Supply Voltage  
(Output Low)




Figure 4-3 HA1631S04  
Supply Current vs. Ambient Temperature




Figure 4-4 HA1631S04  
Output Low Voltage vs. Output Sink Current




Figure 4-5 HA1631S04  
Input Offset Voltage vs. Supply Voltage
















Figure 4-6 HA1631S04  
Input Offset Voltage vs. Ambient Temperature











**Test Circuits**


1. Supply Current,  $I_{DD}$  (Output High)




2. Supply Current,  $I_{DD}$  (Output Low)




3. Output Source Current,  $I_{OSOURCE}$




4. Output Voltage High,  $V_{OH}$




5. Output Sink Current,  $I_{OSINK}$



6. Output Voltage Low,  $V_{OL}$




7. Input Offset Voltage,  $V_{IO}$




Note:  $V_{IO} = V_{OUT} - 1.5V$

8. Input Offset Voltage vs.  $V_{DD}$




9. Common Mode Input Voltage Range,  $V_{CM}$




Note:  $V_{CML}$  and  $V_{CMH}$  are values of  $V_{IN}$  when  $V_{IO}$  changes more than 50dB taking  $V_{IN} = 0V$  as reference.

10. Input Bias Current,  $I_{IB}$




11. Power Supply Rejection Ratio, PSRR







| $V_{DD}$ | Measure Point | Calculate $V_{IO}$        | PSRR Calculation   |
|----------|---------------|---------------------------|--|
| -1.8V    | $V_{OUT1}$    | $V_{IO1} = V_{OUT1}/1000$ | $PSRR = \left  20 \log_{10} \frac{ (V_{IO2} - V_{IO1}) }{5.5V - 1.8V} \right $ |
| 5.5V     | $V_{OUT2}$    | $V_{IO2} = V_{OUT2}/1000$ |  |

12. Common Mode Rejection Ratio, CMRR





| $V_{IN}$ | Measure Point | Calculate $V_{IO}$        | CMRR Calculation  |
|----------|---------------|---------------------------|---|
| -1.5V    | $V_{OUT1}$    | $V_{IO1} = V_{OUT1}/1000$ | $CMRR = \left  20 \log_{10} \frac{ (V_{IO2} - V_{IO1}) }{0.5V - (-1.5V)} \right $ |
| 0.5V     | $V_{OUT2}$    | $V_{IO2} = V_{OUT2}/1000$ |   |

13. Falling Time, Rising Time, Propagation Delay Time  $TP_{LH}$ ,  $TP_{HL}$




Only for Push Pull HA1631S01/02



Only for Open Drain HA1631S03/04




**Mark Indication**



|             |             | (1) | (2) |
|-------------|-------------|-----|-----|
| HA1631S01CM | HA1631S01LP | 0   | A   |
| HA1631S02CM | HA1631S02LP | 0   | B   |
| HA1631S03CM | HA1631S03LP | 0   | C   |
| HA1631S04CM | HA1631S04LP | 0   | D   |

### Package Dimensions

| JEITA Package Code | RENESAS Code | Previous Code      | MASS (Typ) [g] |
|--------------------|--------------|--------------------|----------------|
| SC-88A             | PTSP0005ZC-A | CMPAK-5 / CMPAK-5V | 0.006          |






A-A Section

| Reference Symbol | Dimensions in millimeters |      |      |
|------------------|---------------------------|------|------|
|                  | Min                       | Nom  | Max  |
| A                | 0.8                       | —    | 1.1  |
| A <sub>1</sub>   | 0                         | —    | 0.1  |
| A <sub>2</sub>   | 0.8                       | 0.9  | 1.0  |
| A <sub>3</sub>   | —                         | 0.25 | —    |
| b                | 0.15                      | 0.22 | 0.3  |
| c                | 0.1                       | 0.13 | 0.15 |
| D                | 1.8                       | 2.0  | 2.2  |
| E                | 1.15                      | 1.25 | 1.35 |
| e                | —                         | 0.65 | —    |
| H <sub>E</sub>   | 1.8                       | 2.1  | 2.4  |
| L                | 0.3                       | —    | 0.7  |
| L <sub>1</sub>   | 0.1                       | —    | 0.5  |
| L <sub>P</sub>   | 0.2                       | —    | 0.6  |
| x                | —                         | —    | 0.05 |
| y                | —                         | —    | 0.05 |
| Q                | —                         | 0.25 | —    |

© 2013 Renesas Electronics Corporation. All rights reserved.

| JEITA Package Code | RENESAS Code | Previous Code    | MASS (Typ) [g] |
|--------------------|--------------|------------------|----------------|
| SC-74A             | PLSP0005ZB-A | MPAK-5 / MPAK-5V | 0.015          |



| Reference Symbol | Dimensions in millimeters |      |      |
|------------------|---------------------------|------|------|
|                  | Min                       | Nom  | Max  |
| A                | 1.0                       | —    | 1.4  |
| A <sub>1</sub>   | 0                         | —    | 0.1  |
| A <sub>2</sub>   | 1.0                       | 1.1  | 1.3  |
| A <sub>3</sub>   | —                         | 0.25 | —    |
| b                | 0.35                      | 0.4  | 0.5  |
| c                | 0.11                      | 0.16 | 0.26 |
| D                | 2.8                       | 2.95 | 3.1  |
| E                | 1.5                       | 1.6  | 1.8  |
| e                | —                         | 0.95 | —    |
| HE               | 2.5                       | 2.8  | 3.0  |
| L                | 0.3                       | —    | 0.7  |
| L <sub>1</sub>   | 0.1                       | —    | 0.5  |
| LP               | 0.2                       | —    | 0.6  |
| x                | —                         | —    | 0.05 |
| y                | —                         | —    | 0.05 |
| Q                | —                         | 0.3  | —    |

© 2013 Renesas Electronics Corporation. All rights reserved.

## Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
3. Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from such alteration, modification, copy or otherwise misappropriation of Renesas Electronics product.
5. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.  
"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots etc.  
"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; and safety equipment etc.  
Renesas Electronics products are neither intended nor authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems, surgical implantations etc.), or may cause serious property damages (nuclear reactor control systems, military equipment etc.). You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application for which it is not intended. Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for which the product is not intended by Renesas Electronics.
6. You should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
7. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or systems manufactured by you.
8. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
9. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You should not use Renesas Electronics products or technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. When exporting the Renesas Electronics products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations.
10. It is the responsibility of the buyer or distributor of Renesas Electronics products, who distributes, disposes of, or otherwise places the product with a third party, to notify such third party in advance of the contents and conditions set forth in this document, Renesas Electronics assumes no responsibility for any losses incurred by you or third parties as a result of unauthorized use of Renesas Electronics products.
11. This document may not be reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.

(Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.

(Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.



### SALES OFFICES

Renesas Electronics Corporation

<http://www.renesas.com>

Refer to "<http://www.renesas.com/>" for the latest and detailed information.

**Renesas Electronics America Inc.**  
2801 Scott Boulevard Santa Clara, CA 95050-2549, U.S.A.  
Tel: +1-408-588-6000, Fax: +1-408-588-6130

**Renesas Electronics Canada Limited**  
9251 Yonge Street, Suite 8309 Richmond Hill, Ontario Canada L4C 9T3  
Tel: +1-905-237-2004

**Renesas Electronics Europe Limited**  
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K  
Tel: +44-1628-585-100, Fax: +44-1628-585-900

**Renesas Electronics Europe GmbH**  
Arcadiastrasse 10, 40472 Düsseldorf, Germany  
Tel: +49-211-6503-0, Fax: +49-211-6503-1327

**Renesas Electronics (China) Co., Ltd.**  
Room 1709, Quantum Plaza, No.27 ZhichunLu Haidian District, Beijing 100191, P.R.China  
Tel: +86-10-8235-1155, Fax: +86-10-8235-7679

**Renesas Electronics (Shanghai) Co., Ltd.**  
Unit 301, Tower A, Central Towers, 555 Langao Road, Putuo District, Shanghai, P. R. China 200333  
Tel: +86-21-2226-0888, Fax: +86-21-2226-0899

**Renesas Electronics Hong Kong Limited**  
Unit 1601-1611, 16/F., Tower 2, Grand Century Place, 193 Prince Edward Road West, Mongkok, Kowloon, Hong Kong  
Tel: +852-2265-8688, Fax: +852-2886-9022

**Renesas Electronics Taiwan Co., Ltd.**  
13F, No. 363, Fu Shing North Road, Taipei 10543, Taiwan  
Tel: +886-2-8175-9600, Fax: +886-2-8175-9670

**Renesas Electronics Singapore Pte. Ltd.**  
80 Bendemeer Road, Unit #06-02 Hyflux Innovation Centre, Singapore 339949  
Tel: +65-6213-0200, Fax: +65-6213-0300

**Renesas Electronics Malaysia Sdn.Bhd.**  
Unit 1207, Block B, Menara Amcorp, Amcorp Trade Centre, No. 18, Jin Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia  
Tel: +60-3-7955-9390, Fax: +60-3-7955-9510

**Renesas Electronics India Pvt. Ltd.**  
No.777C, 100 Feet Road, HAL II Stage, Indiranagar, Bangalore, India  
Tel: +91-80-67208700, Fax: +91-80-67208777

**Renesas Electronics Korea Co., Ltd.**  
12F., 234 Teheran-ro, Gangnam-Gu, Seoul, 135-080, Korea  
Tel: +82-2-558-3737, Fax: +82-2-558-5141



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Renesas Electronics:](#)

[HA1631S03CMEL-E](#) [HA1631S04CMEL-E](#) [HA1631S02CMEL-E](#) [HA1631S01CMEL-E](#)

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



## JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: [ocean@oceanchips.ru](mailto:ocean@oceanchips.ru)

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А