

1SC0450V2A0-45 and 1SC0450V2A0-65

Preliminary Data Sheet

Single-Channel Cost-Effective SCALE™-2 IGBT Driver Core with Fiber-Optic Interface for 4500V and 6500V IGBTs

Abstract

The 1SC0450V2A0-xx features versatile fiber-optic links and drives all usual high-power IGBT modules up to 4500V or 6500V. Thanks to its high output power capability, a single 1SC0450V2A0-xx driver can drive up to four parallel-connected 4500V or 6500V IGBT modules and consequently provides easy inverter design covering higher power ratings. Multi-level topologies involving 3300V or 4500V IGBTs with higher isolation requirements can also be easily supported by 1SC0450V2A0-xx.

The 1SC0450V2A0-xx combines a complete single-channel driver core with all components required for driving, such as an isolated DC/DC converter, short-circuit protection, Advanced Active Clamping as well as supply voltage monitoring. Enhanced features such as gate boosting or power supply short-circuit protection are also implemented and provide further driving benefits.

The driver's secondary side is electrically isolated from its primary side. The 1SC0450V2A0-45 meets the requirements of 4500V IGBT applications while the 1SC0450V2A0-65 covers the requirements of 6500V IGBT applications.

An output current of 50A and 6W drive power is available, making the 1SC0450V2A0-xx an ideal driver platform for universal use in medium and high-power applications. The driver provides a gate voltage swing of 15V/-10V. The turn-on voltage is regulated to maintain a stable 15V regardless of the output power level.

Its outstanding EMC allows safe and reliable operation even in harsh industrial applications.

Product Highlights

- ✓ Ultra-compact single-channel driver
- ✓ Highly integrated SCALE™-2 chipset
- ✓ Gate current $\pm 50\text{A}$, 6W output power
- ✓ 15V/-10V gate driving
- ✓ Blocking voltages up to 4500V or 6500V
- ✓ Basic isolation to IEC 61800-5-1 and IEC 60664-1
- ✓ Short signal propagation delays
- ✓ UL-compliant
- ✓ Lead-free

Applications

- ✓ Traction
- ✓ Railroad power supplies
- ✓ Light rail vehicles
- ✓ HVDC
- ✓ Flexible AC transmission systems (FACTS)
- ✓ Medium-voltage converters
- ✓ Wind-power converters
- ✓ Industrial drives
- ✓ Medical applications

Preliminary Datasheet

Safety Notice!

The data contained in this data sheet is intended exclusively for technically trained staff. Handling all high-voltage equipment involves risk to life. Strict compliance with the respective safety regulations is mandatory!

Any handling of electronic devices is subject to the general specifications for protecting electrostatic-sensitive devices according to international standard IEC 60747-1, Chapter IX or European standard EN 100015 (i.e. the workplace, tools, etc. must comply with these standards). Otherwise, this product may be damaged.

Important Product Documentation

This data sheet contains only product-specific data. For a detailed description, must-read application notes and important information that apply to this product, please refer to “1SC0450V Description & Application Manual” on www.power.com/igbt-driver/go/1SC0450.

Mechanical Dimensions

Dimensions: Refer to the “1SC0450V Description & Application Manual”

Fiber-Optic Interfaces

Interface	Remarks	Part type #
Drive signal input IN	Fiber-optic receiver (Notes 1, 2)	HFBR-2522ETZ
Status output OUT	Fiber-optic transmitter (Notes 1, 3)	HFBR-1522ETZ

Preliminary Datasheet

Absolute Maximum Ratings

Parameter	Remarks	Min	Max	Unit
Supply voltage V_{DC}	VDC to GND	0	16	V
Supply voltage V_{CC}	VCC to GND	0	16	V
Logic output voltage V_{SO}	SO to GND	-0.5	$V_{CC}+0.5$	V
SO current	Failure condition, total current (Note 30)		20	mA
Gate peak current $\hat{I}_G$	Note 4	-50	+50	A
External gate resistance	Turn-on and turn-off (Notes 4, 5)	0.3		Ω
Average supply current I_{DC}	Notes 6, 7		860	mA
Output power	Ambient temperature $\leq 70^\circ\text{C}$ (Notes 8, 9)		8	W
	Ambient temperature $\leq 85^\circ\text{C}$ (Note 8)		6	W
Gate boosting output power	Notes 8, 10		4	W
Gate charge Q_{GBS}	GBS to GH		15	nC
Bias current I_{GBS}	On-state		20	μA
Switching frequency f			10	kHz
Power supply short-circuit time	Non-repetitive (Note 25)		1	s
Test voltage (50Hz/1min.)	Primary to secondary (Note 19)		10.2	kV_{eff}
$ dV/dt $	Rate of change of input to output voltage		35	$\text{kV}/\mu\text{s}$
Operating voltage	Primary/secondary, 1SC0450V2A0-45		4500	V_{peak}
	Primary/secondary, 1SC0450V2A0-65		6500	V_{peak}
Operating temperature	Notes 9	-40	+85	$^\circ\text{C}$
Storage temperature		-40	+85	$^\circ\text{C}$

Recommended Operating Conditions

Power Supply	Remarks	Min	Typ	Max	Unit
Supply voltage V_{DC}	VDC to GND	14.5	15	15.5	V
Supply voltage V_{CC}	VCC to GND	14.5	15	15.5	V

Preliminary Datasheet

Electrical Characteristics

All data refer to +25°C and $V_{CC} = V_{DC} = 15V$ unless otherwise specified.

Power Supply	Remarks	Min	Typ	Max	Unit
Supply current I_{DC}	Without load		110		mA
Supply current I_{CC}			20		mA
Coupling capacitance C_{io}	Primary to output, total		8		pF
Supply voltage V_{GB}	VGB to VISO (Note 26)		25		V
VGB charge	VGB to VISO (Note 27)		540		nC
Power Supply Monitoring	Remarks	Min	Typ	Max	Unit
Supply threshold V_{CC}	Primary side, clear fault	11.6	12.6	13.6	V
	Primary side, set fault (Note 16)	11.0	12.0	13.0	V
Monitoring hysteresis	Primary side, set/clear fault	0.35			V
Supply threshold $V_{ISO}-V_E$	Secondary side, clear fault	11.8	12.6	13.4	V
	Secondary side, set fault (Note 17)	11.2	12.0	12.8	V
Monitoring hysteresis	Secondary side, set/clear fault	0.35			V
Supply threshold V_E-V_{COM}	Secondary side, clear fault		5.2		V
	Secondary side, set fault (Note 17)		4.9		V
Monitoring hysteresis	Secondary side, set/clear fault		0.3		V
Power Supply Protection	Remarks	Min	Typ	Max	Unit
Overload power threshold	Output, set fault (Note 23)		17		W
Fault feedback pulse	Fiber-optic OUT (Note 24)	500			μs
Logic Outputs	Remarks	Min	Typ	Max	Unit
SO pull-up resistor to VCC	On board		10		kΩ
SO output voltage V_{SO}	Failure condition, $I(SO) < 6.5mA$			0.7	V
GBS voltage	GBS to GH, on-state (Note 26)		9		V
	GBS to GH, off-state (Note 26)		0		V
Short-Circuit Protection	Remarks	Min	Typ	Max	Unit
V_{CE} -monitoring threshold	Factory set value (Note 21)		10.2		V
Minimum response time	Note 14		5.1		μs
Delay to clear fault state $T_{d(cfs)}$	After IGBT short circuit (Note 15)		8		μs
Delay in IGBT turn-off T_{cshd}	Factory-set value (Note 22)		0.2		μs

Preliminary Datasheet

Timing Characteristics	Remarks	Min	Typ	Max	Unit
Turn-on delay $T_{d(on)}$	Note 11		135		ns
Turn-off delay $T_{d(off)}$	Note 11		105		ns
Output rise time $T_{r(GH)}$	Note 12		30		ns
Output fall time $T_{f(GL)}$	Note 12		25		ns
Transmission delay of fault state	Note 18		150		ns
Acknowledge delay time $T_{d(ack)}$	Note 28		220		ns
Acknowledge pulse width $T_{(ack)}$	On host side	400	700	1050	ns

Electrical Isolation	Remarks	Min	Typ	Max	Unit
Test voltage (50Hz/1s)	Primary to secondary side (Note 19)	10.2			kV _{eff}
Partial discharge extinction volt.	Primary to secondary side				
	1SC0450V2A0-45 (Note 20)	5400			V _{peak}
	1SC0450V2A0-65 (Note 20)	7800			V _{peak}
Creepage distance (Note 29)					
On the PCB	Primary to secondary side (Material group IIIa)	45			mm
On the transformer	Primary to secondary side (Material group I)	36			mm
Clearance distance	Primary to secondary side	25			mm

Output	Remarks	Min	Typ	Max	Unit
Blocking capacitance	VISO to VE (Note 13)		18.8		μF
	VE to COM (Note 13)		9.4		μF

Output Voltage Swing

The output voltage swing consists of two distinct segments. First, there is the turn-on voltage V_{GH} between pins GH and VE. V_{GH} is regulated and maintained at a constant level for all output power values and frequencies.

The second segment of the output voltage swing is the turn-off voltage V_{GL} . V_{GL} is measured between pins GL and VE. It is a negative voltage. It changes with the output power to accommodate the inevitable voltage drop across the internal DC/DC converter.

Output Voltage	Remarks	Min	Typ	Max	Unit
Turn-on voltage, V_{GH}	Any load condition		15.0		V
Turn-off voltage, V_{GL}	No load		-9.5		V
Turn-off voltage, V_{GL}	6W output power		-9.0		V
Turn-off voltage, V_{GL}	8W output power		-8.8		V

Preliminary Datasheet

Footnotes to the Key Data

- 1) The transceivers required on the host controller side are not supplied with the gate driver. It is recommended to use the same types as used in the gate driver. For product information, refer to www.power.com/igbt-driver/go/fiberoptics.
- 2) The recommended transmitter current at the host controller is 20mA. A higher current may increase jitter or delay at turn-off.
- 3) The typical transmitter current at the gate driver is 20.5mA. In case of supply undervoltage, the minimum transmitter current at the gate driver is 15mA: this is suitable for adequate plastic optical fibers with a length of up to 10 meters.
- 4) The maximum peak gate current refers to the highest current level occurring during the product lifetime. It is an absolute value and also applies to short pulses.
- 5) Twice the given minimum resistance value must be inserted between the interface connectors GH and GL. Moreover, the given minimal resistance value must be used in the full gate turn-on (interface connector GH to gate) and turn-off (interface connector GL to gate) path.
- 6) The average supply input current is limited for thermal reasons. Higher values than specified by the absolute maximum rating are permissible (e.g. during power supply start up) if the average remains below the given value, provided this average is taken over a time period which is shorter than the thermal time constants of the driver in the application.
- 7) There is no protection against light overload of the power supply. In the case of start-up with very high blocking capacitor values, or of short circuit/heavy overload at the output, the supply input current is limited internally. The time during which the driver output is shorted/overloaded must be limited externally and must be within the absolute maximum rating.
- 8) The maximum output power must not be exceeded at any time during operation. It must also be observed for time periods shorter than the thermal time constants of the driver in the application.
- 9) An extended output power range is specified in the output power section for ambient temperatures limited from -40°C to 70°C.
- 10) The gate-boosting output power can be calculated according to "1SC0450V Description & Application Manual" and is specified as a part of the gate driver's total output power, which is the sum of the turn-on power over the output GH plus the gate-boosting power over the output VGB. The turn-on power approximately equals the turn-off power of the output GL. The gate boosting is not active at turn-off.
- 11) Including the delay of the external fiber-optic links (cable length: 1m). Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the direct output of the gate drive unit (excluding the delay of the gate resistors). The delay time is measured between 50% of the input signal and the 10% voltage swing of the corresponding output. The delay time is independent of the output loading.
- 12) Output rise and fall times are measured between 10% and 90% of the nominal output swing with an output load of 4.7Ω and 270nF. These values are given for the driver side of the gate resistors. The time constant of the output load in conjunction with the present gate resistors leads to an additional delay at the load side of the gate resistors.
- 13) External blocking capacitors should be placed between the VISO and VE as well as the VE and COM terminals. Refer to "1SC0450V Description & Application Manual" (paragraph "DC/DC output (VISO), emitter (VE) and COM terminals") for recommendations. Ceramic capacitors are recommended.
- 14) The minimum response time is valid for the circuit given in the description and application manual with the values of the corresponding tables.
- 15) Measured on the host side. The fault status on the secondary side is extended by the "delay in IGBT turn-off" and automatically reset after the specified time. Refer to "1SC0450V Description & Application Manual" for more details.
- 16) Undervoltage monitoring of the primary-side supply voltage (VCC to GND). If the voltage drops below this limit, a fault is transmitted to the SO output.
- 17) Undervoltage monitoring of the secondary-side supply voltage (VISO to VE and VE to COM, which correspond to the approximate turn-on and turn-off gate-emitter voltages). If the corresponding voltage drops below this limit, a fault is transmitted to the fiber-optic output and the IGBT is switched off after the corresponding delay. Refer to "1SC0450V Description & Application Manual" for more

Preliminary Datasheet

details.

- 18) Delay of external fiber-optic links. Measured from the driver secondary side (ASIC output) to the optical receiver on the host controller with a 1m cable.
- 19) HiPot testing (= dielectric testing) must generally be restricted to suitable components. This gate driver is suited for HiPot testing. Nevertheless, it is strongly recommended to limit the testing time to 1s slots. Excessive HiPot testing at voltages much higher than 3182V_{AC,rms} with 1SC0450V2A0-45 and 4596V_{AC,rms} with 1SC0450V2A0-65 may lead to insulation degradation. No degradation has been observed over 1min. testing at 10.2kV_{AC,rms}. Every production sample (transformer only) shipped to customers has undergone 100% testing at the given value for 1s.
- 20) Partial discharge measurements are performed in accordance with IEC 60270 and IEC 60664-1 for basic insulation requirements.
- 21) The V_{CE}-monitoring threshold value can be reduced with an external resistor. Refer to "1SC0450V Description & Application Manual".
- 22) The turn-off event of the IGBT after a secondary-side fault (IGBT short circuit, undervoltage monitoring or power-supply short circuit/overload) can be additionally delayed with an external capacitor. Refer to "1SC0450V Description & Application Manual".
- 23) Gate turn-on and turn-off current pulses in normal operation do not affect the power supply protection. This protection is only triggered by a corresponding power-supply overload or short circuit (which would also occur in case of gate-emitter short circuit/overload).
- 24) The fault feedback pulse length/pattern depends on the power supply short-circuit/overload. The minimum value applies for any power-supply overload.
- 25) Maximum short-circuit duration of the driver output. The driver's power supply VDC must be switched off externally within the given time. The power supply protection prevents the driver's components from being damaged within the given time frame. For details refer to the driver's "1SC0450V Description & Application Manual".
- 26) The voltage values of the pins VGB resp. GBS are correspondingly about 50V and 34V respectively referred to COM. This must be considered for the design of the creepage and clearance distances.
- 27) The given value applies for a full discharge of VGB to VISO at turn-on, when no external capacitor is used. It can be increased by using additional external capacitors.
- 28) Including the delay of the external fiber-optic links (cable length: 1m). Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the transition of the acknowledge signal at the optical receiver on the host controller side.
- 29) Creepage distances over additional components (e. g. fiber-optic wires, fixation screws, ...) which are not part of the driver must be taken into account by the user.
- 30) Including current flowing into the on-board pull-up resistor of 10kΩ.

Legal Disclaimer

The statements, technical information and recommendations contained herein are believed to be accurate as of the date hereof. All parameters, numbers, values and other technical data included in the technical information were calculated and determined to our best knowledge in accordance with the relevant technical norms (if any). They may base on assumptions or operational conditions that do not necessarily apply in general. We exclude any representation or warranty, express or implied, in relation to the accuracy or completeness of the statements, technical information and recommendations contained herein. No responsibility is accepted for the accuracy or sufficiency of any of the statements, technical information, recommendations or opinions communicated and any liability for any direct, indirect or consequential loss or damage suffered by any person arising therefrom is expressly disclaimed.

Preliminary Datasheet

Ordering Information

The general terms and conditions of delivery of Power Integrations Switzerland GmbH apply.

Type Designation	Description
------------------	-------------

1SC0450V2A0-45	Single-channel SCALE-2 driver core for 4500V IGBTs
1SC0450V2A0-65	Single-channel SCALE-2 driver core for 6500V IGBTs

Product home page: www.power.com/igbt-driver/go/1SC0450

Refer to www.power.com/igbt-driver/go/nomenclature for information on driver nomenclature.

Information about Other Products

For other drivers, product documentation, and application support:

Please click: www.power.com

Manufacturer

Power Integrations Switzerland GmbH
Johann-Renfer-Strasse 15
2504 Biel-Bienne, Switzerland

Phone +41 32 344 47 47
Fax +41 32 344 47 40
Email igbt-driver.sales@power.com
Website www.power.com/igbt-driver

© 2014...2015 Power Integrations Switzerland GmbH.

All rights reserved.

We reserve the right to make any technical modifications without prior notice.

Version 1.0 from 2016-05-20

Preliminary Datasheet

Power Integrations Worldwide High Power Customer Support Locations**World Headquarters**

5245 Hellyer Avenue
San Jose, CA 95138 | USA
Main +1 408 414 9200
Customer Service:
Phone +1 408 414 9665
Fax +1 408 414 9765
Email usasales@power.com

Switzerland (Biel)

Johann-Renfer-Strasse 15
2504 Biel-Bienne | Switzerland
Phone +41 32 344 47 47
Fax +41 32 344 47 40
Email igbt-driver.sales@power.com

Germany (Ense)

HellwegForum 1
59469 Ense | Germany
Phone +49 2938 643 9990
Email igbt-driver.sales@power.com

Germany (Munich)

Lindwurmstrasse 114
80337 Munich | Germany
Phone +49 895 527 39110
Fax +49 895 527 39200
Email eurosales@power.com

China (Shanghai)

Rm 2410, Charity Plaza, No. 88
North Caoxi Road
Shanghai, PRC 200030
Phone +86 21 6354 6323
Fax +86 21 6354 6325
Email chinasales@power.com

China (Shenzhen)

17/F, Hivac Building, No 2,
Keji South 8th Road,
Nanshan District
Shenzhen | China, 518057
Phone +86 755 8672 8725
Fax +86 755 8672 8690
Hotline +86 400 0755 669
Email chinasales@power.com

Italy (Milano)

Via Milanese 20, 3rd. Fl.
20099 Sesto San Giovanni | Italy
Phone +39 024 550 8701
Fax +39 028 928 6009
Email eurosales@power.com

UK (Herts)

First Floor, Unit 15, Meadway Court,
Rutherford Close, Stevenage,
Herts SG1 2EF | United Kingdom
Phone +44 1252 730 141
Fax +44 1252 727 689
Email eurosales@power.com

India (Bangalore)

#1, 14th Main Road
Vasanthanagar
Bangalore 560052 | India
Phone +91 80 4113 8020
Fax +91 80 4113 8023
Email indiasales@power.com

Japan (Kanagawa)

Kosei Dai-3 Bldg., 2-12-11, Shin-
Yokohama, Kohoku-ku, Yokohama-shi,
Kanagawa 222-0033 | Japan
Phone +81 45 471 1021
Fax +81 45 471 3717
Email japansales@power.com

Korea (Seoul)

RM 602, 6FL
Korea City Air Terminal B/D, 159-6
Samsung-Dong, Kangnam-Gu
Seoul 135-728 | Korea
Phone +82 2 2016 6610
Fax +82 2 2016 6630
Email koreasales@power.com

Taiwan (Taipei)

5F, No. 318, Nei Hu Rd., Sec. 1
Nei Hu Dist.
Taipei 11493 | Taiwan R.O.C.
Phone +886 2 2659 4570
Fax +886 2 2659 4550
Email taiwansales@power.com

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели,
кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: ocean@oceanchips.ru

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А