

Vacuum Fluorescent Display Module Specification

Model: GU128X32-800B

Specification No: DS-1329-0000-01

Date of Issue: April 6, 2006

Revision: May 1, 2006

:
:
:
:

PUBLISHED BY
NORITAKE ITRON CORP. / JAPAN

This specification is subject to change without prior notice.

This product complies with RoHS Directive 2002/95/EC

Table of Contents

| | |
|---|-----------|
| 1. General Description | 2 |
| 2. Absolute Maximum Ratings | 2 |
| 3. Electrical Characteristics | 2 |
| 4. Optical Specifications | 2 |
| 5. Environmental Specifications | 2 |
| 6. Description of Bus and Signals | 3 |
| 6.1 Parallel Interface | 3 |
| 6.2 Serial Interface | 3 |
| 7. Block Diagram | 3 |
| 8. Display Screen and Initialize Set | 4 |
| 8.1 Graphic Display (GRAM) | 5 |
| 9. Function | 7 |
| 9.1 Commands | 7 |
| 9.2 Display On/Off (C/D= "1") | 8 |
| 9.3 Brightness Set (C/D= "1") | 8 |
| 9.4 Display Clear (C/D= "1") This command clears the GRAM. | 9 |
| 9.5 Display Area Set (C/D="1", only used for Initialize Set)..... | 10 |
| 9.6 GRAM Data Write position Address Set (Graphic Display) (C/D="1")..... | 11 |
| 9.6.1 GRAM Data Write Position X Address Set | 11 |
| 9.6.2 GRAM Data Write Position Y Address Set | 11 |
| 9.7 GRAM Display Start Position Address Set (C/D="1")..... | 11 |
| 9.7.1 Horizontal Shift | 11 |
| 9.7.2 Vertical Shift | 11 |
| 9.8 Address Mode Set (C/D="1") | 12 |
| 9.9 Address Read (C/D ="1") | 12 |
| 9.10 Data Write to Graphic Display(GRAM) (C/D="0") | 13 |
| 9.11 Default Status at Reset | 14 |
| 9.12 FRP (Frame Pulse)..... | 14 |
| 10. Interface | 15 |
| 10.1 Parallel Interface (Parallel #1) | 15 |
| 10.1.1 Command Write operation | 15 |
| 10.1.2 Command Read operation | 15 |
| 10.1.3 Data Write operation | 15 |
| 10.2 Parallel Interface(Parallel #2) | 16 |
| 10.2.1 Command Write operation | 16 |
| 10.2.2 Command Read operation | 16 |
| 10.2.3 Data Write operation | 16 |
| 10.3.1 Timing | 17 |
| 11. Jumper | 18 |
| 11.1 Jumper Position | 18 |
| 11.2 Jumper Setting (Must be done when power is OFF)..... | 18 |
| 12. Pin Assignment (See connector diagrams below) | 19 |
| 12.1 Signal Connection | 19 |
| 12.2 Connectors | 19 |
| 13. Outline Dimension | 20 |
| Notice for the Cautious Handling VFD Modules | 21 |

1. General Description

- 1.1 Construction: A 128X32 dot BD-VFD single board display module consisting of an 8 bit micro-computer, and a DC/DC converter.
- 1.2 Features: Simultaneous display of graphic.
Flexible Display and Editing Functions.
Compact design due to the application of a BD-VFD tube.
- 1.3 Dimensions: See attached drawings.

2. Absolute Maximum Ratings

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Condition |
|----------------------|-----------------|------|------|----------------------|------|-----------|
| Logic Input Voltage | VI | -0.5 | — | V _{cc} +0.3 | V | — |
| Power Supply Voltage | V _{cc} | 0 | — | 6.5 | VDC | — |

3. Electrical Characteristics

Measurement Conditions: 25°C / V_{cc}=5.0V

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Condition |
|----------------------|-----------------|------|------|------|------|------------------------------------|
| Logic Input Voltage | "H" | VIH | 4.0 | — | — | VDC IIH= 2 μA |
| | "L" | VIL | — | — | 1.0 | |
| Logic Output Voltage | "H" | VOH | 4.7 | — | — | VDC IOH= - 300 μA |
| | "L" | VOL | — | — | 0.3 | |
| Reset Input Voltage | "H" | VRH | 4.0 | — | — | VDC IRH= 5 μA |
| | "L" | VRL | — | — | 0.6 | |
| Power Supply Voltage | V _{cc} | 4.75 | 5.00 | 5.25 | VDC | — |
| Power Supply Current | I _{cc} | — | 450 | 600 | mA | V _{CC} =+5V, All dots ON |
| | | — | 350 | 450 | | V _{CC} =+5V, All dots OFF |

Notes:

The rise time of **V_{cc}** should not exceed **100 ms**.

I_{cc} may peak at power up may be more than twice the normal operating current

4. Optical Specifications

- Number of dots: 4096 (128X32)
 Display area: 83.05 mm x 20.65 mm (X x Y)
 Dot size: 0.5 mm x 0.5 mm (X x Y)
 Dot pitch: 0.65 mm x 0.65 mm (X x Y)
 Luminance: 350cd/m² (Min.)
 Color of illumination: Green (Blue Green)

5. Environmental Specifications

- Operating temperature: -40 to +85°C
 Storage temperature: -40 to +85°C
 Storage humidity: 20 to 80 % R.H(Non Condensation)
 Vibration: 10-55-10Hz, all amplitude 1mm, 30Min., X-Y-Z (Non operating)
 Shock: 539m/s² 10mS (Non operating)

6. Description of Bus and Signals

This module has serial and 2 types of parallel interface.

Type of interface can be selected by jumper settings. Refer to 11 on page # 18 for details.


6.1 Parallel Interface

| Data Line | Function |
|------------------------|---|
| D0 ~ D7 | Data Bus (Input / Output) |
| \overline{WR} (R/W) | Parallel #1: \overline{Write} Signal, Parallel #2: $\overline{R/W}$ (Input) |
| \overline{RD} (ENCK) | Parallel #1: \overline{Read} Signal, Parallel #2: ENCK (Input) |
| \overline{CSS} | Chip Select (Input) |
| $\overline{C/D}$ | $\overline{Command / Data Select}$ Signal (Input) C/D = "1" ... Command C/D = "0" ... Data |
| \overline{FRP} | Frame Pulse Signal (Output) |
| \overline{RESET} | $\overline{RESET}="0"$... Reset (Input) |
| Vcc | Power Supply |
| GND | Ground |

6.2 Serial Interface

| Data Line | Function |
|--------------------|---|
| RXD | Serial Input |
| TXD | Serial Output |
| SCK | Clock (Input) |
| \overline{CSS} | Chip Select (Input) |
| $\overline{C/D}$ | $\overline{Command / Data Select}$ Signal (Input) C/D = "1" ... Command C/D = "0" ... Data |
| \overline{FRP} | Frame Pulse Signal (Output) |
| \overline{RESET} | $\overline{RESET}="0"$... Reset (Input) Active Low |
| Vcc | Power Supply |
| GND | Ground |


7. Block Diagram



8. Display Screen and Initialize Set

The Display screen consists of 4,096 dots arranged as 128 by 32 dots. It is divided into 32 display area blocks of 16 by 8 dots each. Each display area block can be assigned to GRAM (Graphic mode) or DDRAM (Character mode) by the Display Area Set command. (9.5 Page #10)


But, this is the version which has no Font ROM. Therefore, DDRAM is not available, all of display area block must be assigned to GRAM as the initialize setting, and this must be done when the module is powered up and also every time the reset is applied, because all display area blocks are set to DDRAM area as default setting. Initialize sequence is as follows;



8.1 Graphic Display (GRAM)


GRAM consists of 16,384 bits arranged in 128 by 128 bit blocks with access is structured as 8 bits of vertical data. The detail of GRAM is as follows:

GRAM Data Write Position Address



8.1 Cont'd

GRAM Display Start Position Address



This module has 2 layers - Layer 0 and Layer 1. Each layer in this display consists of 128 by 64 dots. Display merging using these 2 layers can be done with the Display ON/OFF command. Refer to 9.2 on page # 8 for details.

Layer 0 has an area of 128x64 dots that starts from top left point defined by the GRAM Start Position Address. The area of Layer 1 is the next 128x64 dots.

When the value of the GRAM Start Position Address X overflow = 7FH, the next position goes to 00H. When the value of the GRAM Start Position Address Y overflow = 7FH, the next position goes to 00H.

For example:
 If the GRAM Start Position Address is set as X=02H, Y=08H, the area of Layer 0 is as follows;
 X=02H,03H,04H.....7FH,00H,01H
 Y=08H,09H.....46H, 47H

In this case, the area of Layer1 is as follows;
 X=02H,03H,04H.....7FH,00H,01H
 Y=48H,49H.....06H,07H

9. Function

9.1 Commands


| Command | C/D | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | Comments | |
|------------------------------------|-----|----------------------------|-----|------|------|------|-----------|----------|-----|----------|--|
| Display ON/OFF | 1 | 0 | 0 | 1 | 0 | L1 | L0 | * | * | 1st Byte | Display ON/OFF Control, 2 Byte Command |
| | | 0 | GS | 0 | GRV | AND | EXOR | * | * | 2nd Byte | |
| Brightness Set | 1 | 0 | 1 | 0 | 0 | BW3 | BW2 | BW1 | BW0 | 1 Byte | 1 Byte Command |
| Display Clear | 1 | 0 | 1 | 0 | 1 | G1C | G0C | 1 | HM | 1 Byte | 1 Byte Command |
| Display Area SET (Initialize) | 1 | 0 | 1 | 1 | 0 | 0 | 0 | 1 | 0 | 1st Byte | Display Area is assigned 3 Byte Command |
| | | 0 | 0 | 0 | 0 | 0 | (A2 – A0) | | | 2nd Byte | |
| | 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 3rd Byte | |
| Data Write Position Address Set | 1 | 0 | 1 | 1 | 0 | 0 | 1 | 0 | * | 1st Byte | Graphic Display X-Address Set, 2 Byte Command |
| | | GRAM X-Address (GXA6~GXA0) | | | | | | | | 2nd Byte | |
| | 1 | 0 | 1 | 1 | 0 | 0 | 0 | 0 | * | 1st Byte | Graphic Address Y-Address Set, 2-Byte Command |
| * | * | * | * | GYA3 | GYA2 | GYA1 | GYA0 | 2nd Byte | | | |
| Display Start Position Address Set | 1 | 0 | 1 | 1 | 1 | * | * | * | * | 1st Byte | Graphic Display Horizontal Shift, 2-Byte Command |
| | | XA7 | XA6 | XA5 | XA4 | XA3 | XA2 | XA1 | XA0 | 2nd Byte | |
| Address Mode Set | 1 | 1 | 0 | 0 | 0 | * | IGX | IGY | * | 1 Byte | Address Increment, 1 Byte Command |
| Address Read | 1 | 1 | 1 | 0 | 1 | 0 | 1 | * | * | 1st Byte | Graphic Display (GRAM) Horizontal And Vertical Display Start Address, 3 Byte Command |
| | | * | VG6 | VG5 | VG4 | VG3 | VG2 | VG1 | VG0 | 2nd Byte | |
| | | HG7 | HG6 | HG5 | HG4 | HG3 | HG2 | HG1 | HG0 | 3rd Byte | |
| Data Write | 0 | WRITE DATA | | | | | | | | | Writes Data Graphic Data is 1 Byte |

* Either a "0" or a "1" is acceptable


9.2 Display On/Off (C/D= "1")

The GRAM Layer is selected with the 1st Byte of data. DDRAM (**On/Off**), GRAM (**On/Off**), DDRAM (**reverse** or **normal** modes), GRAM (**reverse** or **normal** modes) and display merge are selected by the 2nd Byte. Reverse mode toggles the representation of green in the foreground and black in the background to the exact opposite - green to back and black to the foreground. This is similar to the concept of reverse video.

1st Byte:



2nd Byte:




DS="0", GS= "0": Stand-by mode

| 1st Byte | | 2nd Byte | | Action |
|----------|----|----------|------|----------------------------------|
| L1 | L0 | AND | EXOR | |
| * | * | 1 | * | AND Display of Layer 1& 0 |
| * | * | 0 | 1 | EXOR Display of Layer 1& 0 |
| 1 | 1 | 0 | 0 | OR Display of Layer 1& 0 |
| 1 | 0 | 0 | 0 | Only Layer1 selected for display |
| 0 | 1 | 0 | 0 | Only Layer0 selected for display |
| 0 | 0 | 0 | 0 | Graphic Display Off |

* Either a "0" or a "1" is acceptable

9.3 Brightness Set (C/D= "1")

The Brightness level of the display screen can be scaled by the following four bit control. Please note that the brightness is consistent across the illuminated pixels. There is no scaling of individual pixels. The display self-initializes to 100% brightness.




9.3 Cont'd

Brightness levels are set by the following:

| BW3 | BW2 | BW1 | BW0 | Brightness Level |
|-----|-----|-----|-----|------------------|
| 0 | 0 | 0 | 0 | 100%(Light) |
| 0 | 0 | 0 | 1 | 94% |
| 0 | 0 | 1 | 0 | 87% |
| 0 | 0 | 1 | 1 | 81% |
| 0 | 1 | 0 | 0 | 75% |
| 0 | 1 | 0 | 1 | 69% |
| 0 | 1 | 1 | 0 | 62% |
| 0 | 1 | 1 | 1 | 56% |
| 1 | 0 | 0 | 0 | 50% |
| 1 | 0 | 0 | 1 | 44% |
| 1 | 0 | 1 | 0 | 37% |
| 1 | 0 | 1 | 1 | 31% |
| 1 | 1 | 0 | 0 | 25% |
| 1 | 1 | 0 | 1 | 19% |
| 1 | 1 | 1 | 0 | 12% |
| 1 | 1 | 1 | 1 | 6%(Dark) |

9.4 Display Clear ($\overline{C/D}$ = "1") This command clears the GRAM.

This command should always be applied at power on or reset. In the period of 1mS following the issue of this command, the module requires internal processing and does not accept any commands.



To clear the GRAM area, G1C or G0C bit must be asserted. By asserting HM bit, both data write position address and display start position address which selected by G1C, G0C, DC also be reset.

HM = (1 or 0) equals (Initialize data write position address and display start position address or Not initialize).

G1C= (1 or 0) equals (GRAM area 1 is cleared or GRAM area 1 not cleared)

G0C= (1 or 0) equals (GRAM area 0 cleared or GRAM area 0 not cleared)


GRAM area 1: X= 00H-7FH, Y=0H – 7H (Display data write position address)

GRAM area 2: X= 00H-7FH, Y=8H – FH (Display data write position address)


9.5 Display Area Set ($\overline{C/D}="1"$, only used for Initialize Set)

This command sets the display area block as Graphic Display (GRAM) or Character display (DDRAM). But, this is version which has no Font ROM. Therefore, DDRAM is not available, all of display area block must be assigned to GRAM as the initialize setting, and this must be done when the module is powered up and also every time the reset is applied. Setup is performed by 3-byte command.


1st Byte: ($\overline{C/D}="1"$) Command Select



2nd Byte: ($\overline{C/D}="1"$) Display Area Data Address Select




3rd Byte: ($\overline{C/D}="0"$) Display Area Block Select



- D0 to D7 = "1": Graphic Display (GRAM)
- D0 to D7 = "0": Character Display (DDRAM, **Not available**)

Display area block is assigned as follows on a screen.



Display Area Data Address(0 ~ 7H)


9.6 GRAM Data Write position Address Set (Graphic Display) ($\overline{C/D}="1"$)

This command specifies both X & Y data write position address.


9.6.1 GRAM Data Write Position X Address Set

Data write position X address of GRAM expressed with 8 bits (00Hex-7FHex) is specified.
Refer to 8.1 Graphic Display (GRAM) on Page #5.

1st Byte: Command Select




2nd Byte: GRAM Data Write Position X Address




9.6.2 GRAM Data Write Position Y Address Set

Data write position Y address of GRAM expressed with 4 bits (0Hex-FHex) is specified.

1st Byte:



2nd Byte:




9.7 GRAM Display Start Position Address Set ($\overline{C/D}="1"$)


9.7.1 Horizontal Shift

This command specifies the address that a display pattern can be positioned to by **8 bits (00Hex to 7FHex)**. This is equivalent to an offset in the X-axis.

1st Byte:




2nd Byte:



9.7.2 Vertical Shift


This is equivalent to an offset Y-axis.



UD= "1": Display scrolled up.
 UD= "0": Display scrolled down.
 S1= "0", S0= "1": Display shift by 8 dots.
 S1= "1", S0= "0": Display shift by 1 dot.
 S1= "1", S0= "1": Display shift by 2 dots.

9.8 Address Mode Set (C/D="1")

This command specifies the GRAM data write position address auto increment mode.





IGX = "1" : X-Address +1(increment) when writing to GRAM.(It not affect to Y-Address.)
 IGX = "0" : GRAM X address fixed mode
 IGY = "1" : Y-Address +1(increment) when writing to GRAM.(It not affect to X-Address)
 IGY = "0" : GRAM Y address fixed mode.

9.9 Address Read (C/D="1")

This command reads both vertical and horizontal display start position addresses of GRAM (Refer to sect. 8 - Display Screen and Initialize set on Page # 4). On the parallel interface, the data bus outputs the address until CSS goes high after the READY signal goes active (Parallel#1:RD=LOW, Parallel#2:R/W=HIGH). The Data bus becomes an input when other. On the serial interface, TXD outputs the data from SCK rising after command is issued until the CSS goes high. Refer to 10.Interface on Page #15.

1st Byte:




VG0 to VG6: Vertical display start position address
 HG0 to HG7: Horizontal display start position address

9.10 Data Write to Graphic Display (GRAM) (C/D="0")

Can be written into GRAM by setting GRAM X or Y data write position address.

Example:

Writing "EA Hex" sets "D1, 3, 5, 6, 7 =1" and "D0, 2, 4 =0".



■ : Display ON

9.11 Default Status at Reset

When the reset is applied, the display self-initializes into the following status:

| | |
|-----------------|------------------------------------|
| GRAM Layer: | Layer (0) |
| Display ON/OFF: | Display (Off) |
| Display Area: | All DDRAM (Character display area) |


All of display area block must be assigned to GRAM again as the initialize setting after reset is applied because DDRAM is not available.

| | |
|-------------------|-----------------|
| GRAM X-address: | Fixed mode |
| GRAM Y-address: | Fixed mode |
| Brightness Level: | 100% Brightness |


The following precautions should be observed at power on, and after a reset:

External Reset: After Vcc reaches 2.5V, the Reset level is "Low" for more than 1.5mS.

Power-Up: The following sequence occurs:



9.12 FRP (Frame Pulse)




An FRP signal is triggered each time the display is refreshed by the module from its own memory. Smooth scrolling can be achieved by synchronizing the change of display start address with of the FRP signal from module. The area marked as "A" is optimal for writing commands.


10. Interface

10.1 Parallel Interface (Parallel #1)


10.1.1 Command Write operation



10.1.2 Command Read operation




10.1.3 Data Write operation




10.2 Parallel Interface(Parallel #2)


10.2.1 Command Write operation



10.2.2 Command Read operation




10.2.3 Data Write operation




10.3 Serial Interface

To use the serial interface of this module, (RXD, TXD and SCK) will be activated by CSS= "L". The internal shift registers and counters will be reset by CSS= "H". Serial data is transferred from MSB to LSB (D7->D0) on the rising edge of SCK. After the 8th clock edge, the data stream is converted to 8 bit parallel data. Recognition of the RXD input as either data or command is determined by C/D on the 8th pulse SCK.




10.3.1 Timing



11. Jumper

11.1 Jumper Position

Component side of board



11.2 Jumper Setting (Must be done when power is OFF)

| | J1 | J2 | Function |
|-----------|----|----|---------------------------------|
| Interface | 0 | X | Serial Interface |
| | 1 | 1 | Parallel #1 Interface (Default) |
| | 1 | 0 | Parallel #2 Interface |

1:Open

0:Short

X: Open or Short


12. Pin Assignment (See connector diagrams below)

12.1 Signal Connection

| Pin No. | Description | | |
|---------|------------------|------------------|------------------|
| | Parallel #1 | Parallel #2 | Serial |
| 1 | D7 | D7 | × |
| 3 | D6 | D6 | × |
| 5 | D5 | D5 | × |
| 7 | D4 | D4 | × |
| 9 | D3 | D3 | × |
| 11 | D2 | D2 | × |
| 13 | D1 | D1 | TXD |
| 15 | D0 | D0 | RXD |
| 17 | \overline{WR} | $\overline{R/W}$ | × |
| 19 | $\overline{C/D}$ | $\overline{C/D}$ | $\overline{C/D}$ |
| 21 | \overline{RD} | ENCK | SCK |
| 23 | \overline{CSS} | \overline{CSS} | \overline{CSS} |
| 25 | FRP | FRP | FRP |


| Pin No. | Description | | |
|---------|--------------------|--------------------|--------------------|
| | Parallel #1 | Parallel #2 | Serial |
| 2 | GND | GND | GND |
| 4 | GND | GND | GND |
| 6 | GND | GND | GND |
| 8 | GND | GND | GND |
| 10 | GND | GND | GND |
| 12 | GND | GND | GND |
| 14 | GND | GND | GND |
| 16 | GND | GND | GND |
| 18 | GND | GND | GND |
| 20 | GND | GND | GND |
| 22 | GND | GND | GND |
| 24 | GND | GND | GND |
| 26 | \overline{RESET} | \overline{RESET} | \overline{RESET} |

12.2 Connectors




Power Connector:
JST: B3B-XH-A or equivalent

| Pin No. | Description |
|---------|---------------------|
| 1 | Vcc |
| 2 | Test (Factory Only) |
| 3 | GND |



Data Connector
IMSA: 9032B-26P or Equivalent

13. Outline Dimension



Notice for the Cautious Handling VFD Modules

Handling and Usage Precautions:

Please carefully follow the appropriate product application notes for proper usage, safety handling, and operation standards for maximum performance.

[VFD tubes are made of glass]

- Because the edges of the VFD glass-envelop are not smooth, it is necessary to handle carefully to avoid injuries to your hands
- Please avoid breaking the VFD glass-envelop to prevent injury from sharp glass particles.
- The tip of the exhaust pipe is fragile so avoid shock from impact.
- It is recommended to allow sufficient open space surrounding the exhaust pipe to avoid possible damage.
- Please design the PCB for the VFD-module within 0.3 mm warping tolerance to avoid any forces that may damage the display due to PCB distortion causing a breakdown of the electrical circuit leading to VFD failure.

[High voltage]

- Avoid touching conductive electrical parts, because the VFD-module uses high voltage exceeding 30~100 volts.
- Even when electric power is turned off, it may take more than one minute for the electrical current to discharge.

[Cable connection]

- Do not unplug the power and/or data cables of VFD-modules during operating condition because unrecoverable damage may result.
- Sending input signals to the VFD-module during a power off condition sometimes causes I/O port damage.
- It is recommended to use a 30 cm or shorter signal cable to prevent functional failures.

[Electrostatic charge]

- VFD-modules needs electrostatic free packaging and protection from electrostatic charges during handling and usage.

[Structure]

- During operation, VFD and VFD-modules generate heat. Please consider sufficient heat radiation dissipation using heat sink solutions.
- We prefer to use UL grade materials or components in conjunction with VFD-modules.
- Wrap and twist motion causes stress and may break VFDs & VFD modules. Please adhere to allowances within 0.3mm at the point of attachment.

[Power]

- Apply regulated power to the VFD-module within specified voltages to protect from failures.
- Because some VFD-modules may consume in rush current equal to twice the typical current at power-on timing, we recommend using a sufficient power capability and quick starting of the power regulator.
- VFD-module needs a specified voltage at the point of connection. Please use an adequate power cable to avoid a decrease in voltage. We also recommend inserting a power fuse for extra protection.

[Operating consideration]

- Illuminating phosphor will decrease in brightness during extended operation. If a fixed pattern illuminates for an extended period,(several hours), the phosphor efficiency will decrease compared to the non operating phosphor causing a non uniform brightness among pixels. Please consider programming the display patterns to use all phosphor segments evenly. Scrolling may be a consideration for a period of time to refresh the phosphor condition and improve even illumination to the pixels.
- We recommend using a signal cable 30cm or less to avoid some possible disturbances to the signal.

[Storage and operating environment]

- Please use VFD-modules under the recommended specified environmental conditions. Salty, sulfur and dusty environments may damage the VFD-module even during storage.

[Discard]

- Some VFDs contain a small amount of cadmium in the phosphor and lead in the solder. When discarding VFDs or VFD-modules, please adhere to governmental related laws or regulations.

[Others]

- Although the VFD-module is designed to be protected from electrical noise, please plan your circuitry to exclude as much noise as possible.
- Do not reconstruct or repair the VFD-module without our authorization. We cannot assure the quality or reliability of unauthorized reconstructed VFD-modules.

Notice:

·We do not authorize the use of any patents that may be inherent in these specifications.

·Neither whole nor partial copying of these specifications are permitted without our approval.

If necessary , please ask for assistance from our sales consultant.

·This product is not designed for military, aerospace, medical or other life-critical applications. If you choose to use this product for these applications, please ask us for prior consultation or we cannot take responsibility for problems that may occur.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Noritake:](#)

[GU128X32-800B](#)

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: ocean@oceanchips.ru

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А