

Terminal Relay

G6D-F4PU/G3DZ-F4PU (Push-In Plus Technology)

G6D-F4B/G3DZ-F4B (Screw Terminal)

Model with Push-In Plus technology Added to Terminal Relays with Four-point Output Lineup

- Realized 5 A rating by optimal designs for wide variety of applications (Push-In Plus technology).
 - Push-In Plus terminal enables work reduction and requires no retightening.
 - Short Bars (order separately) ensure easy common wiring and crossover wiring to adjacent terminal relays.
 - Double wire method enables branch wiring (Push-In Plus technology)
 - Each relay has independent coils and contacts for PLC output compatible (both NPN and PNP).
 - Mechanical Relay models and power MOS FET relay models (for high frequency contact ratings) are available.
 - LED operation indicator, diode for coil surge absorption, and tools for easy removal of relays are included as standard equipment.
 - UL and CSA certification for standard models.
- VDE certification for Screws terminal, TÜV certification for Push-In Plus terminal.
IP20 protection code for Push-In Plus models.




For the most recent information on models that have been certified for safety standards, refer to your OMRON website.



Refer to Safety Precautions on page 12.

Features (G6D-F4PU/G3DZ-F4PU (Model with Push-In Plus technology))

Pursuing High Usability




Slimmer Width Yet Larger Power Supply Capacity



Wide Variety of Application

Short Height for Installation in Narrow Spaces



Applicable to Various Number of I/O Points



* Value Design for Panel

Our shared concept "Value Design for Panel" for the specifications of products used in control panels (hereinafter called "Value Design") will create new value to your control panels. Combining multiple products that share the Value Design concept will further increase the value provided to control panels.

G6D-F4PU/G3DZ-F4PU/G6D-F4B/G3DZ-F4B

Ordering Information

When your order, specify the rated voltage.

■ Main unit

Model with Push-In Plus technology

| Mounted Relay type | Contact form | Model | Operation coil ratings |
|---------------------|-----------------------|------------------|------------------------|
| Mechanical Relay | SPST x 4 (1NO x 4) | G6D-F4PU | 12 VDC |
| Power MOS FET relay | | | 24 VDC |
| Power MOS FET relay | SPST x 4 (1NO x 4) | G3DZ-F4PU | 12 VDC |
| | | | 24 VDC |

Model with Screw Terminal

| Mounted Relay type | Contact form | Model | Operation coil ratings |
|-------------------------|-----------------------|-----------------|------------------------|
| Mechanical Relay models | SPST x 4 (1NO x 4) | G6D-F4B | 12 VDC |
| Power MOS FET relay | | | 24 VDC |
| Power MOS FET relay | SPST x 4 (1NO x 4) | G3DZ-F4B | 12 VDC |
| | | | 24 VDC |

■ Accessories (Order Separately)

● Connection socket (single sales available)

G6D-F4PU/G3DZ-F4PU (Model with Push-In Plus technology)

| Model | Operation coil ratings |
|------------------|------------------------|
| P6DF-F4PU | 12 VDC |
| | 24 VDC |

G6D-F4B/G3DZ-F4B (Models with Screw terminal)

| Model | Operation coil ratings |
|-----------------|------------------------|
| P6DF-F4B | 12 VDC |
| | 24 VDC |

Note: 1. Connection socket P6DF-F4B as a single part is not certified by safety standards individually.
2. Single socket which does not mount a relay (with cover)

● Short Bar (G6D-F4PU/G3DZ-F4PU (Model with Push-In Plus technology))

| Pitch | Applicable models | Number of poles | Color | Model*1 |
|---------|------------------------------------|-----------------|-----------------------------------|---|
| 7.75 mm | G6D-F4PU G3DZ-F4PU P6DF-F4PU | 2 | Red (R) Blue (S) Yellow (Y) | PYDN-7.75-020 <input type="checkbox"/> |
| | | 3 | | PYDN-7.75-030 <input type="checkbox"/> |
| | | 4 | | PYDN-7.75-040 <input type="checkbox"/> |
| | | 20 | | PYDN-7.75-200 <input type="checkbox"/> |

Note: Use the Short Bars for crossover wiring within one Socket or between Sockets.

*1. Replace the box () in the model number with the code for the covering color. Selection of the box (): R=Red, S=Blue, Y=Yellow

● Short Bar (G6D-F4B/G3DZ-F4B (Model with Screw Terminal))

| Applicable Terminal Relay Model | Model |
|---------------------------------|-----------------|
| G6D-F4B | G6D-4-SB |
| G3DZ-F4B | |

● Replacement Relay (G6D-F4PU/G3DZ-F4PU (Model with Push-In Plus technology))

| Applicable Terminal Relay Model | Model | Operation coil ratings |
|---------------------------------|-------------------|------------------------|
| G6D-F4PU/G6D-F4B | G6D-1A-ASI | 12 VDC |
| | | 24 VDC |
| G3DZ-F4PU/G3DZ-F4B | G3DZ-2R6PL | 12 VDC |
| | | 24 VDC |

● Parts for DIN Track Mounting

| Appearance | Type | Model |
|---|--------------|----------------------|
|  | DIN Tracks | 1 m PFP-100N |
| | | 0.5 m PFP-50N |
|  | End Plate *1 | PFP-M |
|  | Spacer | PFP-S |

*1. When mounting support rail, please use End Plate (Model PFP-M).

Ratings/Specifications

■ Ratings

● Relay Specification

Coil Ratings (per G6D Relay)

| Operation coil rating | | Rated current (mA) | Coil resistance (Ω) | Must operate voltage (V) | Must release voltage (V) | Max. voltage (V) | Power consumption (mW) |
|-----------------------|----|--------------------|---------------------|--------------------------|--------------------------|------------------|------------------------|
| DC | 12 | 18.7 | 720 | 70% max.* | 10% min. | 130% | Approx. 200 |
| | 24 | 10.5 | 2,880 | | | | |

Note: 1. Rated current and coil resistance were measured at a coil temperature of 23°C with a tolerance of ±20%.

2. Performance characteristic data are measured at a coil temperature of 23°C.

3. The maximum allowable voltage is the maximum value of the operating voltage for the relay coil operating power supply. There is no continuous allowance.

4. The rated current includes the terminal's LED current.

* The must operate voltage is 75% or less of the rated voltage if the relay is mounted in the upside down.

Contact Ratings (per G6D Relay)

G6D-F4PU (Model with Push-In Plus technology)

| Item | Load | Resistive load ($\cos\phi = 1$) |
|---|-------------------------------|-----------------------------------|
| Rated load | 5 A at 250 VAC, 5 A at 30 VDC | |
| Rated carry current | 5 A | |
| Max. switching voltage | 250 VAC, 30 VDC | |
| Max. switching current | 5 A | |
| Max. switching capacity (reference value) | 1,250 VA, 150 W | |

G6D-F4B (Model with Screw terminal)

| Item | Load | Resistive load ($\cos\phi = 1$) |
|---|-------------------------------|-----------------------------------|
| Rated load | 3 A at 250 VAC, 3 A at 30 VDC | |
| Rated carry current | 5 A | |
| Max. switching voltage | 250 VAC, 30 VDC | |
| Max. switching current | 5 A | |
| Max. switching capacity (reference value) | 1,250 VA, 150 W | |

■ Characteristics

| Item | Model | | G6D-F4PU (Model with Push-In Plus technology) |
|--|---------------------------------------|--|--|
| | Relay output | | |
| Contact resistance *1 | | 100 mΩ max. | |
| Operate time *2 | | 10 ms max. | |
| Release time *2 | | 10 ms max. | |
| Insulation resistance | | 1,000 MΩ min. (at 500 VDC) | |
| Dielectric strength | Between coil and contacts | 2,000 VAC, 50/60 Hz for 1 min | |
| | Between contacts of the same polarity | 750 VAC, 50/60 Hz for 1 min | |
| Shock resistance voltage (between coil and contacts) | | 4,000 V (1.2 × 50 μs) | |
| Vibration resistance | Destruction | 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude) | |
| | Malfunction | 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude) | |
| Shock resistance | Destruction | 500 m/s ² | |
| | Malfunction | 100 m/s ² | |
| Endurance | Mechanical | 20,000,000 operations min. (switching frequency: 18,000 operations/hr) | |
| | Electrical *2 | 70,000 operations min. (5 A at 250 VAC, resistive load) 70,000 operations min. (5 A at 30 VDC, resistive load) (at 1,800 switching frequencies/hr) | |
| Failure rate P Level (reference value *3) | | 10 mA at 5 VDC | |
| Ambient operating temperature, Ambient storage temperature | | -25 to 55°C (with no icing) | |
| Ambient operating humidity | | 45% to 85% | |
| LED color | | Yellow | |
| Sealing | | IP20 | |
| Weight | | Approx. 95 g | |

Note: The data shown above are initial values.

*1. Measurement condition: 1 A at 5 VDC

*2. Ambient temperature condition: 23°C

*3. This value is measured at 120 switching frequencies/min.

| Item | Model | | G6D-F4B (Model with Screw terminal) |
|--|---------------------------------------|--|--|
| | Relay output | | |
| Contact resistance *1 | | 100 mΩ max. | |
| Operate time *2 | | 10 ms max. | |
| Release time *2 | | 10 ms max. | |
| Insulation resistance | | 1,000 MΩ min. (at 500 VDC) | |
| Dielectric strength | Between coil and contacts | 2,000 VAC, 50/60 Hz for 1 min | |
| | Between contacts of the same polarity | 750 VAC, 50/60 Hz for 1 min | |
| Shock resistance voltage (between coil and contacts) | | 4,000 V (1.2 × 50 μs) | |
| Vibration resistance | Destruction | 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude) | |
| | Malfunction | 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude) | |
| Shock resistance | Destruction | 500 m/s ² | |
| | Malfunction | 100 m/s ² | |
| Endurance | Mechanical | 20,000,000 operations min. (switching frequency: 18,000 operations/hr) | |
| | Electrical *2 | 200,000 operations min. (3 A at 250 VAC, resistive load) 200,000 operations min. (3 A at 30 VDC, resistive load) (at 1,800 switching frequencies/hr) | |
| Failure rate P Level (reference value *3) | | 10 mA at 5 VDC | |
| Ambient operating temperature, Ambient storage temperature | | -25 to 55°C (with no icing) | |
| Ambient operating humidity | | 45% to 85% | |
| LED color | | Yellow | |
| Sealing | | --- | |
| Weight | | Approx. 65 g | |

Note: The data shown above are initial values.

*1. Measurement condition: 1 A at 5 VDC

*2. Ambient temperature condition: 23°C

*3. This value is measured at 120 switching frequencies/min.

■ Ratings

● Power MOS FET Relay Specifications

Input (per G3DZ Power MOS FET Relay)

| Rated voltage | Operating voltage | Must operate voltage level | Must release voltage level | Input impedance | Rated current |
|---------------|-------------------|----------------------------|----------------------------|-----------------|--------------------------|
| DC | 12 | 9.6 to 14.4 VDC | 9.6 VDC max. | 1 VDC min. | 2 kΩ ±20% 8.0 mA ±20% |
| | 24 | 19.2 to 28.8 VDC | 19.2 VDC max. | | 4 kΩ ±20% 8.2 mA ±20% |

Note: The rated current includes the terminal's LED current.

Output (per G3DZ Power MOS FET Relay)

| Rated operating voltage | Load voltage range | Load current | Inrush current resistance |
|------------------------------|------------------------------|----------------|---------------------------|
| 5 to 240 VAC 5 to 100 VDC | 3 to 264 VAC 3 to 125 VDC | 100 μ to 0.3 A | 6 A (10 ms) |

Note: There is no output polarity for the G3DZ.

■ Characteristics

| Item | Model | G3DZ-F4PU (Model with Push-In Plus technology) |
|--|-------|---|
| | | Power MOS FET relay output |
| Must operate time | | 10 ms max. |
| Release time | | 15 ms max. |
| Output ON-resistance | | 2.4 Ω max. |
| Leakage current at OFF state | | 10 μA max. (at 125 VDC) |
| Insulation resistance | | 100 MΩ min. (at 500 VDC) |
| Dielectric strength between I/O | | 2,000 VAC, 50/60 Hz for 1 min |
| Vibration resistance | | 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude) |
| Shock resistance | | 500 m/s ² |
| Ambient operating temperature, Ambient storage temperature | | -25 to 55°C (with no icing) |
| Ambient operating humidity | | 45% to 85% |
| LED color | | Yellow |
| Sealing | | IP20 |
| Weight | | Approx. 95 g |

| Item | Model | G3DZ-F4B (Model with Screw terminal) |
|--|-------|---|
| | | Power MOS FET relay output |
| Must operate time | | 10 ms max. |
| Release time | | 15 ms max. |
| Output ON-resistance | | 2.4 Ω max. |
| Leakage current at OFF state | | 10 μA max. (at 125 VDC) |
| Insulation resistance | | 100 MΩ min. (at 500 VDC) |
| Dielectric strength between I/O | | 2,000 VAC, 50/60 Hz for 1 min |
| Vibration resistance | | 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude) |
| Shock resistance | | 500 m/s ² |
| Ambient operating temperature, Ambient storage temperature | | -25 to 55°C (with no icing) |
| Ambient operating humidity | | 45% to 85% |
| LED color | | Yellow |
| Sealing | | --- |
| Weight | | Approx. 65 g |

G6D-F4PU/G3DZ-F4PU/G6D-F4B/G3DZ-F4B

■ Ratings for Safety Standard Certification

The rated values for safety standard certification are not the same as individually defined performance values. Always check the specifications before use.

G6D-F4PU/G3DZ-F4PU

●UL-certified Models (File No. E41515)

| Model | Standard number | Category | Listed/Recognition Classification | Operating coil ratings | Number of poles | Contact ratings | Certified number of operations |
|-----------|-----------------|----------|-----------------------------------|------------------------|-----------------|--|--|
| G6D-F4PU | UL508 | NRNT/7 | Listed | 12 VDC 24 VDC | 4 | Rated load voltage 250 VAC 30 VDC Load Current, General Use and Resistive 5 A at 40°C | Mechanical 20,000,000 operations min. (at 18,000 switching frequencies/hr) Electrical 70,000 operations (5 A at 250 VAC, resistive load) 70,000 operations (5 A at 30 VDC, resistive load) (at 1,800 switching frequencies/hr) |
| G3DZ-F4PU | | | | | | Rated load voltage 5-240 VAC 5-100 VDC Load Current, General Use and Resistive 0.3 A at 55°C | --- |
| P6DF-F4PU | | SWIV2 | Recognition | | | Contact terminal 5 A, 250 V | --- |

● CSA-certified Models (File No. LR35535)

| Model | Standard number | Class number | Operating coil ratings | Number of poles | Contact ratings | Certified number of operations |
|-----------|-----------------|--------------------------------|------------------------|-----------------|--------------------------------|--------------------------------|
| P6DF-F4PU | C22.2 NO. 14 | CLASS 3211 07 CLASS 3211 87 | 12 VDC 24 VDC | 4 | Contact terminal 5 A, 250 V | --- |

● TÜV Rheinland Certification (Certification No.R50429253)

| Model | Operating Coil ratings | Number of poles | Contact ratings | Certified number of operations |
|----------|------------------------|-----------------|---|--|
| G6D-F4PU | 12 VDC 24 VDC | 4 | Rated load voltage 250 VAC 30 VDC Load Current, General Use and Resistive 5 A at 40°C | Mechanical 1,000,000 operations (at 18,000 switching frequencies/hr) Electrical 70,000 operations (5 A at 250 VAC, resistive load) 70,000 operations (5 A at 30 VDC, resistive load) (at 1,800 switching frequencies/hr) |

● TÜV Rheinland Certification (Certification No.R50429249)

| Model | Operating Coil ratings | Number of poles | Contact ratings | Certified number of operations |
|-----------|------------------------|-----------------|--|--------------------------------|
| G3DZ-F4PU | 12 VDC 24 VDC | 4 | Rated load voltage 5-240 VAC 5-100 VDC Load Current, General Use and Resistive 0.3 A at 55°C | --- |

● TÜV Rheinland Certification (Certification No.50429224)

| Model | Operating Coil ratings | Number of poles | Contact ratings | Certified number of operations |
|-----------|------------------------|-----------------|--------------------------------|--------------------------------|
| P6DF-F4PU | 12 VDC 24 VDC | 4 | Contact terminal 5 A, 250 V | --- |

G6D-F4B/G3DZ-F4B

● UL-certified Models (File No. E87929)

| Model | Standard number | Category | Listed/Recognition Classification | Operating coil ratings | Number of poles | Contact ratings | Certified number of operations |
|----------|-----------------|----------|-----------------------------------|------------------------|-----------------|---|--------------------------------|
| G6D-F4B | UL508 | SWIV2 | Recognition | 12 VDC 24 VDC | 4 | Rated load voltage 250 VAC 30 VDC | --- |
| G3DZ-F4B | | | | | | Load Current 5 A, Resistive Rated load voltage 3-264 VAC 3-125 VDC Load Current 0.3 A | |

● CSA-certified Models (File No. LR35535)

| Model | Standard number | Class number | Operating coil ratings | Number of poles | Contact ratings | Certified number of operations |
|----------|-----------------|--------------------------------|------------------------|-----------------|--|--------------------------------|
| G6D-F4B | C22.2 NO. 14 | CLASS 3211 07 CLASS 3211 87 | 12 VDC 24 VDC | 4 | Rated load voltage 250 VAC 30 VDC Load Current 5 A, Resistive | --- |
| G3DZ-F4B | | | | | Rated load voltage 3-264 VAC 3-125 VDC Load Current 0.3 A, Resistive | |

● VDE Certification (Certification No.40017757)

| Model | Operating coil ratings | Number of poles | Contact ratings | Certified number of operations |
|---------|------------------------|-----------------|--|--------------------------------|
| G6D-F4B | 12 VDC 24 VDC | 4 | Rated load voltage 250 VAC 24 VDC Load Current 3 A | --- |

● VDE Certification (Certification No.40046252)

| Model | Operating coil ratings | Number of poles | Contact ratings | Certified number of operations |
|----------|------------------------|-----------------|---|--------------------------------|
| G3DZ-F4B | 12 VDC 24 VDC | 4 | Rated load voltage 5-240 VAC 5-100 VDC Load Current 0.3 A | --- |

● VDE Certification (Certification No.40046241)


| Model | Operating coil ratings | Number of poles | Contact ratings | Certified number of operations |
|----------|------------------------|-----------------|--|--------------------------------|
| P6DF-F4B | 12 VDC 24 VDC | 4 | Rated load voltage 250 VAC Load Current 0.3 A | --- |

Engineering Data


■ Engineering Data

● G6D-F4PU


Maximum Switching Capacity




Load Current vs. Ambient Temperature (Product specification)



Endurance Curve




Load Current vs. Ambient Temperature (Specifications with UL and TÜV certification)




● G6D-F4B

Maximum Switching Capacity




Endurance Curve




● G3DZ-F4PU

Load Current vs. Ambient Temperature Inrush current resistance



Non-repetitive
(Keep the inrush current to below the inrush current resistance value (i.e., below the broken line) if it occurs repetitively.)




Note: These data are actual measured values that were sampled from the production line and prepared in graph format, and are for reference purposes only.


A relay is manufactured by mass production, and as a basic rule must be used with allowance made for a certain amount of deviation.

● G3DZ-F4B

Load Current vs. Ambient Temperature Inrush current resistance



Non-repetitive
(Keep the inrush current to below the inrush current resistance value (i.e., below the broken line) if it occurs repetitively.)



Note: These data are actual measured values that were sampled from the production line and prepared in graph format, and are for reference purposes only.

A relay is manufactured by mass production, and as a basic rule must be used with allowance made for a certain amount of deviation.


Dimensions

(Unit: mm)


■ Main unit

G6D-F4PU

G3DZ-F4PU




Terminal Connection Examples



Mounting Hole Dimensions


Note: Pull out the hooks to mount the Relay with screws.



- Note:**
1. Pay utmost attention not to make mistakes with the polarity of the input terminals.
 2. There is no output polarity for G6D-F4PU/G3DZ-F4PU.


G6D-F4B

G3DZ-F4B




Mounting Hole Dimensions

Terminal Arrangement/Internal Connection Diagram (Top View)



- Note:**
1. Pay utmost attention not to make mistakes with the polarity of the input terminals.
 2. There is no output polarity for G6D-F4B/G3DZ-F4B.


Terminal Connection Examples



■ Accessories (Order Separately)

● Short Bars

PYDN-7.75-□□ (7.75 mm)





| Pitch | Applicable model | Number of poles | L (Length) | Color | Model* |
|---------|------------------------------------|-----------------|------------|-----------------------------------|----------------|
| 7.75 mm | G6D-F4PU G3DZ-F4PU P6DF-F4PU | 2 | 15.1 | Red (R) Blue (S) Yellow (Y) | PYDN-7.75-020□ |
| | | 3 | 22.85 | | PYDN-7.75-030□ |
| | | 4 | 30.6 | | PYDN-7.75-040□ |
| | | 20 | 154.6 | | PYDN-7.75-200□ |

* Replace the box (□) in the model number with the code for the covering color. Selection of the box (□): R=Red, S=Blue, Y=Yellow

Note: Use the Short Bars for crossover wiring within one Socket or between Sockets.

● Short Bars

G6D-4-SB






● Parts for DIN Track Mounting

DIN Tracks

PFP-100N


PFP-50N



* () indicates the dimension of PFP-50N.



End Plate

PFP-M



Spacer

PFP-S



Safety Precautions

Be sure to read the Common Precautions for All Relays in the website.

Warning Indications

| | |
|------------------------------------|---|
| Precautions for Safe Use | Supplementary comments on what to do or avoid doing, to use the product safely. |
| Precautions for Correct Use | Supplementary comments on what to do or avoid doing, to prevent failure to operate, malfunction, or undesirable effects on product performance. |

Precautions for Safe Use

● Transport

- Do not transport the I/O Relay Terminal under the following locations. Doing so may occasionally result in damage, malfunction, or deterioration of performance characteristics.
 - Locations subject to water or oil
 - Locations subject to high temperature or high humidity
 - Locations subject to condensation as the result of rapid changes in temperature.
- Do not transport a Socket when it is not packaged. Damage or failure may occur.


● Operating and Storage Environments

- Do not use or store the I/O Relay Terminal in the following locations. Doing so may result in damage, malfunction, or deterioration of performance characteristics.
 - Locations subject to rainwater or water splashes.
 - Locations subject to exposure to water, oil, or chemicals.
 - Locations subject to high temperature or high humidity.
- Storage at locations subject to ambient temperatures outside the range -25 to 55°C
- Usage at locations subject to ambient temperatures outside the range -25 to 55°C
- Locations subject to relative humidity outside the range 45% to 85%
- Locations subject to condensation as the result of rapid changes in temperature.
- Locations subject to corrosive or flammable gases.
- Locations subject to dust, salts, or iron, or locations where there is salt damage
- Locations subject to direct sunlight.
- Locations subject to shock or vibration.

● Installation and Mounting

- Mount the I/O Relay Terminal in the specified direction. Otherwise excessive heat generated by the I/O Relay Terminal may occasionally cause burning.

Mounting Directions



- Mount the I/O Relay Terminal firmly to a DIN Track. Otherwise, the I/O Relay Terminal may fall off.
- Do not handle the I/O Relay Terminal with oily or dusty (especially iron dust) hands.
- Make sure that there is no excessive ambient temperature rise due to the heat generation of the I/O Relay Terminal. If the I/O Relay Terminal is mounted inside a panel, install a fan so that the interior of the panel is fully ventilated.

● Installation and Wiring

- Use wires that are suited to the load current and voltage. Otherwise, excessive heat generated by the wires may cause burning or may cause the wire covering to melt, possibly leading to electric shock.
- Do not use wires with a damaged outer covering. It may result in electric shock or ground leakage. It may result in electric shock or ground leakage.
- Do not wire any wiring in the same duct or conduit as power or high-tension lines. Inductive noise may damage the I/O Relay Terminal or cause it to malfunction.
- Do not apply a voltage or current that exceeds the rating to any terminal. Doing so may result in failure or burning.
- Do not use a deforming Short Bars. Doing so may result in damage, malfunction, or deterioration of performance characteristics.

● Push-In Plus Terminal


- Do not wire anything to the release holes.
- Do not tilt or twist the screwdriver while it is inserted into a release hole on the terminal. The terminal may be damaged.
- Insert a flat-blade screwdriver into the release holes at an angle. The terminal may be damaged if you insert the screwdriver straight in.
- Do not allow the flat-blade screwdriver to fall out while it is inserted into a release hole.
- Do not bend a wire past its natural bending radius or pull on it with excessive force. Doing so may cause the wire disconnection.
- Do not insert more than one wire into each terminal insertion hole.
- To prevent wire materials from smoking or ignition, confirm wire ratings and use the wiring materials given in the following table.

| Recommended wires | Stripping length (Ferrules not used) |
|---|---|
| 0.5 to 1.5 mm ² /AWG20 to 16 | 8 mm |

● Application

- Select a load within the rated values. Not doing so may result in malfunction, failure, or burning.
- The G6D may occasionally rupture if short-circuit current flows. As protection against accidents due to short-circuiting, be sure to install protective devices, such as fuses and no-fuse breakers, on the power supply side.
- Use a power supply within the rated frequencies. Otherwise, malfunction, failure, or burning may occasionally occur.
- Minor electrical shock may occasionally occur if you touch the power charging area such as the terminal wiring area. Always turn OFF the power supply before performing wiring.

- Insert Short Bars so that the protrusion part of a Short Bar comes to the wire insertion side. If the Short Bar is inserted in the upside down direction, the Short Bar may not be inserted securely.




● Recommended Ferrules and Crimp Tools

Recommended ferrules

| Applicable wire | | Ferrules Conductor length (mm) | Stripping length [mm] (Ferrules used) | Recommended ferrules | | |
|------------------------|-------|--------------------------------|--|---------------------------------|----------------------------|----------------------|
| (mm ²) | (AWG) | | | Manufactured by Phoenix Contact | Manufactured by Weidmuller | Manufactured by Wago |
| 0.25 | 24 | 8 | 10 | AI0,25-8 | H0.25/12 | FE-0.25-8N-YE |
| | | 10 | 12 | AI0,25-10 | --- | --- |
| 0.34 | 22 | 8 | 10 | AI0,34-8 | H0.34/12 | FE-0.34-8N-TQ |
| | | 10 | 12 | AI0,34-10 | --- | --- |
| 0.5 | 20 | 8 | 10 | AI0,5-8 | H0.5/14 | FE-0.5-8N-WH |
| | | 10 | 12 | AI0,5-10 | H0.5/16 | FE-0.5-10N-WH |
| 0.75 | 18 | 8 | 10 | AI0,75-8 | H0.75/14 | FE-0.75-8N-GY |
| | | 10 | 12 | AI0,75-10 | H0.75/16 | FE-0.75-10N-GY |
| 1/1.25 | 18/17 | 8 | 10 | AI1-8 | H1.0/14 | FE-1.0-8N-RD |
| | | 10 | 12 | AI1-10 | H1.0/16 | FE-1.0-10N-RD |
| 1.25/1.5 | 17/16 | 8 | 10 | AI1,5-8 | H1.5/14 | FE-1.5-8N-BK |
| | | 10 | 12 | AI1,5-10 | H1.5/16 | FE-1.5-10N-BK |
| Recommended crimp tool | | | CRIMPFOX6 CRIMPFOX6T-F CRIMPFOX10S | PZ6 roto | Variocrimp4 | |

Note: 1. Make sure that the outer diameter of the wire coating is smaller than the inner diameter of the insulation sleeve of the recommended ferrule.

2. Make sure that the ferrule processing dimensions conform to the following figures.




- Wires of AWG24 to AWG22/0.25 mm² to 0.34 mm² are not certified by UL standard.
- Do not connect a ferrule for the applicable wires (AWG17 to AWG16/1.25 mm² to 1.5 mm²) with an adjacent terminal insertion hole.

Precautions for Correct Use

- Do not drop the Socket or subject it to abnormal vibration or shock during transportation or mounting. Doing so may result in deterioration of performance, malfunction, or failure.
- Use a power supply with low noise.


● G6D-F4PU/G3DZ-F4PU (Model with Push-In Plus technology)

1. Connecting Wires to the Push-In Plus Terminal



Connecting Wires with Ferrules and Solid Wires

Insert the solid wire or ferrule straight into the terminal until the end strikes the terminal.




- If a wire is difficult to connect because it is too thin, use a flat-blade screwdriver in the same way as when connecting stranded wire.

Connecting Stranded Wires

Use the following procedure to connect the wires to the terminal.

- Hold a flat-blade screwdriver at an angle and insert it into the release hole. The angle should be between 10° and 15°. If the flat-blade screwdriver is inserted correctly, you will feel the spring in the release hole.
- With the flat-blade screwdriver still inserted into the release hole, insert the wire into the terminal hole until it strikes the terminal.
- Remove the flat-blade screwdriver from the release hole.




Checking Connections

- After the insertion, pull gently on the wire to make sure that it will not come off and the wire is securely fastened to the terminal.
- To prevent short circuits, insert the stripped part of a stranded or solid wire or the conductor part of a ferrule until it is hidden inside the terminal insertion hole.
- If you use recommended ferrules, part of the conductor may be visible after the ferrule is inserted into the terminal, but the product insulation distance will still be satisfied.

2. Removing Wires from the Push-In Plus Terminal

Use the following procedure to remove wires from the terminal. The same method is used to remove stranded wires, solid wires, and ferrules.

1. Hold a flat-blade screwdriver at an angle and insert it into the release hole.
2. With the flat-blade screwdriver still inserted into the release hole, remove the wire from the terminal insertion hole.
3. Remove the flat-blade screwdriver from the release hole.




Recommended Flat-blade Screwdriver

Use a flat-blade screwdriver to connect and remove wires.

Use the following flat-blade screwdriver.

The following table shows manufacturers and models as of 2018/Dec.




| Model | Manufacturer |
|--------------------------------|-----------------|
| ESD 0,40x2,5 | Wera |
| SZS 0,4x2,5 SZF 0-0,4x2,5 * | Phoenix Contact |
| 0.4x2.5x75 302 | Wiha |
| AEF 2,5x75 | Facom |
| 210-719 | Wago |
| SDIS 0,4x2,5x75 | Weidmuller |
| 9900 (-2.5 x 75) | Vessel |

* OMRON's exclusive purchase model XW4Z-00B is available to order as SZF 0-0,4x2,5 (manufactured by Phoenix Contact).


● Relay Replacement

- Use the Relay Removal Tool provided with the Unit to dismount a Terminal Relay.
- Always turn OFF the power supply before replacing Relays.
- When mounting Relays, take care to vertically insert the sockets of relays into the contact pins properly.
- Relays with other models or other voltages cannot be mounted together.



● Removing the Terminal Cover (G6D-F4B)

Hold the base side of the terminal cover as shown in the diagram, and remove the terminal cover by pulling it in upward.



● Mountable Relays

Relays and SSRs cannot be mounted together.

Terms and Conditions Agreement

Read and understand this catalog.

Please read and understand this catalog before purchasing the products. Please consult your OMRON representative if you have any questions or comments.

Warranties.

- (a) Exclusive Warranty. Omron's exclusive warranty is that the Products will be free from defects in materials and workmanship for a period of twelve months from the date of sale by Omron (or such other period expressed in writing by Omron). Omron disclaims all other warranties, express or implied.
- (b) Limitations. OMRON MAKES NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, ABOUT NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE OF THE PRODUCTS. BUYER ACKNOWLEDGES THAT IT ALONE HAS DETERMINED THAT THE PRODUCTS WILL SUITABLY MEET THE REQUIREMENTS OF THEIR INTENDED USE.

Omron further disclaims all warranties and responsibility of any type for claims or expenses based on infringement by the Products or otherwise of any intellectual property right. (c) Buyer Remedy. Omron's sole obligation hereunder shall be, at Omron's election, to (i) replace (in the form originally shipped with Buyer responsible for labor charges for removal or replacement thereof) the non-complying Product, (ii) repair the non-complying Product, or (iii) repay or credit Buyer an amount equal to the purchase price of the non-complying Product; provided that in no event shall Omron be responsible for warranty, repair, indemnity or any other claims or expenses regarding the Products unless Omron's analysis confirms that the Products were properly handled, stored, installed and maintained and not subject to contamination, abuse, misuse or inappropriate modification. Return of any Products by Buyer must be approved in writing by Omron before shipment. Omron Companies shall not be liable for the suitability or unsuitability or the results from the use of Products in combination with any electrical or electronic components, circuits, system assemblies or any other materials or substances or environments. Any advice, recommendations or information given orally or in writing, are not to be construed as an amendment or addition to the above warranty.

See <http://www.omron.com/global/> or contact your Omron representative for published information.

Limitation on Liability; Etc.

OMRON COMPANIES SHALL NOT BE LIABLE FOR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, LOSS OF PROFITS OR PRODUCTION OR COMMERCIAL LOSS IN ANY WAY CONNECTED WITH THE PRODUCTS, WHETHER SUCH CLAIM IS BASED IN CONTRACT, WARRANTY, NEGLIGENCE OR STRICT LIABILITY.

Further, in no event shall liability of Omron Companies exceed the individual price of the Product on which liability is asserted.

Suitability of Use.

Omron Companies shall not be responsible for conformity with any standards, codes or regulations which apply to the combination of the Product in the Buyer's application or use of the Product. At Buyer's request, Omron will provide applicable third party certification documents identifying ratings and limitations of use which apply to the Product. This information by itself is not sufficient for a complete determination of the suitability of the Product in combination with the end product, machine, system, or other application or use. Buyer shall be solely responsible for determining appropriateness of the particular Product with respect to Buyer's application, product or system. Buyer shall take application responsibility in all cases.

NEVER USE THE PRODUCT FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY OR IN LARGE QUANTITIES WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISKS, AND THAT THE OMRON PRODUCT(S) IS PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

Programmable Products.

Omron Companies shall not be responsible for the user's programming of a programmable Product, or any consequence thereof.

Performance Data.

Data presented in Omron Company websites, catalogs and other materials is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of Omron's test conditions, and the user must correlate it to actual application requirements. Actual performance is subject to the Omron's Warranty and Limitations of Liability.

Change in Specifications.

Product specifications and accessories may be changed at any time based on improvements and other reasons. It is our practice to change part numbers when published ratings or features are changed, or when significant construction changes are made. However, some specifications of the Product may be changed without any notice. When in doubt, special part numbers may be assigned to fix or establish key specifications for your application. Please consult with your Omron's representative at any time to confirm actual specifications of purchased Product.

Errors and Omissions.

Information presented by Omron Companies has been checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical or proofreading errors or omissions.

OMRON Corporation Industrial Automation Company**Kyoto, JAPAN****Contact: www.ia.omron.com****Regional Headquarters****OMRON EUROPE B.V.**

Wegalaan 67-69, 2132 JD Hoofddorp

The Netherlands

Tel: (31)2356-81-300/Fax: (31)2356-81-388

OMRON ASIA PACIFIC PTE. LTD.No. 438A Alexandra Road # 05-05/08 (Lobby 2),
Alexandra Technopark,
Singapore 119967
Tel: (65) 6835-3011/Fax: (65) 6835-2711**OMRON ELECTRONICS LLC**2895 Greenspoint Parkway, Suite 200
Hoffman Estates, IL 60169 U.S.A.
Tel: (1) 847-843-7900/Fax: (1) 847-843-7787**OMRON (CHINA) CO., LTD.**Room 2211, Bank of China Tower,
200 Yin Cheng Zhong Road,
PuDong New Area, Shanghai, 200120, China
Tel: (86) 21-5037-2222/Fax: (86) 21-5037-2200**Authorized Distributor:**© OMRON Corporation 2019 All Rights Reserved.
In the interest of product improvement,
specifications are subject to change without notice.CSM_1_1_0319
Cat. No. J228-E1-01

0319(0319)

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Omron](#):

[G3DZ-F4PU DC12](#) [G3DZ-F4PU DC24](#) [G6D-F4PU DC12](#) [G6D-F4PU DC24](#)



OCEAN CHIPS

Океан Электроники

Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибутором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибутором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: ocean@oceanchips.ru

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А