SoftStore 2K x 8 nvSRAM

Features

- High-performance CMOS non-volatile static RAM 2048 x 8 bits
- 25, 35 and 45 ns Access Times
- 12, 20 and 25 ns Output Enable Access Times
- Software STORE Initiation (STORE Cycle Time < 10 ms)
- Automatic STORE Timing
- 10^5 STORE cycles to EEPROM
- 10 years data retention in EEPROM
- Automatic RECALL on Power Up
- Software RECALL Initiation (RECALL Cycle Time < 20 µs)
- Unlimited RECALL cycles from EEPROM
- Unlimited Read and Write to SRAM
- Single 5 V ± 10 % Operation
- Operating temperature ranges:
  0 to 70 °C
  -40 to 85 °C
- CECC 90000 Quality Standard
- ESD characterization according
- MIL STD 883C M3015.7-HBM (classification see IC Code Numbers)
- Packages: PDIP28 (300 mil)
  PDIP28 (600 mil)
  SOP28 (300 mil)
  SOP24 (300 mil)

Description

The U631H16 has two separate modes of operation: SRAM mode and nonvolatile mode. In SRAM mode, the memory operates as an ordinary static RAM. In nonvolatile operation, data is transferred in parallel from SRAM to EEPROM or from EEPROM to SRAM. In this mode SRAM functions are disabled.

The U631H16 is a fast static RAM (25, 35, 45 ns), with a nonvolatile electrically erasable PROM (EEPROM) element incorporated in each static memory cell. The SRAM can be read and written an unlimited number of times, while independent nonvolatile data resides in EEPROM.

Data transfers from the SRAM to the EEPROM (the STORE operation), or from the EEPROM to the SRAM (the RECALL) operation) are initiated through software sequences.

The U631H16 combines the high performance and ease of use of a fast SRAM with nonvolatile data integrity.


Once a STORE cycle is initiated, further input or output are disabled until the cycle is completed.

Because a sequence of addresses is used for STORE initiation, it is important that no other read or write accesses intervene in the sequence or the sequence will be aborted.


Internally, RECALL is a two step procedure. First, the SRAM data is cleared and second, the nonvolatile information is transferred into the SRAM cells.

The RECALL operation in no way alters the data in the EEPROM cells. The nonvolatile data can be recalled an unlimited number of times.

Pin Configuration



Top View




Top View

Pin Description

Signal Name	Signal Description
A0 - A10	Address Inputs
DQ0 - DQ7	Data In/Out
$\overline{E}$	Chip Enable
$\overline{G}$	Output Enable
$\overline{W}$	Write Enable
VCC	Power Supply Voltage
VSS	Ground

Block Diagram



Truth Table for SRAM Operations

Operating Mode	$\overline{E}$	$\overline{W}$	$\overline{G}$	DQ0 - DQ7
Standby/not selected	H	*	*	High-Z
Internal Read	L	H	H	High-Z
Read	L	H	L	Data Outputs Low-Z
Write	L	L	*	Data Inputs High-Z

*H or L

Characteristics

All voltages are referenced to V_{SS} = 0 V (ground).
All characteristics are valid in the power supply voltage range and in the operating temperature range specified.
Dynamic measurements are based on a rise and fall time of ≤ 5 ns, measured between 10 % and 90 % of V_I, as well as input levels of V_{IL} = 0 V and V_{IH} = 3 V. The timing reference level of all input and output signals is 1.5 V, with the exception of the t_{dis}-times and t_{en}-times, in which cases transition is measured ± 200 mV from steady-state voltage.

Absolute Maximum Ratings[a]		Symbol	Min.	Max.	Unit
Power Supply Voltage		V_{CC}	-0.5	7	V
Input Voltage		V_I	-0.3	V_{CC}+0.5	V
Output Voltage		V_O	-0.3	V_{CC}+0.5	V
Power Dissipation		P_D		1	W
Operating Temperature	C-Type K-Type	T_a	0 -40	70 85	°C °C
Storage Temperature		T_{stg}	-65	150	°C

a: Stresses greater than those listed under „Absolute Maximum Ratings“ may cause permanent damage to the device. This is a stress rating only, and functional operation of the device at condition above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

Recommended Operation Conditions	Symbol	Conditions	Min.	Max.	Unit
Power Supply Voltage	V_{CC}		4.5	5.5	V
Input Low Voltage	V_{IL}	-2 V at Pulse Width 10 ns permitted	-0.3	0.8	V
Input High Voltage	V_{IH}		2.2	V_{CC}+0.3	V

DC Characteristics	Symbol	Conditions	C-Type		K-Type		Unit
			Min.	Max.	Min.	Max.	
Operating Supply Current[b]	I_{CC1}	V_{CC} = 5.5 V V_{IL} = 0.8 V V_{IH} = 2.2 V					
		t_c = 25 ns		90		95	mA
		t_c = 35 ns		80		85	mA
		t_c = 45 ns		75		80	mA
Average Supply Current during STORE[c]	I_{CC2}	V_{CC} = 5.5 V $\overline{E}$ ≥ V_{CC}-0.2 V $\overline{W}$ ≥ V_{CC}-0.2 V V_{IL} ≤ 0.2 V V_{IH} ≥ V_{CC}-0.2 V		6		7	mA
Standby Supply Current[d] (Cycling TTL Input Levels)	$I_{CC(SB)1}$	V_{CC} = 5.5 V $\overline{E}$ ≥ V_{IH}					
		t_c = 25 ns		30		34	mA
		t_c = 35 ns		23		27	mA
		t_c = 45 ns		20		23	mA
Average Supply Current at t_{cR} = 200 ns[b] (Cycling CMOS Input Levels)	I_{CC3}	V_{CC} = 5.5 V $\overline{W}$ ≥ V_{CC}-0.2 V V_{IL} ≤ 0.2 V V_{IH} ≥ V_{CC}-0.2 V		15		15	mA
Standby Supply Current[d] (Stable CMOS Input Levels)	$I_{CC(SB)}$	V_{CC} = 5.5 V $\overline{E}$ ≥ V_{CC}-0.2 V V_{IL} ≤ 0.2 V V_{IH} ≥ V_{CC}-0.2 V		1		1	mA

b: I_{CC1} and I_{CC3} are dependent on output loading and cycle rate. The specified values are obtained with outputs unloaded. The current I_{CC1} is measured for WRITE/READ - ratio of 1/2.

c: I_{CC2} is the average current required for the duration of the STORE cycle (STORE Cycle Time).

d: Bringing $\overline{E} \geq V_{IH}$ will not produce standby current levels until any nonvolatile cycle in progress has timed out. See MODE SELECTION table. The current $I_{CC(SB)1}$ is measured for WRITE/READ - ratio of 1/2.


DC Characteristics	Symbol	Conditions	C-Type		K-Type		Unit
			Min.	Max.	Min.	Max.	
Output High Voltage	V_{OH}	V_{CC} = 4.5 V, I_{OH} =-4 mA	2.4		2.4		V
Output Low Voltage	V_{OL}	I_{OL} = 8 mA		0.4		0.4	V
Output High Current	I_{OH}	V_{CC} = 4.5 V, V_{OH} = 2.4 V		-4		-4	mA
Output Low Current	I_{OL}	V_{OL} = 0.4 V	8		8		mA
Input Leakage Current		V_{CC} = 5.5 V					
High	I_{IH}	V_{IH} = 5.5 V		1		1	µA
Low	I_{IL}	V_{IL} = 0 V	-1		-1		µA
Output Leakage Current		V_{CC} = 5.5 V					
High at Three-State- Output	I_{OHZ}	V_{OH} = 5.5 V		1		1	µA
Low at Three-State- Output	I_{OLZ}	V_{OL} = 0 V	-1		-1		µA

SRAM MEMORY OPERATIONS


No.	Switching Characteristics Read Cycle	Symbol		25		35		45		Unit
		Alt.	IEC	Min.	Max.	Min.	Max.	Min.	Max.	
1	Read Cycle Time[f]	t_{AVAV}	t_{cR}	25		35		45		ns
2	Address Access Time to Data Valid[g]	t_{AVQV}	$t_{a(A)}$		25		35		45	ns
3	Chip Enable Access Time to Data Valid	t_{ELQV}	$t_{a(E)}$		25		35		45	ns
4	Output Enable Access Time to Data Valid	t_{GLQV}	$t_{a(G)}$		12		20		25	ns
5	$\overline{E}$ HIGH to Output in High-Z[h]	t_{EHQZ}	$t_{dis(E)}$		13		17		20	ns
6	$\overline{G}$ HIGH to Output in High-Z[h]	t_{GHQZ}	$t_{dis(G)}$		13		17		20	ns
7	$\overline{E}$ LOW to Output in Low-Z	t_{ELQX}	$t_{en(E)}$	5		5		5		ns
8	$\overline{G}$ LOW to Output in Low-Z	t_{GLQX}	$t_{en(G)}$	0		0		0		ns
9	Output Hold Time after Addr. Change[g]	t_{AXQX}	$t_{v(A)}$	3		3		3		ns
19	Chip Enable to Power Active[e]	t_{ELICCH}		0		0		0		ns
11	Chip Disable to Power Standby[d, e]	t_{EHICCL}			25		35		45	ns

e: Parameter guaranteed but not tested.
f: Device is continuously selected with $\overline{E}$ and $\overline{G}$ both LOW.
g: Address valid prior to or at the same time with $\overline{E}$ transition LOW.
h: Measured ± 200 mV from steady state output voltage.

Read Cycle 1: Ai-controlled (during Read cycle: $\overline{E}$ = $\overline{G}$ = V_{IL}, $\overline{W}$ = V_{IH})[f]




Read Cycle 2: $\overline{G}$-, $\overline{E}$-controlled (during Read cycle: $\overline{W}$ = V_{IH})[g]




No.	Switching Characteristics Write Cycle	Symbol			25		35		45		Unit
		Alt. #1	Alt. #2	IEC	Min.	Max.	Min.	Max.	Min.	Max.	
12	Write Cycle Time	t_{AVAV}	t_{AVAV}	t_{cW}	25		35		45		ns
13	Write Pulse Width	t_{WLWH}		$t_{w(W)}$	20		30		35		ns
14	Write Pulse Width Setup Time		t_{WLEH}	$t_{su(W)}$	20		30		35		ns
15	Address Setup Time	t_{AVWL}	t_{AVEL}	$t_{su(A)}$	0		0		0		ns
16	Address Valid to End of Write	t_{AVWH}	t_{AVEH}	$t_{su(A-WH)}$	20		30		35		ns
17	Chip Enable Setup Time	t_{ELWH}		$t_{su(E)}$	20		30		35		ns
18	Chip Enable to End of Write		t_{ELEH}	$t_{w(E)}$	20		30		35		ns
19	Data Setup Time to End of Write	t_{DVWH}	t_{DVEH}	$t_{su(D)}$	12		18		20		ns
20	Data Hold Time after End of Write	t_{WHDX}	t_{EHDX}	$t_{h(D)}$	0		0		0		ns
21	Address Hold after End of Write	t_{WHAX}	t_{EHAX}	$t_{h(A)}$	0		0		0		ns
22	$\overline{W}$ LOW to Output in High-Z[h, i]	t_{WLQZ}		$t_{dis(W)}$		10		13		15	ns
23	$\overline{W}$ HIGH to Output in Low-Z	t_{WHQX}		$t_{en(W)}$	5		5		5		ns

Write Cycle #1: $\overline{W}$-controlled[j]



Write Cycle #2: $\overline{E}$-controlled[j]



undefined L- to H-level H- to L-level


i: If $\overline{W}$ is LOW and when $\overline{E}$ goes LOW, the outputs remain in the high impedance state.
j: $\overline{E}$ or $\overline{W}$ must be $\geq V_{IH}$ during address transitions.

NONVOLATILE MEMORY OPERATIONS

No.	STORE CYCLE INHIBIT and AUTOMATIC POWER UP RECALL	Symbol		Min.	Max.	Unit
		Alt.	IEC			
24	Power Up RECALL Duration[k, e]	$t_{RESTORE}$			650	µs
	Low Voltage Trigger Level	V_{SWITCH}		4.0	4.5	V

k: $t_{RESTORE}$ starts from the time V_{CC} rises above V_{SWITCH}.

STORE CYCLE INHIBIT and AUTOMATIC POWER UP RECALL



SOFTWARE MODE SELECTION

$\overline{E}$	$\overline{W}$	A10 - A0 (hex)	Mode	I/O	Power	Notes
L	H	000	Read SRAM	Output Data	Active	l, m
		555	Read SRAM	Output Data		l, m
		2AA	Read SRAM	Output Data		l, m
		7FF	Read SRAM	Output Data		l, m
		0F0	Read SRAM	Output Data		l, m
		70F	Nonvolatile STORE	Output High Z	I_{CC2}	l
L	H	000	Read SRAM	Output Data	Active	l, m
		555	Read SRAM	Output Data		l, m
		2AA	Read SRAM	Output Data		l, m
		7FF	Read SRAM	Output Data		l, m
		0F0	Read SRAM	Output Data		l, m
		70E	Nonvolatile RECALL	Output High Z		l


l: The six consecutive addresses must be in order listed (000, 555, 2AA, 7FF, 0F0, 70F) for a Store cycle or (000, 555, 2AA, 7FF, 0F0, 70E) for a RECALL cycle. $\overline{W}$ must be high during all six consecutive cycles. See STORE cycle and RECALL cycle tables and diagrams for further details.
The following six-address sequence is used for testing purposes and should not be used: 000, 555, 2AA, 7FF, 0F0, 39C.

m: I/O state assumes that $\overline{G} \leq V_{IL}$. Activation of nonvolatile cycles does not depend on the state of $\overline{G}$.


No.	Software Controlled STORE/RECALL Cycle[l, n]	Symbol		25		35		45		Unit
		Alt.	IEC	Min.	Max.	Min.	Max.	Min.	Max.	
25	STORE/RECALL Initiation Time	t_{AVAV}	t_{cR}	25		35		45		ns
26	Chip Enable to Output Inactive[o]	t_{ELQZ}	$t_{dis(E)SR}$		600		600		600	ns
27	STORE Cycle Time[p]	t_{ELQXS}	$t_{d(E)S}$		10		10		10	ms
28	RECALL Cycle Time[q]	t_{ELQXR}	$t_{d(E)R}$		20		20		20	µs
29	Address Setup to Chip Enable[r]	t_{AVELN}	$t_{su(A)SR}$	0		0		0		ns
30	Chip Enable Pulse Width[r, s]	t_{ELEHN}	$t_{w(E)SR}$	20		25		35		ns
31	Chip Disable to Address Change[r]	t_{EHAXN}	$t_{h(A)SR}$	0		0		0		ns

n: The software sequence is clocked with $\overline{E}$ controlled READs.
o: Once the software controlled STORE or RECALL cycle is initiated, it completes automatically, ignoring all inputs.
p: Note that STORE cycles (but not RECALL) are aborted by $V_{CC} < V_{SWITCH}$ (STORE inhibit).
q: An automatic RECALL also takes place at power up, starting when V_{CC} exceeds V_{SWITCH} and takes $t_{RESTORE}$. V_{CC} must not drop below V_{SWITCH} once it has been exceeded for the RECALL to function properly.
r: Noise on the $\overline{E}$ pin may trigger multiple READ cycles from the same address and abort the address sequence.
s: If the Chip Enable Pulse Width is less than $t_{a(E)}$ (see Read Cycle) but greater than or equal $t_{w(E)SR}$, than the data may not be valid at the end of the low pulse, however the STORE or RECALL will still be initiated.

SOFTWARE CONTROLLED STORE/RECALL CYCLE[r, s, t, u] ($\overline{E}$ = HIGH after STORE initiation)




SOFTWARE CONTROLLED STORE/RECALL CYCLE[r, s, t, u] ($\overline{E}$ = LOW after STORE initiation)



t: $\overline{W}$ must be HIGH when $\overline{E}$ is LOW during the address sequence in order to initiate a nonvolatile cycle. $\overline{G}$ may be either HIGH or LOW throughout. Addresses 1 through 6 are found in the mode selection table. Address 6 determines whether the U631H16 performs a STORE or RECALL.
u: $\overline{E}$ must be used to clock in the address sequence for the Software controlled STORE and RECALL cycles.

Test Configuration for Functional Check



v: In measurement of t_{dis}-times and t_{en}-times the capacitance is 5 pF.

w: Between V_{CC} and V_{SS} must be connected a high frequency bypass capacitor 0.1 µF to avoid disturbances.

Capacitance[e]	Conditions	Symbol	Min.	Max.	Unit
Input Capacitance	V_{CC} = 5.0 V V_I = V_{SS} f = 1MHz T_a = 25 °C	C_I		8	pF
Output Capacitance		C_O		7	pF

All pins not under test must be connected with ground by capacitors.

IC Code Numbers

Example

U631H16 B D C 25

Type

ESD Class
blank > 2000 V[x]
B > 1000 V

Package
D = PDIP28 (300 mil)
D1= PDIP28 (600 mil)
S = SOP28 (300 mil)
S1= SOP24 (300 mil)

Operating Temperature Range
C = 0 to 70 °C
K = -40 to 85 °C

Access Time
25 = 25 ns
35 = 35 ns (on special request)
45 = 45 ns (on special request)

The date of manufacture is given by the last 4 digits of the mark, the first 2 digits indicating the year, and the last 2 digits the calendar week.

x: ESD protection > 2000 V under development

Device Operation

The U631H16 has two separate modes of operation: SRAM mode and nonvolatile mode. In SRAM mode, the memory operates as a standard fast static RAM. In nonvolatile mode, data is transferred from SRAM to EEPROM (the STORE operation) or from EEPROM to SRAM (the RECALL operation). In this mode SRAM functions are disabled.

SRAM READ

The U631H16 performs a READ cycle whenever $\overline{E}$ and $\overline{G}$ are LOW while $\overline{W}$ is HIGH. The address specified on pins A0 - A10 determines which of the 2048 data bytes will be accessed. When the READ is initiated by an address transition, the outputs will be valid after a delay of t_{cR}. If the READ is initiated by $\overline{E}$ or $\overline{G}$, the outputs will be valid at $t_{a(E)}$ or at $t_{a(G)}$, whichever is later. The data outputs will repeatedly respond to address changes within the t_{cR} access time without the need for transition on any control input pins, and will remain valid until another address change or until $\overline{E}$ or $\overline{G}$ is brought HIGH or $\overline{W}$ is brought LOW.

SRAM WRITE

A WRITE cycle is performed whenever $\overline{E}$ and $\overline{W}$ are LOW. The address inputs must be stable prior to entering the WRITE cycle and must remain stable until ei-ther $\overline{E}$ or $\overline{W}$ goes HIGH at the end of the cycle. The data on pins DQ0 - 7 will be written into the memory if it is valid $t_{su(D)}$ before the end of a $\overline{W}$ controlled WRITE or $t_{su(D)}$ before the end of an $\overline{E}$ controlled WRITE.
It is recommended that $\overline{G}$ is kept HIGH during the entire WRITE cycle to avoid data bus contention on the common I/O lines. If $\overline{G}$ is left LOW, internal circuitry will turn off the output buffers $t_{dis(W)}$ after $\overline{W}$ goes LOW.

NOISE CONSIDERATION

The U631H16 is a high speed memory and therefore it must have a high frequency bypass capacitor of approximately 0.1 µF connected between V_{CC} and V_{SS} using leads and traces that are as short as possible. As with all high speed CMOS ICs, normal carefull routing of power, ground and signals will help prevent noise problems.

SOFTWARE NONVOLATILE STORE

The U631H16 software controlled STORE cycle is initiated by executing sequential READ cycles from six specific address locations. By relying on READ cycles only, the U631H16 implements nonvolatile operation while remaining compatible with standard 2K x 8 SRAMs. During the STORE cycle, an erase of the previous nonvolatile data is first performed, followed by parallel programming of all nonvolatile elements. Once a STORE cycle is initiated, further inputs and outputs are disabled until the cycle is completed.
Because a sequence of addresses is used for STORE initiation, it is important that no other READ or WRITE accesses intervene in the sequence or the sequence will be aborted and no STORE or RECALL will take place.
To initiate the STORE cycle the following READ sequence must be performed:

1.	Read address	000	(hex)	Valid READ
2.	Read address	555	(hex)	Valid READ
3.	Read address	2AA	(hex)	Valid READ
4.	Read address	7FF	(hex)	Valid READ
5.	Read address	0F0	(hex)	Valid READ
6.	Read address	70F	(hex)	Initiate STORE

Once the sixth address in the sequence has been entered, the STORE cycle will commence and the chip will be disabled. It is important that READ cycles and not WRITE cycles are used in the sequence. It is not necessary that $\overline{G}$ is LOW for the sequence to be valid. After the t_{STORE} cycle time has been fulfilled, the SRAM will again be activated for READ and WRITE operation.

SOFTWARE NONVOLATILE RECALL

A RECALL cycle of the EEPROM data into the SRAM is initiated with a sequence of READ operations in a manner similar to the STORE initiation. To initiate the RECALL cycle the following sequence of READ operations must be performed:

1.	Read address	000	(hex)	Valid READ
2.	Read address	555	(hex)	Valid READ
3.	Read address	2AA	(hex)	Valid READ
4.	Read address	7FF	(hex)	Valid READ
5.	Read address	0F0	(hex)	Valid READ
6.	Read address	70E	(hex)	Initiate RECALL

Internally, RECALL is a two step procedure. First, the SRAM data is cleared and second, the nonvolatile information is transferred into the SRAM cells. The RECALL operation in no way alters the data in the EEPROM cells. The nonvolatile data can be recalled an unlimited number of times.

AUTOMATIC POWER UP RECALL

On power up, once V_{CC} exceeds the sense voltage of V_{SWITCH}, a RECALL cycle is automatically initiated. The voltage on the V_{CC} pin must not frop belwo V_{SWITCH} once it has risen above it in order for the RECALL to operate properly. Due to this automatic RECALL, SRAM operation cannot commence until $t_{RESTORE}$ after V_{CC} exceeds V_{SWITCH}.

If the U631H16 is in a WRITE state at the end of power up RECALL, the SRAM data will be corrupted.
To help avoid this situation, a 10 KΩ resistor should be connected between $\overline{W}$ and V_{CC}.

HARDWARE PROTECTION

The U631H16 offers hardware protection against inadvertent STORE operation through V_{CC} sense.
For $V_{CC} < V_{SWITCH}$ the software initiated STORE operation will be inhibited.

LOW AVERAGE ACTIVE POWER

The U631H16 has been designed to draw significantly less power when $\overline{E}$ is LOW (chip enabled) but the access cycle time is longer than 55 ns.
When $\overline{E}$ is HIGH the chip consumes only standby current.
The overall average current drawn by the part depends on the following items:
1. CMOS or TTL input levels
2. the time during which the chip is disabled ($\overline{E}$ HIGH)
3. the cycle time for accesses ($\overline{E}$ LOW)
4. the ratio of READs to WRITEs
5. the operating temperature
6. the V_{CC} level



Memory Products 1998
SoftStore 2K x 8 nvSRAM U631H16

LIFE SUPPORT POLICY
ZMD products are not designed, intended, or authorized for use as components in systems intend for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the ZMD product could create a situation where personal injury or death may occur. Components used in life-support devices or systems must be expressly authorized by ZMD for such purpose.

The information describes the type of component and shall not be considered as assured characteristics.

Terms of delivery and rights to change design reserved.

Zentrum Mikroelektronik Dresden GmbH
Grenzstraße 28 • D-01109 Dresden • P. O. B. 80 01 34 • D-01101 Dresden • Germany
Phone: +49 351 88 22-3 06 • Fax: +49 351 88 22-3 37 • Email: sales@zmd.de
Internet Web Site: http://www.zmd.de

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А