VAC VACUUMSCHMELZE	SPECIFICATION	Item no.:	T60404-N4646-X412

K-No.: 24618	**50/100 A Current Sensor** For the electronic measurement of currents: DC, AC, pulsed, mixed ..., with a galvanic Isolation between the primary circuit (high power) and the secondary circuit (electronic circuit)		Date: 28.01.2008
Customer: Standard type		Customers Part no.:	Page 1 of 2

Description

- Closed loop (compensation) Current Sensor with magnetic field probe
- Printed circuit board mounting
- Casing and materials UL-listed

Characteristics

- Excellent accuracy
- Very low offset current
- Very low temperature dependency and offset current drift
- Very low hysteresis of offset current
- Low response time
- Wide frequency bandwidth
- Compact design
- Reduced offset ripple

Applications

Mainly used for stationary operation in industrial applications:

- AC variable speed drives and servo motor drives
- Static converters for DC motor drives
- Battery supplied applications
- Switched Mode Power Supplies (SMPS)
- Power Supplies for welding applications
- Uninterruptable Power Supplies (UPS)

Electrical data – Ratings[1)]

I_{PN}	Primary nominal r.m.s. current		
	@ V_C = ±15V, R_M ≥ 0 Ω	50	A
	@ V_C = ±12V, R_M ≥ 0 Ω or V_C = ±15V, R_M ≥ 16 Ω	100	A
R_M	Measuring resistance V_C=± 12V	0 ... 200	Ω
	V_C=± 15V	16 … 400	Ω
I_{SN}	Secondary nominal r.m.s. current	25/50	mA
K_N	Turns ratio	1…3 : 2000	

Accuracy – Dynamic performance data[1)]

		min.	typ.	max.	Unit
$I_{P,max}$	Max. measuring range				
	@ V_C = ±12V, R_M = 10 Ω (t_{max} = 10sec)	±145			A
	@ V_C = ±15V, R_M = 16 Ω (t_{max} = 10sec)	±175			A
X	Accuracy @ I_{PN}, T_A= 25°C		0.1	0.5	%
ε_L	Linearity			0.1	%
I_0	Offset current @ I_P=0, T_A= 25°C		0.02	0.08	mA
t_r	Response time		500		ns
Δt ($I_{P,max}$)	Delay time at di/dt = 100 A/µs		200		ns
f	Frequency bandwidth	DC...200			kHz

General data[1)]

		min.	typ.	max.	Unit
T_A	Ambient operating temperature	-40		+85	°C
T_S	Ambient storage temperature	-40		+90	°C
m	Mass		13,5		g
V_C	Supply voltage	±11.4	±12 or ±15	±15.75	V
I_C	Current consumption		18.5		mA
	Constructed and manufactored and tested in accordance with EN 61800-5-1 (Pin 1 - 6 to Pin 7 – 9) Reinforced insulation, Insulation material group 1, Pollution degree 2				
S_{clear}	clearance (component without solder pad)	10.2			mm
S_{creep}	creepage (component without solder pad)	10.2			mm
V_{sys}	System voltage overvoltage category 3	RMS		600	V
V_{work}	Working voltage (table 7 acc. to EN61800-5-1)	RMS		1020	V
U_{PD}	Rated discharge voltage	peak value		1400	V

Date	Name	Isuue	Amendment
28.01.08	Le	81	Date changed. Insignificant

Hrsg.: KB-E editor	Bearb: SA designer		KB-E BE: Len. check	KB-PM IA: KRe. check		freig.: Heu. released

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden
Any offenders are liable to pay all relevant damages.

VAC VACUUMSCHMELZE	SPECIFICATION	Item no.:	T60404-N4646-X412

K-No.: 24618	**50/100 A Current Sensor** For the electronic measurement of currents: DC, AC, pulsed, mixed ..., with a galvanic Isolation between the primary circuit (high power) and the secondary circuit (electronic circuit)		Date: 28.01.2008
Customer: Standard type		Customers Part no.:	Page 2 of 2

Mechanical outline (mm): General tolerances DIN ISO 2768-c



Connections:
1...6: ∅ 1,5 mm
7...9: 0,6x0,7 mm

Marking:

VAC
4646X412
F DC

DC = Date Code
F= Factory

Schematic diagram



Possibilities of wiring for V_C = ±15V [1] (@ T_A = 85°C, R_M = 25 Ω)

primary windings N_P	primary current RMS I_P [A]	primary current maximal $\hat{I}_{P,max}$ [A]	output current RMS I_S (I_P) [mA]	turns ratio K_N	primary resistance R_P [mW]	wiring
1	100	175	50	1:2000	0.12	
2	35	82	35	2:2000	0.54	
3	25	58	37,5	3:2000	1.1	

[1] preliminary data

Temperature of the primary conductor should not exceed 100°C.
Additional information is obtainable on request.
This specification is no declaration of warranty acc. BGB §443 dar.

Hrsg.: KB-E editor	Bearb: SA designer		KB-E BE: Len. check	KB-PM IA: KRe. check		freig.: Heu. released

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden
Any offenders are liable to pay all relevant damages.

VAC VACUUMSCHMELZE	Additional Information	Item No.: T60404-N4646-X412

K-No.: 24618

50/100 A Current Sensor
For electronic current measurement:
DC, AC, pulsed, mixed ..., with a galvanic isolation between primary circuit (high power) and secondary circuit



Date: 28.01.2008

Customer: | Customers Part No.: |

Electrical Data (investigate by a type checking) [1)]

		min.	typ.	max.	Unit
V_{Ctot}	Maximum supply voltage (without function) ±15.75 bis ±18 V: for 1s per hour			±18	V
R_S	Secondary coil resistance @ T_A=85°C			145	Ω
R_p	Primary coil resistance per turn @ T_A=25°C			0.36	mΩ
X_{Ti}	Temperature drift of X @ T_A = -40 ... +85 °C			0.1	%
I_{0ges}	Offset current (including I_0, I_{0t}, I_{0T})			0.1	mA
I_{0t}	Long term drift Offset current I_0		0.03		mA
I_{0T}	Offset current temperature drift I_0 @ T_A = -40 ...+85°C		0.03		mA
I_{0H}	Hyteresis current @ I_P=0 (caused by primary current 3 x I_{PN})		0.02	0.05	mA
$\Delta I_0/\Delta V_C$	Supply voltage rejection ratio			0.01	mA/V
i_{oss}	Offset ripple* (with1 MHz- filter first order)			0.15	mA
i_{oss}	Offset ripple* (with 100 kHz- filter first order)		0.017	0.025	mA
i_{oss}	Offset ripple* (with 20 kHz- filter first order)		0.005	0.007	mA
C_k	Maximum possible coupling capacity (primary – secondary)		5		pF
	Mechanical Stress according to M3209/3 Settings: 10 – 2000 Hz, 1 min/Decade, 2 hours An exceptionally high rate of on/off – switching of the supply voltage accelerates the aging process of the sensor.			10g	

Inspection[1)] (Measurement after temperature balance of the samples at room temperature)

$K_N(N_1/N_2)$	(V)	M3011/6	Transformation ratio (I_P=3*10A, 40-80 Hz)	1…3 : 2000 ± 0.5	%
I_0	(V)	M3226	Offset current	< 0.05	mA
$V_{P,eff}$	(V)	M3014	Test voltage, rms, 1s Pin 1 - 6 to Pin 7 - 9	2.5	kV
V_e	(AQL 1/S4)		Partial discharge voltage acc. M3024 (RMS) with V_{vor} (RMS)	1500 1875	V V

Type Testing (Pin 1 - 6 to Pin 7 – 9)

Designed according standard EN 61800 with insulation material group 1

V_W	HV transient test according (to M3064) (1,2 µs / 50 µs-wave form)		8	kV
V_d	Testing voltage acc. M3014 (RMS)	(5 s)	5	kV
V_e	Partial discharge voltage acc. M3024 (RMS) with V_{vor} (RMS)		1500 1875	V V

Datum	Name	Index	Änderung
28.01.08	Le	81	Page 3: write error in X_{ges} (I_{PN}). changed. Insignificant

Hrsg.: KB-E editor	Bearb: SA designer		KB-E BE: Len. check	KB-PM IA:KRe. check		freig.: Heu. released

Weitergabe sowie Vervielfältigung dieser Unterlage, Verwertung und Mitteilung ihres Inhalts nicht gestattet, soweit nicht ausdrücklich zugestanden. Zuwiderhandlungen verpflichten zu Schadenersatz. Alle Rechte für den Fall der Patenterteilung oder GM-Eintragung vorbehalten

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden. Any offenders are liable to pay all relevant damages.

K-No.: 24618	**50/100 A Current Sensor** For electronic current measurement: DC, AC, pulsed, mixed ..., with a galvanic isolation between primary circuit (high power) and secondary circuit		Date: 28.01.2008
Customer:	Customers Part No.:	Page 2 of 3

Limit curve of measurable current $\hat{I}_P(R_M)$ [1)]

@ ambient temperature $T_A \leq 85$ °C



Maximum measuring range (µs-range) [1)]

Output current behaviour of a 3kA current pulse
@ V_C = ±15V und R_M= 25Ω



Fast increasing currents (higher than the specified $I_{p,max}$), e.g. in case of a short circuit, can be transmitted because the currents are transformed directly.

The offset ripple can be reduced by an external low pass. Simplest solution is a passive low pass filter of 1st order with

$$f_g = \frac{1}{2p \cdot R_M \cdot C_a}$$

In this case the response time is enlarged.
It is calculated from:

$$t_r' \leq t_r + 2{,}5 R_M C_a$$

Applicable documents

Current direction: A positive output current appears at point I_S, by primary current in direction of the arrow.
Constructed and manufactored and tested in accordance with EN 61800.
Housing and bobbin material UL-listed: Flammability class 94V-0.

Weitergabe sowie Vervielfältigung dieser Unterlage, Verwertung und Mitteilung ihres Inhalts nicht gestattet, soweit nicht ausdrücklich zugestanden. Zuwiderhandlungen verpflichten zu Schadenersatz. Alle Rechte für den Fall der Patenterteilung oder GM-Eintragung vorbehalten

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden.
Any offenders are liable to pay all relevant damages.



I_{0H}: Zero variation of I_o after overloading with a DC of tenfold the rated value ($R_M = R_{MN}$)

I_{0t}: Long term drift of I_o after 100 temperature cycles in the range -40 bis 85 °C.

t_r: Response time (describe the dynamic performance for the specified measurement range), measured as delay time at $I_P = 0{,}9 \cdot I_{Pmax}$ between a rectangular current and the output current.

Δt (I_{Pmax}): Delay time (describe the dynamic performance for the rapid current pulse rate e.g short circuit current) measured between I_{Pmax} and the output current i_a with a primary current rise of di_1/dt = 100 A/µs.

$X_{ges}(I_{PN})$: The sum of all possible errors over the temperature range by measuring a current I_{PN}:

$$X_{ges} = 100 \cdot \left| \frac{I_S(I_{PN})}{K_N \cdot I_{PN}} - 1 \right| \%$$

X: Permissible measurement error in the final inspection at RT, defined by

$$X = 100 \cdot \left| \frac{I_{SB}}{I_{SN}} - 1 \right| \%$$

where I_{SB} is the output DC value of an input DC current of the same magnitude as the (positive) rated current ($I_o = 0$)

X_{Ti}: Temperature drift of the rated value orientated output term. I_{SN} (cf. Notes on F_i) in a specified temperature range, obtained by:

$$X_{Ti} = 100 \cdot \left| \frac{I_{SB}(T_{A2}) - I_{SB}(T_{A1})}{I_{SN}} \right| \%$$

ε_L: Linearity fault defined by $e_L = 100 \cdot \left| \frac{I_P}{I_{PN}} - \frac{I_{Sx}}{I_{SN}} \right| \%$

Where I_P is any input DC and I_{Sx} the corresponding output term. I_{SN}: see notes of F_i ($I_o = 0$).

This “Additional information“ is no declaration of warranty according BGB $443.

Weitergabe sowie Vervielfältigung dieser Unterlage, Verwertung und Mitteilung ihres Inhalts nicht gestattet, soweit nicht ausdrücklich zugestanden. Zuwiderhandlungen verpflichten zu Schadenersatz. Alle Rechte für den Fall der Patenterteilung oder GM-Eintragung vorbehalten

Copying of this document, disclosing it to third parties or using the contents there for any purposes without express written authorization by use illegally forbidden. Any offenders are liable to pay all relevant damages.

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения **«JONHON»**, а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов **«FORSTAR»**.

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А