FEATURES

- **Tight Initial Output Voltage: <0.05%**
- **Ultralow Drift: 3ppm/°C Typical**
- **Series or Shunt Operation**
- Curvature Corrected
- Ultrahigh Line Rejection: ≈0.5ppm/V
- Low Output Impedance: ≈0.02Ω
- Plug-In Replacement for Present References
- Available at 2.5V, 4.5V, 5V, and 10V
- 100% Noise Tested
- Temperature Output
- Industrial Temperature Range in SO-8
- Available in 8-Lead N8 and S8 Packages

APPLICATIONS

- Negative Shunt References
- A/D and D/A Converters
- Precision Regulators
- Constant Current Sources
- V/F Converters
- Bridge Excitation

DESCRIPTION

The LT®1019 is a third generation bandgap voltage reference utilizing thin film technology and a greatly improved curvature correction technique. Wafer level trimming of both reference and output voltage combines to produce very low TC and tight initial output voltage tolerance.


The LT1019 can both sink and source up to 10mA and can be used in either the series or shunt mode, allowing the reference to operate with positive or negative output voltages without external components. Minimum input/output voltage is less than 1V in the series mode, providing improved tolerance of low line conditions and excellent line regulation.

The LT1019 is available in four voltages: 2.5V, 4.5V, 5V and 10V. It is a direct replacement for most bandgap references presently available including AD580, AD581, REF-01, REF-02, MC1400, MC1404 and LM168.

LT, LTC and LT are registered trademarks of Linear Technology Corporation.
All other trademarks are the property of their respective owners.

TYPICAL APPLICATION

Ultralinear Strain Gauge




*REDUCES REFERENCE AND AMPLIFIER LOADING TO ≈0.

**IF R6 = R3, BRIDGE IS NOT LOADED BY R2 AND R4.

†A1 V_{OS} AND DRIFT ARE NOT CRITICAL BECAUSE A2 ACTS AS A DIFFERENTIAL AMPLIFIER.

Output Voltage Drift




ABSOLUTE MAXIMUM RATINGS (Note 1)

Input Voltage 40V
Output Voltage (Note 2)
  LT1019-5, LT1019-10 ..... 16V
  LT1019-2.5, LT1019-4.5 ..... 7V
Output Short-Circuit Duration (Note 2)
  V_{IN} < 20V ..... Indefinite
  20V ≤ V_{IN} ≤ 35V ..... 10 sec

Specified Temperature Range
  Commercial ..... 0°C to 70°C
  Industrial ..... –40°C to 85°C
  Military ..... –55°C to 125°C
Trim Pin Voltage ..... ±30V
Temp Pin Voltage 5V
Storage Temperature Range (Note 11) –65°C to 150°C
Lead Temperature (Soldering, 10 sec) ..... 300°C


PACKAGE/ORDER INFORMATION



H PACKAGE
8-LEAD TO-5 METAL CAN

*INTERNALLY CONNECTED. DO NOT CONNECT EXTERNALLY


T_{JMAX} = 150°C, θ_{JA} = 150°C/W, θ_{JC} = 45°C/W



N8 PACKAGE
8-LEAD PDIP

*INTERNALLY CONNECTED. DO NOT CONNECT EXTERNALLY.

T_{JMAX} = 100°C, θ_{JA} = 130°C/W



S8 PACKAGE
8-LEAD PLASTIC SO

*INTERNALLY CONNECTED. DO NOT CONNECT EXTERNALLY.

T_{JMAX} = 100°C, θ_{JA} = 130°C/W

ORDER PART NUMBER	ORDER PART NUMBER	ORDER PART NUMBER	S8 PART MARKING
LT1019ACH-2.5	LT1019ACN8-2.5	LT1019ACS8-2.5	019A25
LT1019ACH-4.5	LT1019ACN8-4.5	LT1019ACS8-5	1019A5
LT1019ACH-5	LT1019ACN8-5	LT1019AIS8-2.5	19AI25
LT1019ACH-10	LT1019ACN8-10	LT1019AIS8-5	019AI5
LT1019AMH-2.5	LT1019CN8-2.5	LT1019CS8-2.5	1925
LT1019AMH-4.5	LT1019CN8-4.5	LT1019CS8-4.5	1945
LT1019AMH-5	LT1019CN8-5	LT1019CS8-5	1905
LT1019AMH-10	LT1019CN8-10	LT1019CS8-10	1910
LT1019CH-2.5	LT1019IN8-2.5	LT1019IS8-2.5	19I25
LT1019CH-4.5	LT1019IN8-4.5	LT1019IS8-5	19I05
LT1019CH-5	LT1019IN8-5		
LT1019CH-10	LT1019IN8-10		
LT1019MH-2.5			
LT1019MH-4.5			
LT1019MH-5			
LT1019MH-10			

OBSOLETE

CONSIDER THE N8 OR S8 FOR ALTERNATE SOURCES.

AVAILABLE OPTIONS

OUTPUT VOLTAGE (V)	TEMPERATURE (°C)	ACCURACY (%)	TEMPERATURE COEFFICIENT (ppm/°C)	PACKAGE TYPE		
				TO-5 H8	SO-8 S8	PDIP-8 N8
2.5	0 to 70	0.05 0.2	5 20	LT1019ACH-2.5 LT1019CH-2.5	LT1019ACS8-2.5 LT1019CS8-2.5	LT1019ACN8-2.5 LT1019CN8-2.5
	–40 to 85	0.05 0.2	10 20		LT1019AIS8-2.5 LT1019IS8-2.5	 LT1019IN8-2.5
	–55 to 125	0.05 0.2	10 25	LT1019AMH-2.5 LT1019MH-2.5		
4.5	0 to 70	0.05 0.2	5 20	LT1019ACH-4.5 LT1019CH-4.5	 LT1019CS8-4.5	LT1019ACN8-4.5 LT1019CN8-4.5
	–40 to 85	0.2	20			LT1019IN8-4.5
	–55 to 125	0.05 0.2	10 25	LT1019AMH-4.5 LT1019MH-4.5		
5	0 to 70	0.05 0.2	5 20	LT1019ACH-5 LT1019CH-5	LT1019ACS8-5 LT1019CS8-5	LT1019ACN8-5 LT1019CN8-5
	–40 to 85	0.05 0.2	10 20		LT1019AIS8-5 LT1019IS8-5	 LT1019IN8-5
	–55 to 125	0.05 0.2	10 25	LT1019AMH-5 LT1019MH-5		
10	0 to 70	0.05 0.2	5 20	LT1019ACH-10 LT1019CH-10	 LT1019CS8-10	LT1019ACN8-10 LT1019CN8-10
	–40 to 85	0.2	20			LT1019IN8-10
	–55 to 125	0.05 0.2	10 25	LT1019AMH-10 LT1019MH-10		

ELECTRICAL CHARACTERISTICS

The ● denotes specifications which apply over the full operating temperature range, otherwise specifications are T_A = 25°C. V_{IN} = 15V, I_{OUT} = 0 unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS		LT1019A MIN	LT1019A TYP	LT1019A MAX	LT1019 MIN	LT1019 TYP	LT1019 MAX	UNITS
	Output Voltage Tolerance				0.02	0.05		0.02	0.2	%
TC	Output Voltage Temperature Coefficient (Note 3)	LT1019C (0°C to 70°C)	●		3	5		5	20	ppm/°C
		LT1019I (–40°C to 85°C)	●		3	10		5	20	ppm/°C
		LT1019M (–55°C to 125°C)	●		5	10		8	25	ppm/°C
$\frac{\Delta V_{OUT}}{\Delta V_{IN}}$	Line Regulation (Note 4)	$(V_{OUT} + 1.5V) \le V_{IN} \le 40V$			0.5	3		0.5	3	ppm/V
			●		1.0	5		1.0	5	ppm/V
RR	Ripple Rejection	50Hz ≤ f ≤ 400Hz		90	110		90	110		dB
			●	84			84			dB

ELECTRICAL CHARACTERISTICS

The ● denotes specifications which apply over the full operating temperature range, otherwise specifications are T_A = 25°C. V_{IN} = 15V, I_{OUT} = 0 unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS		LTC1019A MIN	LTC1019A TYP	LTC1019A MAX	LTC1019 MIN	LTC1019 TYP	LTC1019 MAX	UNITS
$\frac{\Delta V_{OUT}}{\Delta I_{OUT}}$	Load Regulation Series Mode (Notes 4, 5)	0 ≤ I_{OUT} ≤ 10mA (Note 5)			0.02	0.05		0.02	0.05	mV/mA (Ω)
			●			0.08			0.08	mV/mA (Ω)
	Load Regulation, Shunt Mode	1mA ≤ I_{SHUNT} ≤ 10mA (Notes 5, 6)								
		2.5V, 4.5V, 5V	●		0.1	0.4		0.1	0.4	mV/mA (Ω)
		10V	●			0.8			0.8	mV/mA (Ω)
	Thermal Regulation (Note 7)	ΔP = 200mW, t = 50ms			0.1	0.5		0.1	0.5	ppm/mW
I_Q	Quiescent Current				0.65	1.0		0.65	1.2	mA
	Series Mode		●			1.3			1.5	mA
	Minimum Shunt Current	(Note 8)	●		0.5	0.8		0.5	0.8	mA
	Minimum Input/Output Voltage Differential	I_{OUT} ≤ 1mA	●		0.9	1.1		0.9	1.1	V
		I_{OUT} = 10mA	●			1.3			1.3	V
	Trim Range	LT1019-2.5		±3.5	±6		±3.5	±6		%
		LT1019-5		±3.5	5, –13		±3.5	5, –13		%
		LT1019-10		±3.5	5, –27		±3.5	5, –27		%
I_{SC}	Short-Circuit Current	2V ≤ V_{IN} ≤ 35V		15	25	50	15	25	50	mA
	Output Connected to GND		●	10			10			mA
e_n	Output Voltage Noise (Note 10)	10Hz ≤ f ≤ 1kHz			2.5	4		2.5	4	ppm (RMS)
		0.1Hz ≤ f ≤ 10Hz			2.5			2.5		ppm (P-P)

Note 1: Absolute Maximum Ratings are those values beyond which the life of a device may be impaired.

Note 2: These are high power conditions and are therefore guaranteed only at temperatures equal to or below 70°C. Input is either floating, tied to output or held higher than output.

Note 3: Output voltage drift is measured using the box method. Output voltage is recorded at T_{MIN}, 25°C and T_{MAX}. The lowest of these three readings is subtracted from the highest and the resultant difference is divided by ($T_{MAX} – T_{MIN}$).

Note 4: Line regulation and load regulation are measured on a pulse basis with low duty cycle. Effects due to die heating must be taken into account separately. See thermal regulation and application section.

Note 5: Load regulation is measured at a point 1/8" below the base of the package with Kelvin contacts.

Note 6: Shunt regulation is measured with the input floating. This parameter is also guaranteed with the input connected ($V_{IN} – V_{OUT}$) > 1V, 0mA ≤ I_{SINK} ≤ 10mA. Shunt and sink current flow into the output.

Note 7: Thermal regulation is caused by die temperature gradients created by load current or input voltage changes. This effect must be added to normal line or load regulation.

Note 8: Minimum shunt current is measured with shunt voltage held 20mV below the value measured at 1mA shunt current.


Note 9: Minimum input/output voltage is measured by holding input voltage 0.5V above the nominal output voltage, while measuring $V_{IN} – V_{OUT}$.

Note 10: RMS noise is measured with a single pole highpass filter at 10Hz and a 2-pole lowpass filter at 1kHz. The resulting output is full-wave rectified and then integrated for a fixed period, making the final reading an average as opposed to RMS. A correction factor of 1.1 is used to convert from average to RMS, and a second correction of 0.88 is used to correct the nonideal bandpass of the filters.

Note 11: If the part is stored outside of the specified temperature range, the output may shift due to hysteresis.


TYPICAL PERFORMANCE CHARACTERISTICS

Quiescent Current (LT1019-2.5)




LT1019 • TPC01

Quiescent Current (LT1019-4.5/LT1019-5)




LT1019 • TPC02

Quiescent Current (LT1019-10)




LT1019 • TPC03

Minimum Input/Output Voltage Differential




LT1019 • TPC04

Load Regulation




LT1019 • TPC05

Ripple Rejection




LT1019 • TPC06

Shunt Mode Characteristics (LT1019-2.5)




LT1019 • TPC07

Shunt Mode Characteristics (LT1019-5)



LT1019 • TPC08


Shunt Mode Characteristics (LT1019-10)




LT1019 • TPC09

TYPICAL PERFORMANCE CHARACTERISTICS


Temp Pin Voltage



Line Regulation




LT1019-2.5* Stability with Output Capacitance



* LT1019-4.5/LT1019-5/LT1019-10 ARE STABLE WITH ALL LOAD CAPACITANCE.

BLOCK DIAGRAM



APPLICATIONS INFORMATION

Line and Load Regulation

Line regulation on the LT1019 is nearly perfect. A 10V change in input voltage causes a typical output shift of less than 5ppm. Load regulation (sourcing current) is nearly as good. A 5mA change in load current shifts output voltage by only 100µV. These are *electrical* effects, measured with low duty cycle pulses to eliminate heating effects. In real world applications, the *thermal* effects of load and line changes must be considered.

Two separate thermal effects are evident in monolithic circuits. One is a gradient effect, where power dissipation on the die creates temperature gradients. These gradients can cause output voltage shifts *even if the overall temperature coefficient of the reference is zero*. The LT1019, unlike previous references, specifies thermal regulation caused by die temperature gradients.The specification is 0.5ppm/mW. To calculate the effect on output voltage, simply multiply the *change* in device power dissipation by

APPLICATIONS INFORMATION

the thermal regulation specification. Example: a 10V device with a nominal input voltage of 15V and load current of 5mA. Find the effect of an input voltage change of 1V and a load current change of 2mA.

$$\Delta P \text{ (line change)} = (\Delta V_{IN})(I_{LOAD}) = (1V)(5mA) = 5mW$$
$$\Delta V_{OUT} = (0.5ppm/mW)(5mW) = 2.5ppm$$

$$\Delta P \text{ (load change)} = (\Delta I_{LOAD})(V_{IN} - V_{OUT})$$
$$= (2mA)(5V) = 10mW$$
$$\Delta V_{OUT} = (0.5ppm/mW)(10mW) = 5ppm$$

Even though these effects are small, they should be taken into account in critical applications, especially where input voltage or load current is high.

The second thermal effect is overall die temperature change. The magnitude of this change is the product of change in power dissipation times the thermal resistance (θ_{JA}) of the IC package ≅ (100°C/W to 150°C/W). The effect on the reference output is calculated by multiplying die temperature change by the temperature drift specification of the reference. Example: same conditions as above with θ_{JA} = 150°C/W and an LT1019 with 20ppm/°C drift specification.

$$\Delta P \text{ (line change)} = 5mW$$
$$\Delta V_{OUT} = (5mW)(150°C/W)(20ppm/°C)$$
$$= 15ppm$$

$$\Delta P \text{ (load change)} = 10mW$$
$$\Delta V_{OUT} = (10mW)(150°C/W)(20ppm/°C)$$
$$= 30ppm$$

These calculations show that thermally induced output voltage variations can easily exceed the electrical effects. In critical applications where shifts in power dissipation are expected, a small clip-on heat sink can significantly improve these effects by reducing overall die temperature change. Alternately, an LT1019A can be used with four times lower TC. If warm-up drift is of concern, these measures will also help. With warm-up drift, *total* device power dissipation must be considered. In the example given, warm-up drift (worst case) is equal to:

$$\text{Warm-up drift} = [(V_{IN})(I_Q) + (V_{IN} - V_{OUT})(I_{LOAD})]$$
$$[(\theta_{JA})(TC)]$$

with I_Q (quiescent current) = 0.6mA,

$$\text{Warm-up drift} = [(15V)(0.6mA) + (5V)(5mA)]$$
$$[(150°C/W)(25ppm/°C)]$$
$$= 127.5ppm$$

Note that 74% of the warm-up drift is due to load current times input/output differential. This emphasizes the importance of keeping both these numbers low in critical applications.

Note that line regulation is now affected by reference output impedance. R1 should have a wattage rating high enough to withstand full input voltage if output shorts must be tolerated. Even with load currents below 10mA, R1 can be used to reduce power dissipation in the LT1019 for lower warm-up drift, etc.

Output Trimming

Output voltage trimming on the LT1019 is nominally accomplished with a potentiometer connected from output to ground with the wiper tied to the trim pin. The LT1019 was made compatible with existing references, so the trim range is large: +6%, –6% for the LT1019-2.5, +5%, –13% for the LT1019-5, and +5%, –27% for the LT1019-10. This large trim range makes precision trimming rather difficult. One solution is to insert resistors in series with both ends of the potentiometer. This has the disadvantage of potentially poor tracking between the fixed resistors and the potentiometer. A second method of reducing trim range is to insert a resistor in series with the wiper of the potentiometer. This works well only for very small trim range because of the mismatch in TCs between the series resistor and the internal thin film resistors. These film resistors can have a TC as high as 500ppm/°C. That same TC is then transferred to the change in output voltage: a 1% shift in output voltage causes a (500ppm)(1%) = 5ppm/°C change in output voltage drift.

APPLICATIONS INFORMATION

The worst-case error in initial output voltage for the LT1019 is 0.2%, so a series resistor is satisfactory if the output is simply trimmed to nominal value. The maximum TC shift expected would be 1ppm/°C.

Using the Temp Pin

The LT1019 has a TEMP pin like several other bandgap references. The voltage on this pin is directly proportional to absolute temperature (PTAT) with a slope of approximately 2.1mV/°C. Room temperature voltage is therefore approximately (295°K)(2.1mV/°C) = 620mV. This voltage varies with process parameters and should not be used to measure absolute temperature, but rather relative temperature changes. Previous bandgap references have been very sensitive to any loading on the TEMP pin because it is an integral part of the reference "core" itself. The LT1019 "taps" the core at a special point which has much less effect on the reference. The relationship between TEMP pin loading and a change in reference output voltage is less than 0.05%/μA, about ten times improvement over previous references.

Output Bypassing

The LT1019 is designed to be stable with a wide range of load currents and output capacitors. The 4.5V, 5V, and 10V devices do not oscillate under any combination of capacitance and load. The 2.5V device can oscillate when sinking currents between 1mA and 6mA for load capacitance between 400pF and 2μF (see Figure 1).

If output bypassing is desired to reduce high frequency output impedance, keep in mind that loop phase margin is significantly reduced for output capacitors between 500pF and 1μF if the capacitor has low ESR (Effective Series Resistance). This can make the output "ring" with transient loads. The best transient load response is obtained by deliberately adding a resistor to increase ESR as shown in Figure 1.





Figure 1. Output Bypassing


Use configuration (a) if DC voltage error cannot be compromised as load current changes. Use (b) if absolute minimum peak perturbation at the load is needed. For best transient response, the output can be loaded with ≥1mA DC current.

TYPICAL APPLICATIONS

Wide Range Trim ≥ ±5%



Narrow Trim Range (±0.2%)




*INCREASE TO 4.7M FOR LT1019A (±0.05%)


1019 TA05

TYPICAL APPLICATIONS


Trimming LT1019-5 Output to 5.120V




Trimming LT1019-10 Output to 10.240V




Precision 1μA Current Source




Negative Series Reference



Output Current Boost with Current Limit




SCHEMATIC DIAGRAM



PACKAGE DESCRIPTION

H Package
8-Lead TO-5 Metal Can (0.200 PCD)
(LTC DWG # 05-08-1320)




*LEAD DIAMETER IS UNCONTROLLED BETWEEN THE REFERENCE PLANE AND 0.045" BELOW THE REFERENCE PLANE

**FOR SOLDER DIP LEAD FINISH, LEAD DIAMETER IS 0.016 – 0.024 (0.406 – 0.610)

H8(TO-5) 0.200 PCD 1197


OBSOLETE

N8 Package
8-Lead PDIP (Narrow 0.300)
(LTC DWG # 05-08-1510)



*THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED 0.010 INCH (0.254mm)

S8 Package
8-Lead Plastic Small Outline (Narrow 0.150)
(LTC DWG # 05-08-1610)




NOTE:
1. DIMENSIONS IN INCHES (MILLIMETERS)
2. DRAWING NOT TO SCALE
3. THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED .006" (0.15mm)

LINEAR TECHNOLOGY

Information furnished by Linear Technology Corporation is believed to be accurate and reliable. However, no responsibility is assumed for its use. Linear Technology Corporation makes no representation that the interconnection of its circuits as described herein will not infringe on existing patent rights.

TYPICAL APPLICATION

Negative 10V Reference for CMOS DAC



RELATED PARTS

PART NUMBER	DESCRIPTION	COMMENTS
LT1027	Precision 5V Reference	Lowest TC, High Accuracy, Low Noise, Zener Based
LT1236	Precision Reference	5V and 10V Zener Based, 5ppm/°C, SO-8 Package
LT1460	Micropower Precision Series Reference	Bandgap, 130μA Supply Current, 10ppm/°C, Available in SOT-23 Package
LT1634	Micropower Precision Shunt Reference	Bandgap 0.05%, 10ppm/°C, 10μA Supply Current
LTC1798	Micropower Low Dropout Reference	0.15% Max, 6.5μA Supply Current
LT1461	Micropower Low Dropout Reference	3ppm/°C, 0.04%, 50μA Supply Current

Linear Technology Corporation
1630 McCarthy Blvd., Milpitas, CA 95035-7417
(408) 432-1900 • FAX: (408) 434-0507 • www.linear.com

LT/TP 0205 1K REV D • PRINTED IN USA

© LINEAR TECHNOLOGY CORPORATION 1993

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А