FUJITSU SEMICONDUCTOR
DATA SHEET

DS04-28222-1E

ASSP For Video Applications

CMOS

3 ch 8-bit 162 MSPS A/D Converter

MB40C338

■ DESCRIPTION


MB40C338 is a high-speed 3ch A/D converter using a fast CMOS technology.

■ FEATURES

- Resolution : 8 bit
- No. of AD channels : 3 ch
- Linearity error : ±0.40 % (typical)
- Maximum conversion rate : 162 MSPS (minimum)
- Power supply voltage : 3.3 V (typical : internal circuit)
- Digital input voltage range : TTL level
- Digital output voltage range : 3.3 V CMOS level
- Amp. input voltage range : 0.7 V_{P-P} (typical)
- Amp. gain : 1.9 double fixed
- Power dissipation : 1100 mW (typical)
- Additional features : PLL circuit
  Video amp. circuit (1.9 double fixed gain)
  CLAMP circuit
  V_{RT} AMP circuit (RGB 3 ch common)
  V_{RB} AMP circuit (RGB 3 ch common)
  Overflow output
  High impedance output, power down function
- Package : LQFP120 (16 mm × 16mm, lead pitch : 0.5 mm)

■ PACKAGE


120-pin plastic LQFP



(FPT-120P-M21)

■ PIN ASSIGNMENT

(TOP VIEW)



(FPT-120P-M21)

■ PIN DESCRIPTION

Pin No.	Symbol	Description
9, 23, 47, 79, 107	AV_{DD}	Analog power supply (+3.3 V)
28, 38, 50, 59, 70, 82, 93, 106	DV_{DD}	Digital power supply (+3.3 V)
116, 119	PV_{DD}	PLL Power supply pin (+3.3 V)
14	V_{ESD}	Digital input power supply for protect device (+3.3 V or +5 V)
10, 12, 22, 48, 80, 91, 108	AV_{SS}	Analog power supply ground pin (0 V)
27, 37, 49, 60, 69, 81, 92, 105	DV_{SS}	Digital power supply ground pin (0 V)
114, 120	PV_{SS}	PLL Power supply ground pin (0 V)
1 3 5	RV_{IN} GV_{IN} BV_{IN}	1.9 double amp. input pin
11 13 15	RADIN GADIN BADIN	A/D converter input pin Please set these pins to open usually.
19 20 21	RV_{CLP} GV_{CLP} BV_{CLP}	Clamp voltage setting input pin
110	V_{RTM}	Reference voltage output pin on top side
111	V_{RT}	Reference voltage input pin on top side
112	V_{REFT}	Reference voltage generator output pin on top side
16	V_{RBM}	Reference voltage output pin on bottom side
17	V_{RB}	Reference voltage input pin on bottom side
18	V_{REFB}	Reference voltage generator output pin on bottom side
6 2 109	V_{R1} V_{R2} V_{R3}	Reference 1/4 voltage output pin (Add 0.1 µF for AV_{SS}) Reference 1/2 voltage output pin (Add 0.1 µF for AV_{SS}) Reference 3/4 voltage output pin (Add 0.1 µF for AV_{SS})
25	CK	Serial data transfer clock input pin
26	DATA	Serial data input pin
24	$\overline{CS}$	Chip select signal input pin It is possible to input to the shift register at $\overline{CS}$ falling The content of the shift register is executed at $\overline{CS}$ rising.
98	EXCLK	Clock input pin for A/D converter (CMOS level) Fix to “L” level when unused.

Note: The values in parentheses are standard.


(Continued)

(Continued)

Parameter	Symbol	Description	
99	EXPCLKB	Differential clock (negative-phase) input pin for A/D converter Fix to “H” level when unused.	PECL level
100	EXPCLK	Differential clock (positive-phase) input pin for A/D converter Fix to “L” level when unused.	
8	PCLP	Clamp pulse input pin	
4	$\overline{CE}$	Power down at $\overline{CE}$ input “H” (internal pull-up resistor)	
113	R_{REF}	Internal current setting pin (Add 12 kΩ for AV_{SS})	
103	DSYNC	Delay sync signal output pin	
102	DSYNCB	Inverted delay sync signal output pin	
95	CLK	Clock output pin (See “■ TIMING DIAGRAM”.)	
94	CLKB		
97	ADCLKA		
96	ADCLKB		
83 to 90 61 to 68 39 to 46	RD_{A7} to RD_{A0} GD_{A7} to GD_{A0} BD_{A7} to BD_{A0}	Digital output pin (Port A) RD_{A7}, GD_{A7}, BD_{A7} : MSB RD_{A0}, GD_{A0}, BD_{A0} : LSB	
71 to 78 51 to 58 29 to 36	RD_{B7} to RD_{B0} GD_{B7} to GD_{B0} BD_{B7} to BD_{B0}	Digital output pin (Port B) RD_{B7}, GD_{B7}, BD_{B7} : MSB RD_{B0}, GD_{B0}, BD_{B0} : LSB	
101	COUT	PLL counter output pin	
115	LPF	External capacitor/resistor connection pin	
117	HHOLD	Phase detector operation is hold by input “H” level	
118	HSYNC	Horizontal sync signal input pin	
7	V_{REF}	Internal voltage output pin (Add 3.3µF for AV_{SS})	
104	OF	Overflow output pin (“H” level output at overflow)	

Note: The values in parentheses are standard.

■ BLOCK DIAGRAM



■ ABSOLUTE MAXIMUM RATINGS

Parameter	Symbol	Rating		Unit
		Min.	Max.	
Power supply voltage	AV_{DD}, DV_{DD}, PV_{DD}	–0.3	+4.0	V
	V_{ESD}	–0.3	+7.0	V
Input/output voltage	RV_{IN}, GV_{IN}, BV_{IN}, RADIN, GADIN, BADIN, RV_{CLP}, GV_{CLP}, BV_{CLP}, V_{RT}, V_{RTM}, V_{REFT}, V_{RB}, V_{RBM}, V_{REFB}, V_{R1}, V_{R2}, V_{R3} V_{REF}, R_{REF}	–0.3	AV_{DD}+0.3*1	V
	RD_{A0} to RD_{A7}, RD_{B0} to RD_{B7}, GD_{A0} to GD_{A7}, GD_{B0} to GD_{B7}, BD_{A0} to BD_{A7}, BD_{B0} to BD_{B7}, DSYNC, DSYNCB, OF, COUT, CLK, CLKB, ADCLKA, ADCLKB	–0.3	DV_{DD}+0.3*1	V
	LPF	–0.3	PV_{DD}+0.3*1	V
	CK, DATA, $\overline{CS}$, EXPCLKB, EXPCLK, PCLP, $\overline{CE}$, EXCLK, HHOLD, HSYNC	–0.3	V_{ESD}+0.3*2	V
Storage temperature	T_{STG}	–55	+125	°C

*1 : Do not exceed +4.0 V.

*2 : Do not exceed +7.0 V.

WARNING: Semiconductor devices can be permanently damaged by application of stress (voltage, current, temperature, etc.) in excess of absolute maximum ratings. Do not exceed these ratings.

■ RECOMMENDED OPERATING CONDITIONS

Parameter	Symbol	Rating			Unit
		Min.	Typ.	Max.	
Power supply voltage	AV_{DD}, DV_{DD}	3.00	3.30	3.60	V
	PV_{DD}	3.00	3.30	3.60	V
	V_{ESD}	3.00	—	5.25	V
A/D converter input voltage	V_{ADIN}	V_{RB}	—	V_{RT}	V
Analog reference voltage: T	V_{RT}	—	2.2	AV_{DD} – 0.6	V
Analog reference voltage: B	V_{RB}	0.6	0.7	—	V
Analog reference voltage range	$V_{RT} – V_{RB}$	1.0	1.5	1.8	V
Video AMP input voltage	$V_{IN\ (P\text{-}P)}$	0.5	—	0.9	$V_{P\text{-}P}$
Clamp input voltage	V_{CLP}	0.6	V_{RB}	1.7	V
Digital “H” level input voltage	V_{IHD}	2.5	—	V_{ESD}	V
Digital “L” level input voltage	V_{ILD}	0	—	0.5	V
Digital “H” level output current	I_{OHD}	–400	—	—	µA
Digital “L” level output current	I_{OLD}	—	—	1.6	mA
PLL counter	P_C	100	—	4095	—
HSYNC input frequency range	f_{HSYNC}	10	—	100	kHz
HHOLD set up time	t_{sHHOLD}	20	—	—	ns
HHOLD hold time	t_{hHHOLD}	20	—	—	ns
Clamp pulse width	t_{WCLP}	0.5	—	—	µs
CK clock pulse width	t_{WCKL}, t_{WCKH}	100	—	—	ns
DATA set up time	t_{sDATA}	30	—	—	ns
DATA hold time	t_{hDATA}	30	—	—	ns
$\overline{CS}$ set up time	t_{sCS}	50	—	—	ns
$\overline{CS}$ hold time	t_{hCS}	50	—	—	ns
$\overline{CS}$ “H” level hold time	t_{WCSH}	100	—	—	ns
Operating temperature range	Ta	–20	—	70	°C

WARNING: The recommended operating conditions are required in order to ensure the normal operation of the semiconductor device. All of the device’s electrical characteristics are warranted when the device is operated within these ranges.

Always use semiconductor devices within their recommended operating condition ranges. Operation outside these ranges may adversely affect reliability and could result in device failure.

No warranty is made with respect to uses, operating conditions, or combinations not represented on the data sheet. Users considering application outside the listed conditions are advised to contact their FUJITSU representatives beforehand.

■ ELECTRICAL CHARACTERISTICS

1. DC Characteristics in Analog Section

• Power supply current (AV_{DD} = DV_{DD} = PV_{DD} = 3.0 V to 3.6 V, V_{ESD} = 3.0 V to 5.25 V, Ta = –20 °C to +70 °C)

Parameter	Symbol	Value			Unit
		Min.	Typ.	Max.	
Analog power supply current	AI_{DD}	—	220	310	mA
Digital power supply current	DI_{DD}	—	100	110	mA
Power supply current PLL section (@ f_{VCOH} = 162 MHz, Icp = 0.5 mA, DIV = 1/1)	PI_{DD}	—	16	20	mA
Standby current	I_{SB}	—	10	—	mA

• A/D Block (AV_{DD} = DV_{DD} = PV_{DD} = 3.0 V to 3.6 V, V_{ESD} = 3.0 V to 5.25 V, Ta = –20 °C to +70 °C)

Parameter	Symbol	Value			Unit
		Min.	Typ.	Max.	
Resolution	—	—	8	—	bit
Linearity error (DC Accuracy)	LE	–0.8	±0.4	+0.8	%
Differential linearity error (DC Accuracy)	DLE	–0.36	±0.2	+0.65	%
Reference voltage : T	V_{REFT}	0.63 × AV_{DD}	0.67 × AV_{DD}	0.70 × AV_{DD}	V
Reference voltage : B	V_{REFB}	0.18 × AV_{DD}	0.21 × AV_{DD}	0.24 × AV_{DD}	V
Analog reference voltage input current	I_{RT}, I_{RB}	—	5	20	µA

• Video AMP Block (AV_{DD} = DV_{DD} = PV_{DD} = 3.0 V to 3.6 V, V_{ESD} = 3.0 V to 5.25 V, Ta = –20 °C to +70 °C)

Parameter	Symbol	Value			Unit
		Min.	Typ.	Max.	
Video AMP gain	G_{AMP}	1.8	1.9	2.0	—
Video AMP output voltage range	V_{AMPOUT}	0.5	—	AV_{DD} – 0.6	V
Video AMP frequency width	BW	—	250	—	MHz
Video AMP input capacity	C_{VIN}	—	5	—	pF

• CLAMP Block (AV_{DD} = DV_{DD} = PV_{DD} = 3.0 V to 3.6 V, V_{ESD} = 3.0 V to 5.25 V, Ta = –20 °C to +70 °C)

Parameter	Symbol	Value			Unit
		Min.	Typ.	Max.	
V_{CLP} input current	I_{CLP}	—	5	20	µA
Clamp voltage	V_{CLAMP}	V_{CLP} – 0.1	V_{CLP}	V_{CLP} + 0.1	V

• PLL Block (AV_{DD} = DV_{DD} = PV_{DD} = 3.0 V to 3.6 V, V_{ESD} = 3.0 V to 5.25 V, Ta = –20 °C to +70 °C)

Parameter	Symbol	Value			Unit
		Min.	Typ.	Max.	
CLK jitter (@ f_{HSYNC} = 79.98 kHz, f_{CLK} = 135.0 MHz)	P_{tj}	—	1.0	1.5	ns

2. DC Characteristic in Digital Section

(AV_{DD} = DV_{DD} = PV_{DD} = 3.0 V to 3.6 V, V_{ESD} = 3.0 V to 5.25 V, Ta = –20 °C to +70 °C)


Parameter	Symbol	Value			Unit
		Min.	Typ.	Max.	
Digital input current	I_{ID}	–20	—	5	µA
Digital “H” level output voltage	V_{OHD}	DV_{DD} – 0.4	—	—	V
Digital “L” level output voltage	V_{OLD}	—	—	0.4	V

3. Switching Characteristics

(AV_{DD} = DV_{DD} = PV_{DD} = 3.0 V to 3.6 V, V_{ESD} = 3.0 V to 5.25 V, Ta = –20 °C to +70 °C)

Parameter		Symbol	Value			Unit
			Min.	Typ.	Max.	
A/D Maximum conversion rate		f_S	162	—	—	MSPS
Aperture time		t_{AD}	—	1.5	—	ns
VCO oscillation frequency	VCOL	f_{VCOL}	75	—	140	MHz
	VCOH	f_{VCOH}	85	—	162	MHz
CLK output delay time		t_{pd} ($_{HSYNC-CLK}$)	1.0	2.0	4.0	ns
Digital output delay time		t_{pd} ($_{CLK-ADCLK2}$)	0.0	1.0	2.0	ns
		t_{pd} ($_{CLK-DATA2}$)	2.5	4.0	6.0	ns
DSYNC output delay time		t_{pd} ($_{CLK-DSYNC}$)	0.5	1.5	2.0	ns

■ DIGITAL OUTPUT BUFFER LOAD CIRCUIT



Note: C_L includes a stray capacitance of a probe and a fixture.

■ MODE SETTING

Symbol	Setting	Mode
$\overline{CE}$	H	AII function power OFF
	L	Operation mode

■ SERIAL DATA SETTING (MSB FAST)

(Address) (Data)

LSB ← → MSB


RES	D0	D1	D2	D3	D4	D5	D6	D7	D8	D9	D10	Function
1	1	0	0	0	0	0	0	0	0	1	0	Counter low ranking 8 bit
2	0	1	0	0	0	0	0	X	X	X	X	Counter high ranking 4 bit
3	1	1	0	0	0	0	0	0	0	1	0	CLK DELAY adjust*1 : $t_d = N/(32 \times f_{CLK})$
	1	1	0	0	0	0	0	0	0	1	0	HSYNC polarity : 0 = through, 1 = inversion
	1	1	0	0	0	0	0	0	0	1	0	A/D converter output : 0 = operation, 1 = high impedance
4	0	0	1	0	0	0	0	0	0	1	0	CLK output : 0 = on, 1 = “L”
	0	0	1	0	0	0	0	0	0	1	0	CLKB output : 0 = on, 1 = “L”
	0	0	1	0	0	0	0	0	0	1	0	DSYNC output : 0 = on, 1 = “L”
	0	0	1	0	0	0	0	0	0	1	0	DSYNCB output : 0 = on, 1 = “L”
	0	0	1	0	0	0	0	0	0	1	0	ADCLKA output : 0 = on, 1 = “L”
	0	0	1	0	0	0	0	0	0	1	0	ADCLKB output : 0 = on, 1 = “L”
	0	0	1	0	0	0	0	0	0	1	0	DSYNC delay*2 : 0, 1, 2, 3
5	1	0	1	0	0	0	0	0	0	1	0	CLK change : 0 = VCO, 1 = External clock
	1	0	1	0	0	0	0	0	0	1	0	External clock input : 0 = CMOS, 1 = PECL
	1	0	1	0	0	0	0	0	0	1	0	Counter operation : 0 = on, 1 = off
	1	0	1	0	0	0	0	0	0	1	0	Charge pump current*3 : 0.1 mA, 0.5 mA, 1 mA
	1	0	1	0	0	0	0	0	0	1	0	VCO select : 0 = VCOL, 1 = VCOH
	1	0	1	0	0	0	0	0	0	1	0	Divider setting*4 : 1, 1/2, 1/4, 1/8 × 1

*1 : Setting at 6bit, Resolution : 1/32 × CLK, Setting range : 0 to 63/32 × CLK

*2, *3, *4 : See under table

Setting	0 (0, 0)	1 (1, 0)	2 (0, 1)	3 (1, 1)
DSYNC delay*2	0 CLK	1 CLK	2 CLK	3 CLK
Charge pump current*3	0.1 mA	0.5 mA	1.0 mA	—
Divider setting*4	1/1	1/2	1/4	1/8

Example: input at 16 bit



■ RECOMMENDED VALUE OF SERIAL DATA SETTING

	f_{CLK} (MHz)	f_{HSYNC} (kHz)	Counter	Icp (mA)	VCO select	Divider	f_{VCO} (MHz)
UXGA	162.000	75.000	2160	0.5	VCOH	1/1	162.000
SXGA	157.500	91.146	1728	0.5	VCOH	1/1	157.500
	135.000	81.130	1664	0.5	VCOH or VCOL	1/1	135.000
	108.000	64.904	1664	0.5	VCOH or VCOL	1/1	108.000
XGA	94.500	68.677	1376	0.5	VCOH or VCOL	1/1	94.500
	78.750	60.023	1312	0.5	VCOL	1/1	78.750
	75.000	56.476	1328	0.5	VCOH	1/2	150.000
	65.000	48.363	1344	0.5	VCOH or VCOL	1/2	130.000
SVGA	56.250	53.674	1048	0.5	VCOH or VCOL	1/2	112.500
	50.000	48.077	1040	0.5	VCOH or VCOL	1/2	100.000
	49.500	46.875	1056	0.5	VCOH or VCOL	1/2	99.000
	40.000	37.879	1056	0.5	VCOL	1/2	80.000
VGA	36.000	43.269	832	0.5	VCOH	1/4	144.000
	31.500	37.861	832	0.5	VCOH or VCOL	1/4	126.000
	25.175	31.469	800	0.5	VCOH or VCOL	1/4	100.700
	25.149	31.436	800	0.5	VCOH or VCOL	1/4	100.596
PAL	29.375	15.625	1880	0.5	VCOH or VCOL	1/4	117.500
	22.031	15.625	1410	0.5	VCOH or VCOL	1/4	88.125
	14.688	15.625	940	0.5	VCOH or VCOL	1/8	117.500
NTSC	24.545	15.734	1560	0.5	VCOH or VCOL	1/4	98.180
	18.409	15.734	1170	0.5	VCOH	1/8	147.270
	12.273	15.734	780	0.5	VCOH or VCOL	1/8	98.180

VCO select : VCOH (f_{VCO} = 85 MHz to 162 MHz)


VCOL (f_{VCO} = 75 MHz to 140 MHz)

$f_{CLK} = f_{HSYNC} \times$ Counter

$f_{VCO} = f_{HSYNC} \times$ Counter/Divider


■ TIMING DIAGRAM

- Demultiplex Output (in-phase) Mode




- ADIN input: Sampling at CLK rising (at CLKB falling)
- D_{A0} to D_{A7}: Output (after 6 CLK + t_{pd} ($_{CLK\text{-}DATA2}$) from sampling) at CLK rising (at CLKB falling)
- D_{B0} to D_{B7}: Output (after 5 CLK + t_{pd} ($_{CLK\text{-}DATA2}$) from sampling) at CLK rising (at CLKB falling)

■ CLAMP and AMP OPERATION




< For example, Sync on G signal input >




Contrast adjust : controlling the voltage difference between VRT and VRB (typ : $V_{RT} - V_{RB} = 1.33$ V)
Brightness adjust : controlling the voltage difference between VCLP and VRB (typ : $V_{CLP} = V_{RB}$)


■ CLAMP SIGNAL and HOLD SIGNAL



■ SERIAL DATA TRANSFER TIMING



■ TYPICAL APPLICATION



■ USAGE PRECAUTIONS

Be sure to ground the pins of AV_{DD}, DV_{DD}, PV_{DD}, V_{ESD}, V_{RTM}, V_{RBM}, V_{R1}, V_{R2}, V_{R3} and V_{REF} via high-frequency capacitor.


Place the high-frequency capacitor as close as possible to the pin.

■ ORDERING INFORMATION

Part number	Package	Remark
MB40C338PFV	120-pin plastic LQFP (FPT-120P-M21)	

■ PACKAGE DIMENSION

120-pin plastic LQFP
(FPT-120P-M21)



© 1998 FUJITSU LIMITED F120033S-2C-2

Dimension in mm (inches)

FUJITSU LIMITED

For further information please contact:

Japan

FUJITSU LIMITED
Corporate Global Business Support Division
Electronic Devices
Shinjuku Dai-Ichi Seimei Bldg. 7-1,
Nishishinjuku 2-chome, Shinjuku-ku,
Tokyo 163-0721, Japan
Tel: +81-3-5322-3347
Fax: +81-3-5322-3386

http://www.fujitsu.co.jp/

North and South America

FUJITSU MICROELECTRONICS, INC.
3545 North First Street,
San Jose, CA 95134-1804, U.S.A.
Tel: +1-408-922-9000
Fax: +1-408-922-9179

Customer Response Center
Mon. - Fri.: 7 am - 5 pm (PST)
Tel: +1-800-866-8608
Fax: +1-408-922-9179

http://www.fujitsumicro.com/

Europe

FUJITSU MICROELECTRONICS EUROPE GmbH
Am Siebenstein 6-10,
D-63303 Dreieich-Buchschlag,
Germany
Tel: +49-6103-690-0
Fax: +49-6103-690-122

http://www.fujitsu-fme.com/

Asia Pacific

FUJITSU MICROELECTRONICS ASIA PTE. LTD.
#05-08, 151 Lorong Chuan,
New Tech Park,
Singapore 556741
Tel: +65-281-0770
Fax: +65-281-0220

http://www.fmap.com.sg/

Korea

FUJITSU MICROELECTRONICS KOREA LTD.
1702 KOSMO TOWER, 1002 Daechi-Dong,
Kangnam-Gu,Seoul 135-280
Korea
Tel: +82-2-3484-7100
Fax: +82-2-3484-7111

F0009
© FUJITSU LIMITED Printed in Japan

All Rights Reserved.

The contents of this document are subject to change without notice. Customers are advised to consult with FUJITSU sales representatives before ordering.

The information and circuit diagrams in this document are presented as examples of semiconductor device applications, and are not intended to be incorporated in devices for actual use. Also, FUJITSU is unable to assume responsibility for infringement of any patent rights or other rights of third parties arising from the use of this information or circuit diagrams.

The contents of this document may not be reproduced or copied without the permission of FUJITSU LIMITED.

FUJITSU semiconductor devices are intended for use in standard applications (computers, office automation and other office equipments, industrial, communications, and measurement equipments, personal or household devices, etc.).
CAUTION:
Customers considering the use of our products in special applications where failure or abnormal operation may directly affect human lives or cause physical injury or property damage, or where extremely high levels of reliability are demanded (such as aerospace systems, atomic energy controls, sea floor repeaters, vehicle operating controls, medical devices for life support, etc.) are requested to consult with FUJITSU sales representatives before such use. The company will not be responsible for damages arising from such use without prior approval.

Any semiconductor devices have inherently a certain rate of failure. You must protect against injury, damage or loss from such failures by incorporating safety design measures into your facility and equipment such as redundancy, fire protection, and prevention of over-current levels and other abnormal operating conditions.

If any products described in this document represent goods or technologies subject to certain restrictions on export under the Foreign Exchange and Foreign Trade Control Law of Japan, the prior authorization by Japanese government should be required for export of those products from Japan.

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А