

FEATURES

Amplitude settling time: 200 ns
Wideband rejection: ≥ 35 dB
Single-chip replacement for mechanically tuned designs
RoHS compliant, 32-lead, 5 mm \times 5 mm LFCSP package

APPLICATIONS

Testing and measurement equipment
**Military radar and electronic warfare/electronic counter
measures (ECMs)**
Satellite communication and space
Industrial and medical equipment

GENERAL DESCRIPTION

The HMC882A is a monolithic microwave integrated circuit (MMIC) low-pass filter that features a user-selectable cutoff frequency (f_{3dB}). The cutoff frequency can be varied from 3.95 GHz to 6.9 GHz by applying a single analog tuning voltage between 0 V and 14 V. This low-pass filter provides a low 3 dB insertion loss, 13 dB return loss, and >20 dB stopband attenuation at $1.28 \times f_{3dB}$ GHz. This tunable filter can be used as a much

smaller alternative to physically large switched filter banks and cavity tuned filters. The HMC882A has excellent microphonics due to the monolithic design and low residual phase noise of -165 dBc/Hz, and provides a dynamically adjustable solution in advanced communications applications. The low-pass tunable filter is packaged in a RoHS compliant, 5 mm \times 5mm LFCSP package.


FUNCTIONAL BLOCKDIAGRAM

Figure 1.

TABLE OF CONTENTS

| | | | |
|--|---|---|----|
| Features | 1 | Typical Performance Characteristics | 6 |
| Applications..... | 1 | Theory of Operation | 9 |
| Functional BlockDiagram | 1 | Applications Information | 10 |
| General Description | 1 | Typical Application Circuit..... | 10 |
| Revision History | 2 | Evaluation Printed Circuit Board (PCB)..... | 10 |
| Specifications..... | 3 | Outline Dimensions | 11 |
| Absolute Maximum Ratings..... | 4 | Ordering Guide | 11 |
| ESD Caution..... | 4 | | |
| Pin Configuration and Function Descriptions..... | 5 | | |

REVISION HISTORY

2/2019—Revision 0: Initial Version

SPECIFICATIONS

$T_A = 25^\circ\text{C}$, with cutoff frequency control voltage (V_{FCTL}) varying from 0 V to 14 V, unless otherwise noted.

Table 1.

| Parameter | Min | Typ | Max | Unit | Test Conditions/Comments |
|--|------|------------------------------|---------|-----------------------|---|
| FREQUENCY RANGE | | | | | |
| Passband | 0 | | 6.9 | GHz | |
| Cutoff Frequency ($f_{3\text{dB}}$) | 3.95 | | 6.9 | GHz | |
| REJECTION | | | | | |
| Stopband Frequency | | $1.28 \times f_{3\text{dB}}$ | | GHz | ≥ 20 dB |
| Re-Entry Frequency | | ≥ 30 | | GHz | ≥ 35 dB wideband rejection |
| LOSS | | | | | |
| Insertion Loss | | 3 | | dB | |
| Return Loss | | 13 | | dB | |
| DYNAMIC PERFORMANCE | | | | | |
| Maximum Input Power for Linear Operation | | | 10 | dBm | |
| Input Third-Order Intercept | | 41 | | dBm | Input power (P_{IN}) = 20 dBm, two-tone |
| Group Delay | | 0.4 | | ns | |
| Amplitude Settling | | 200 | | ns | Time to settle to minimum insertion loss, within ≤ 0.5 dB of static insertion loss |
| Drift Rate | | 0.3 | | MHz/ $^\circ\text{C}$ | |
| RESIDUAL PHASE NOISE | | | | | |
| 1 MHz Offset | | -165 | | dBc/Hz | |
| TUNING | | | | | |
| Voltage (V_{FCTL}) | 0 | | 14 | V | |
| Cutoff Frequency Control Current (I_{FCTL}) | | | ± 1 | μA | Rated current for pin |

ABSOLUTE MAXIMUM RATINGS

Table 2.

| Parameter | Rating |
|---|-----------------|
| Tuning | |
| Voltage (V_{FCTL}) | -0.5 V to +15 V |
| Current (I_{FCTL}) | ± 1 mA |
| RF Input Power | 27 dBm |
| Temperature | |
| Operating Temperature Range | -40°C to +85°C |
| Storage Temperature Range | -65°C to +150°C |
| Junction Temperature for 1 Million Mean Time to Failure (MTTF) | 175°C |
| Nominal Junction Temperature (Exposed Pad Temperature, $T_{EPAD} = 85^{\circ}\text{C}$, $P_{IN} = 10$ dBm) | 90 |
| Electrostatic Discharge (ESD) Rating | |
| Human Body Model (HBM) | 1000 V |
| Field Induced Charge Device Model (FICDM) | 1250 V |
| Moisture Sensitivity Level (MSL) Rating | MSL3 |


Stresses at or above those listed under Absolute Maximum Ratings may cause permanent damage to the product. This is a stress rating only; functional operation of the product at these or any other conditions above those indicated in the operational section of this specification is not implied. Operation beyond the maximum operating conditions for extended periods may affect product reliability.

ESD CAUTION



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

PIN CONFIGURATION AND FUNCTION DESCRIPTIONS



- NOTES**
1. NIC = NOT INTERNALLY CONNECTED. ALL DATA SHOWN HEREIN WAS MEASURED WITH THESE PINS CONNECTED TO RF AND DC GROUND EXTERNALLY.
 2. EXPOSED PAD. THE PACKAGE BOTTOM HAS AN EXPOSED PAD THAT MUST BE CONNECTED TO RF AND DC GROUND.

Figure 2. Pin Configuration

Table 3. Pin Function Descriptions

| Pin No. | Mnemonic | Description |
|-------------------------------------|-------------------|---|
| 1 to 4, 7 to 13, 15 to 18, 21 to 32 | NIC | Not Internally Connected. These pins are not connected internally. All data shown herein was measured with these pins connected to RF and dc ground externally. |
| 5, 20 | GND | Ground. Connect these pins to RF and dc ground. |
| 6 | RFIN | Radio Frequency Input. This pin is dc-coupled and matched to 50 Ω. Do not apply an external voltage to this pin. |
| 14 | V _{FCTL} | Cutoff Frequency Control Voltage. This pin controls the cutoff frequency of the device. |
| 19 | RFOUT | Radio Frequency Output. This pin is dc-coupled and matched at 50 Ω. Do not apply an external voltage to this pin. |
| | EPAD | Exposed Pad. The package bottom has an exposed metal pad that must be connected to RF and dc ground. |



Figure 3. GND Interface Schematic




Figure 4. RFIN Interface Schematic




Figure 5. V_{FCTL} Interface Schematic




Figure 6. RFOUT Interface Schematic

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 7. Insertion Loss vs. Broadband Frequency at Various V_{FCTL} Voltages




Figure 10. Return Loss vs. Broadband Frequency at Various V_{FCTL} Voltages




Figure 8. Insertion Loss vs. RF Frequency at Various V_{FCTL} Voltages




Figure 11. Return Loss vs. RF Frequency at Various V_{FCTL} Voltages




Figure 9. Insertion Loss vs. RF Frequency at Various Temperatures, $V_{FCTL} = 7V$




Figure 12. Return Loss vs. RF Frequency at Various Temperatures, $V_{FCTL} = 7V$




Figure 13. Cutoff Frequency (f_{3dB}) vs. V_{FCTL} at Various Temperatures




Figure 16. Return Loss vs. V_{FCTL} at Various Temperatures, 2 dB Bandwidth




Figure 14. Rejection Ratio vs. V_{FCTL} at Various Temperatures; Rejection Ratio Is the Ratio of the Frequency of Which the Relative Insertion Loss Is 20 dB to f_{3dB}




Figure 17. Tuning Sensitivity vs. V_{FCTL} at Various Temperatures




Figure 15. Insertion Loss vs. V_{FCTL} at Various Temperatures




Figure 18. Residual Phase Noise vs. Offset Frequency at Various V_{FCTL} Voltages




Figure 19. Group Delay vs. RF Frequency at Various V_{FCTL} Voltages




Figure 21. Phase Shift vs. Input Power (P_{IN}) at Various V_{FCTL} Voltages




Figure 20. Input IP3 vs. V_{FCTL} at Various Temperatures, $P_{IN} = 20$ dBm

THEORY OF OPERATION

The HMC882A is a MMIC low-pass filter that features a user-selectable pass band frequency. Varying the applied analog tuning voltage between 0 V and 14 V at V_{FCTL} varies the f_{3dB} frequency between 3.95 GHz and 6.9 GHz.

APPLICATIONS INFORMATION

TYPICAL APPLICATION CIRCUIT

Figure 22 shows the typical application circuit for the HMC882A. The RFIN and RFOUT pins are dc-coupled and require external, 100 pF series capacitors (C1 and C2).




Figure 22. Typical Application Circuit

EVALUATION PRINTED CIRCUIT BOARD (PCB)

All RF traces are routed on Layer 1 (primary side) and the remaining three layers are ground planes that provide a solid ground for RF transmission lines, as shown in Figure 23. The top dielectric material is Rogers 4350, which offers low loss performance. The prepreg material in Layer 2 attaches the Isola 370HR core layer with copper traces layers above and below the core layer. Both the prepreg material and the Isola 370HR core layer are used to achieve the required board finish thickness.




Figure 23. Cross Sectional View of the EV1HMC882ALP5 PCB Layers

The PCB in this application uses RF circuit design techniques. Signal lines must have 50 Ω impedance and the package ground leads and exposed pad must be connected directly to the ground plane (see Figure 23). Use a sufficient number of via holes to connect the top and bottom ground planes. The evaluation PCB shown in Figure 24 is available from Analog Devices, Inc., upon request.

Table 4. Bill of Materials for the EV1HMC882ALP5

| Item | Description |
|------------------|--|
| J1 to J2 | PCB mount SRI Subminiature Version A (SMA) connector |
| J3 to J4 | PCB mount Johnson SMA connector |
| C1, C2 | Capacitor, 100 pF, 0402 |
| U1 | HMC882A |
| PCB ¹ | 08-049598 ² evaluation PCB |

¹ Circuit board material is Arlon 25FR or Rogers 25FR.

² 08-049598 is the raw, bare PCB identifier. Reference the EV1HMC882ALP5 when ordering the complete evaluation PCB.





Figure 24. Evaluation PCB Top Layer Outline Dimensions

OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MO-220-WHHD-5

Figure 25. 32-Lead Lead Frame Chip Scale Package [LFCSP]
 5 mm × 5 mm Body and 0.75 mm Package Height
 (CP-32-12)

Dimensions shown in millimeters

ORDERING GUIDE

| Model ¹ | Temperature Range | Package Description | Package Option |
|--------------------|-------------------|---|----------------|
| HMC882ALP5E | −40°C to +85°C | 32-Lead Lead Frame Chip Scale Package [LFCSP] | CP-32-12 |
| HMC882ALP5ETR | −40°C to +85°C | 32-Lead Lead Frame Chip Scale Package [LFCSP] | CP-32-12 |
| EV1HMC882ALP5 | | Evaluation PCB | |

¹ All models are RoHS compliant parts.

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели,
кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: ocean@oceanchips.ru

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А