Product Specification

PE42422

UltraCMOS® SPDT RF Switch 100 – 6000 MHz

Features

- Symmetric SPDT reflective switch
- Low insertion loss
  - 0.25 dB typical @ 1000 MHz
  - 0.40 dB typical @ 3000 MHz
  - 0.65 dB typical @ 5000 MHz
  - 0.90 dB typical @ 6000 MHz
- Wide supply range of 2.3V to 5.5V
- Excellent linearity
  - IIP2 of 115 dBm
  - IIP3 of 70 dBm
- High ESD tolerance
  - 4kV HBM on RF pins to GND
  - 1kV on all other pins
- Logic Select (LS) pin provides maximum flexibility of control logic
- 12-lead 2x2 mm QFN package

Product Description

The PE42422 is a HaRP™ technology-enhanced SPDT RF switch designed to cover a broad range of applications from 100-6000 MHz. This reflective switch integrates on-board CMOS control logic with a low voltage CMOS-compatible control interface and requires no external components.

Peregrine's HaRP™ technology enhancements deliver high linearity and exceptional harmonics performance. It is an innovative feature of the UltraCMOS® process, providing performance superior to GaAs with the economy and integration of conventional CMOS.

Figure 1. Functional Diagram





Figure 2. Package Type

12-lead 2x2x0.55 mm QFN



©2012 Peregrine Semiconductor Corp. All rights reserved.

Table 1. Electrical Specifications Temp = 25°C[1], V_{DD} = 2.3V to 5.5V (Z_S = Z_L = 50Ω)

Parameter	Path	Condition	Min	Typ	Max	Units
Operational Frequency			100		6000	MHz
Insertion Loss[2]	RFX to RFC	100-1000 MHz		0.25	0.35	dB
		1000-2000 MHz		0.30	0.40	dB
		2000-3000 MHz		0.40	0.50	dB
		3000-4000 MHz		0.50	0.70	dB
		4000-5000 MHz		0.65	0.90[2]	dB
		5000-6000 MHz		0.90	1.25[2]	dB
Isolation	RFX to RFC	100-1000 MHz	42	44		dB
		1000-2000 MHz	33	35		dB
		2000-3000 MHz	27	29		dB
		3000-4000 MHz	22	24		dB
		4000-5000 MHz	18	20		dB
		5000-6000 MHz	15	17		dB
Isolation	RFX to RFX	100-1000 MHz	40	41		dB
		1000-2000 MHz	32	33		dB
		2000-3000 MHz	26	28		dB
		3000-4000 MHz	22	24		dB
		4000-5000 MHz	18	20		dB
		5000-6000 MHz	15	16		dB
Return Loss[2]	RFX to RFC	100-1000 MHz		28		dB
		1000-2000 MHz		21		dB
		2000-3000 MHz		20		dB
		3000-4000 MHz		18		dB
		4000-5000 MHz		16[2]		dB
		5000-6000 MHz		13[2]		dB
2nd Harmonic	RFX-RFC	+32 dBm output power, 850 / 900 MHz		-67		dBc
		+32 dBm output power, 1800 / 1900 MHz		-69		dBc
3rd Harmonic	RFX-RFC	+32 dBm output power, 850 / 900 MHz		-61		dBc
		+32 dBm output power, 1800 / 1900 MHz		-55		dBc
IMD3	RF-RFC	Bands I, II, V, VIII +17 dBm CW @ TX freq at RFC, -15 dBm CW @ 2Tx-Rx at RFC, 50Ω		-115		dBm
IIP2	RFX	100-6000 GHz		115		dBm
IIP3	RFX	100-6000 GHz		70		dBm
Input 0.1 dB Compression	RFX or RFC	100-6000 GHz		34		dBm
Switching Time		50% CTRL to (10%-90%) or (90%-10%) RF		2	4	µs

Notes: 1. Typical performance over temperature and V_{DD} shown in *Figure 4* through *Figure 20*
2. High frequency performance can be improved by external matching (see *Figure 21* through *Figure 26 and Figure 29*)

©2012 Peregrine Semiconductor Corp. All rights reserved.

Figure 3. Pin Configuration (Top View)




Table 2. Pin Descriptions

Pin No.	Pin Name	Description
1	GND	Ground
2	RF2[1]	RF Port 2
3	GND	Ground
4	GND	Ground
5	RFC[1]	RF Common
6	GND	Ground
7	GND	Ground
8	RF1[1]	RF Port 1
9	DGND	Digital Ground
10	V1	Switch control input, CMOS logic level
11	LS	Logic Select, CMOS logic level
12	V_{DD}	Supply
Paddle	GND	Ground for proper device operation

Note 1: Blocking capacitors needed only when non-zero DC voltage present

Table 3. Truth Table

Path	V1	LS
RFC-RF2	1	1
RFC-RF1	0	1
RFC-RF1	1	0
RFC-RF2	0	0

Table 4. Operating Ranges

Parameter	Min	Typ	Max	Units
V_{DD} Supply Voltage	2.3	3.3	5.5	V
I_{DD} Power Supply Current		120	200	µA
RFX-RFC input power (50Ω)			+32	dBm
Control Voltage High	1.2	1.5	3.3	V
Control Voltage Low	0	0	0.5	V
Operating temperature range	-40	+25	+85	°C

Table 5. Absolute Maximum Ratings

Parameter/Conditions	Min	Max	Units
P_{MAX} Input Power[1]		+32	dBm
ESD Voltage HBM[2] RF pins to GND All other pins		 4000 1000	 V V
ESD Voltage MM, all pins[3]		200	V
T_{ST} Storage Temperature	-65	+150	°C

Notes: 1. V_{DD} within operating range specified in *Table 4*
2. HBM ESD Voltage (MIL_STD 883 Method 3015.7)
3. MM ESD Voltage (JEDEC JESD22-A115-A)

Exceeding absolute maximum ratings may cause permanent damage. Operation should be restricted to the limits in the Operating Ranges table.

Electrostatic Discharge (ESD) Precautions

When handling this UltraCMOS® device, observe the same precautions that you would use with other ESD-sensitive devices. Although this device contains circuitry to protect it from damage due to ESD, precautions should be taken to avoid exceeding the specified rating.

Latch-Up Avoidance

Unlike conventional CMOS devices, UltraCMOS® devices are immune to latch-up.

Moisture Sensitivity Level

The Moisture Sensitivity Level rating for the PE42422 in the 12-lead 2x2x0.55 mm QFN package is MSL1.

©2012 Peregrine Semiconductor Corp. All rights reserved.

Typical Performance Data @ 25°C and V_{DD} = 3.3V unless otherwise specified

Figure 4. Insertion Loss RFX[1]




Figure 5. Insertion Loss vs Temp (RF1-RFC)[1]




Figure 6. Insertion Loss vs Temp (RF2-RFC)[1]




Figure 7. Insertion Loss vs V_{DD} (RF1-RFC)[1]





Figure 8. Insertion Loss vs V_{DD} (RF2-RFC)[1]



Note 1: High frequency performance can be improved by external matching (see *Figure 21* through *Figure 26 and Figure 29*)

©2012 Peregrine Semiconductor Corp. All rights reserved.

Typical Performance Data @ 25°C and V_{DD} = 3.3V unless otherwise specified

Figure 9. RFX-RFX Isolation vs Temp




Figure 10. RFX-RFX Isolation vs V_{DD}




Figure 11. RFC-RFX Isolation vs Temp





Figure 12. RFC-RFX Isolation vs V_{DD}



©2012 Peregrine Semiconductor Corp. All rights reserved.

Typical Performance Data @ 25°C and V_{DD} = 3.3V unless otherwise specified

Figure 13. RFC Port Return Loss vs Temp (RF1 Active)[1]




Figure 14. RFC Port Return Loss vs V_{DD} (RF1 Active)[1]




Figure 15. RFC Port Return Loss vs Temp (RF2 Active)[1]





Figure 16. RFC Port Return Loss vs V_{DD} (RF2 Active)[1]



Note 1: High frequency performance can be improved by external matching (see *Figure 21* through *Figure 26 and Figure 29*)

©2012 Peregrine Semiconductor Corp. All rights reserved.

Typical Performance Data @ 25°C and V_{DD} = 3.3V unless otherwise specified

Figure 17. Active Port Return Loss vs Temp (RF1 Active)[1]




Figure 18. Active Port Return Loss vs V_{DD} (RF1 Active)[1]




Figure 19. Active Port Return Loss vs Temp (RF2 Active)[1]





Figure 20. Active Port Return Loss vs V_{DD} (RF2 Active)[1]



Note 1: High frequency performance can be improved by external matching (see *Figure 21* through *Figure 26 and Figure 29*)

©2012 Peregrine Semiconductor Corp. All rights reserved.

Performance Comparison @ 25°C and V_{DD} = 3.3V with or without matching

Figure 21. Insertion Loss RF1[1]




Figure 22. Insertion Loss RF2[1]




Figure 23. Active Port Return Loss (RF1 Active)[1]




Figure 24. Active Port Return Loss (RF2 Active)[1]




Figure 25. RFC Port Return Loss (RF1 Active)[1]





Figure 26. RFC Port Return Loss (RF2 Active)[1]



Note 1: High frequency performance can be improved by external matching (see *Figure 21* through *Figure 26 and Figure 29*)


©2012 Peregrine Semiconductor Corp. All rights reserved.

Evaluation Board

The SPDT switch evaluation board was designed to ease customer evaluation of Peregrine's PE42422. The RF common port is connected through a 50Ω transmission line via the top SMA connector, J2. RF1 and RF2 ports are connected through 50Ω transmission lines via SMA connectors J1 and J3, respectively. A through 50Ω transmission is available via SMA connectors J4 and J5. This transmission line can be used to estimate the loss of the PCB over the environmental conditions being evaluated. J8 provides DC and digital inputs to the device.

The board is constructed of a four metal layer material with a total thickness of 62 mils. The top and bottom RF layers are Rogers RO4350 material with a 10 mil RF core. The middle layers provide ground for the transmission lines. The transmission lines were designed using a coplanar waveguide with ground plane model using a trace width of 22 mils, trace gaps of 7 mils, and metal thickness of 2.1 mils.


Figure 27. Evaluation Board Layout



101-0593


©2012 Peregrine Semiconductor Corp. All rights reserved.

Figure 28. Evaluation Board Schematic



©2012 Peregrine Semiconductor Corp. All rights reserved.

Figure 29. Evaluation Board Schematic with Matching



©2012 Peregrine Semiconductor Corp. All rights reserved.

Figure 30. Package Drawing
12-lead 2x2x0.55 mm QFN





Figure 31. Top Marking Specifications




17-0112

Marking Spec Symbol	Package Marking	Definition
PP	DE	Part number marking for PE42422
ZZ	00-99	Last two digits of lot code
Y	0-9	Last digit of year, starting from 2009 (0 for 2010, 1 for 2011, etc)
WW	01-53	Work week

©2012 Peregrine Semiconductor Corp. All rights reserved.

Figure 32. Tape and Reel Specifications

12-lead 2x2x0.55 mm QFN



Device Orientation in Tape

	Nominal	Tolerance
Ao	2.20	±0.1
Bo	2.20	±0.1
Ko	0.75	±0.1

(I) Measured from centreline of sprocket hole to centreline of pocket.
(II) Cumulative tolerance of 10 sprocket holes is ± 0.10 .
(III) Measured from centreline of sprocket hole to centreline of pocket.
(IV) Other material available.

This part shall not contain any banned substance as Sony standard SS–00259

Table 6. Ordering Information

Order Code	Description	Package	Shipping Method
PE42422MLAA-Z	PE42422 SPDT RF Switch	Green 12-lead 2x2mm QFN	3000 units T/R
EK42422-01	PE42422 Evaluation board	Evaluation Kit	1/Box

Sales Contact and Information

For Sales and contact information please visit www.psemi.com.

Advance Information*:** The product is in a formative or design stage. The datasheet contains design target specifications for product development. Specifications and features may change in any manner without notice. ***Preliminary Specification: The datasheet contains preliminary data. Additional data may be added at a later date. Peregrine reserves the right to change specifications at any time without notice in order to supply the best possible product. ***Product Specification:*** The datasheet contains final data. In the event Peregrine decides to change the specifications, Peregrine will notify customers of the intended changes by issuing a CNF (Customer Notification Form).
The information in this datasheet is believed to be reliable. However, Peregrine assumes no liability for the use of this information. Use shall be entirely at the user's own risk.

No patent rights or licenses to any circuits described in this datasheet are implied or granted to any third party. Peregrine's products are not designed or intended for use in devices or systems intended for surgical implant, or in other applications intended to support or sustain life, or in any application in which the failure of the Peregrine product could create a situation in which personal injury or death might occur. Peregrine assumes no liability for damages, including consequential or incidental damages, arising out of the use of its products in such applications.
The Peregrine name, logo, UltraCMOS and UTSi are registered trademarks and HaRP, MultiSwitch and DuNE are trademarks of Peregrine Semiconductor Corp.

©2012 Peregrine Semiconductor Corp. All rights reserved.

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А