maxim integrated™

MAX4130–MAX4134

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply, Rail-to-Rail I/O Op Amps

General Description

The MAX4130–MAX4134 family of operational amplifiers combines 10MHz gain-bandwidth product and excellent DC accuracy with rail-to-rail operation at the inputs and outputs. These devices require only 900µA per amplifier, and operate from either a single supply (+2.7V to +6.5V) or dual supplies (±1.35V to ±3.25V) with a common-mode voltage range that extends 250mV beyond V_{EE} and V_{CC}. They are capable of driving 250Ω loads and are unity-gain stable. In addition, the MAX4131/MAX4133 feature a shutdown mode in which the outputs are placed in a high-impedance state and the supply current is reduced to only 25µA per amplifier.

With their rail-to-rail input common-mode range and output swing, the MAX4130–MAX4134 are ideal for low-voltage, single-supply operation. Although the minimum operating voltage is specified at 2.7V, the devices typically operate down to 1.8V. In addition, low offset voltage and high speed make them the ideal signal-conditioning stages for precision, low-voltage data-acquisition systems. The MAX4130 is offered in the space-saving 5-pin SOT23 package. The MAX4131 is offered in the ultra-small 6-bump, 1mm x 1.5mm chip-scale package (UCSP™).

Selector Guide

PART	AMPS PER PACKAGE	SHUTDOWN MODE	PIN-PACKAGE
MAX4130	1	—	5 SOT23
MAX4131	1	Yes	6 UCSP, 8 µMAX/SO
MAX4132	2	—	8 µMAX/SO
MAX4133	2	Yes	14 SO
MAX4134	4	—	14 SO

Applications

Battery-Powered Instruments

Portable Equipment

Data-Acquisition Systems

Signal Conditioning

Low-Power, Low-Voltage Applications

Pin Configurations appear at end of data sheet.

UCSP is a trademark of Maxim Integrated Products, Inc.

Features

- **6-Bump UCSP (MAX4131)**
- **+2.7V to +6.5V Single-Supply Operation**
- **Rail-to-Rail Input Common-Mode Voltage Range**
- **Rail-to-Rail Output Voltage Swing**
- **10MHz Gain-Bandwidth Product**
- **900µA Quiescent Current per Amplifier**
- **25µA Shutdown Function (MAX4131/MAX4133)**
- **200µV Offset Voltage**
- **No Phase Reversal for Overdriven Inputs**
- **Drive 250Ω Loads**
- **Stable with 160pF Capacitive Loads**
- **Unity-Gain Stable**

Ordering Information

PART	TEMP RANGE	PIN-PACKAGE	TOP MARK
MAX4130EUK-T	-40°C to +85°C	5 SOT23	AABB
MAX4131C/D	0°C to +70°C	Dice*	—
MAX4131EBT-T	-40°C to +85°C	6 UCSP	AAX
MAX4131EUA	-40°C to +85°C	8 µMAX	—
MAX4131ESA	-40°C to +85°C	8 SO	—

**Dice are specified at T_A = +25°C. DC parameters only.*

Ordering Information continued at end of data sheet.

Typical Operating Circuit



For pricing, delivery, and ordering information, please contact Maxim Direct at 1-888-629-4642, or visit Maxim's website at www.maximintegrated.com.

19-1089; Rev 4; 1/14

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply, Rail-to-Rail I/O Op Amps

ABSOLUTE MAXIMUM RATINGS

Supply Voltage (V_{CC} - V_{EE}) 7.5V
IN+, IN-, $\overline{SHDN}$ Voltage ..... (V_{CC} + 0.3V) to (V_{EE} - 0.3V)
Output Short-Circuit Duration (Note 1) ..... Continuous
(short to either supply)
Continuous Power Dissipation (T_A = +70°C)
5-Pin SOT23 (derate 7.1mW/°C above +70°C) 571mW
6-Bump UCSP (derate 2.9mW/°C above +70°C) 308mW
8-Pin SO (derate 5.88mW/°C above +70°C) 471mW
8-Pin µMAX (derate 4.10mW/°C above +70°C) 330mW
14-Pin SO (derate 8.00mW/°C above +70°C) 640mW
Operating Temperature Range
MAX413_E__ ..... -40°C to +85°C
Maximum Junction Temperature ..... +150°C
Storage Temperature Range ..... -65°C to +160°C
Lead Temperature (soldering, 10s) ..... +300°C
Bump Reflow Temperature ..... +235°C

Note 1: Provided that the maximum package power-dissipation rating is not exceeded.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

DC ELECTRICAL CHARACTERISTICS

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = +25°C**, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Input Offset Voltage	V_{OS}	V_{CM} = V_{EE} to V_{CC}	MAX4130EUK		±0.35	±1.50	mV
			MAX4131ESA		±0.20	±0.60	
			MAX4131EUA/ MAX4131EBT		±0.35	±1.20	
			MAX4132ESA/ MAX4133ESD		±0.25	±0.75	
			MAX4132EUA		±0.40	±1.50	
			MAX4134ESD		±0.35	±1.50	
Input Bias Current	I_B	V_{CM} = V_{EE} to V_{CC}			±50	±150	nA
Input Offset Current	I_{OS}	V_{CM} = V_{EE} to V_{CC}	MAX4131EBT			±15	nA
			All other packages			±12	
Differential Input Voltage	R_{IN}	-1.5V < V_{DIFF} < 1.5V			500		kΩ
Common-Mode Input Voltage Range	CMVR			V_{EE} - 0.25		V_{CC} + 0.25	V
Common-Mode Rejection Ratio	CMRR	V_{EE} - 0.25V < V_{CM} < V_{CC} + 0.25V	MAX4130EUK	67	90		dB
			MAX4131ESA	78	98		
			MAX4131EUA/ MAX4131EBT	68	88		
			MAX4132ESA/ MAX4133ESD	74	94		
			MAX4132EUA	66	86		
			MAX4134ESD	64	84		
Power-Supply Rejection Ratio	PSRR	V_{CC} = 2.7V to 6.5V		78	100		dB
Output Resistance	R_{OUT}	A_V = 1			0.1		Ω
Off-Leakage Current	I_{LKG}	$\overline{SHDN}$ < 0.8V, V_{OUT} = 0V to V_{CC}			±0.1	±1	µA

DC ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = +25°C**, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS			MIN	TYP	MAX	UNITS
Large-Signal Voltage Gain	A_V	V_{CC} = 2.7V	V_{OUT} = 0.25V to 2.45V, R_L = 100kΩ		92	108		dB
			V_{OUT} = 0.4V to 2.3V, R_L = 250Ω		72	82		
		V_{CC} = 5V	V_{OUT} = 0.25V to 4.75V, R_L = 100kΩ		94	108		
			V_{OUT} = 0.4V to 4.6V, R_L = 250Ω		75	86		
Output Voltage Swing	V_O	MAX4130/ MAX4131	R_L = 100kΩ	V_{CC} - V_{OH}		12	20	mV
				V_{OL} - V_{EE}		20	35	
			R_L = 250Ω	V_{CC} - V_{OH}		240	290	
				V_{OL} - V_{EE}		125	170	
		MAX4132/ MAX4133/ MAX4134	R_L = 100kΩ	V_{CC} - V_{OH}		15	30	
				V_{OL} - V_{EE}		25	40	
			R_L = 250Ω	V_{CC} - V_{OH}		280	330	
				V_{OL} - V_{EE}		180	230	
Output Short-Circuit Current	I_{SC}					50		mA
$\overline{SHDN}$ Logic Threshold	V_{IL}	MAX4131–MAX4134		Low			0.8	V
	V_{IH}			High	2.0			
$\overline{SHDN}$ Input Current	I_{IL}	MAX4131–MAX4134				±1	±3	µA
Operating Supply Voltage Range	V_{CC}				2.7		6.5	V
Supply Current per Amplifier	I_{CC}	V_{CM} = V_{OUT} = V_{CC}/2		V_{CC} = 2.7V		900	1050	µA
				V_{CC} = 5V		1000	1150	
Shutdown Supply Current per Amplifier	$I_{\overline{SHDN}}$	$\overline{SHDN}$ > 0.8V, MAX4131–MAX4134		V_{CC} = 2.7V		25	40	µA
				V_{CC} = 5V		40	60	

DC ELECTRICAL CHARACTERISTICS

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = -40°C to +85°C**, unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Input Offset Voltage	V_{OS}	V_{CM} = V_{EE} to V_{CC}	MAX4130EUK			±3.50	mV
			MAX4131ESA			±0.75	
			MAX4131EUA/MAX4131EBT			±4.40	
			MAX4132ESA/MAX4133ESD			±0.95	
			MAX4132EUA			±4.70	
			MAX4134ESD			±4.00	
Input Offset Voltage Tempco	TCV_{OS}				±2		µV/°C
Input Bias Current	I_B	V_{CM} = V_{EE} to V_{CC}				±160	nA

DC ELECTRICAL CHARACTERISTICS

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = -40°C to +85°C**, unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS			MIN	TYP	MAX	UNITS
Input Offset Current	I_{OS}	V_{CM} = V_{EE} to V_{CC}	MAX4131EBT				±24	nA
			All other packages				±18	
Common-Mode Input Voltage Range	CMVR				V_{EE} - 0.20		V_{CC} + 0.20	V
Common-Mode Rejection Ratio	CMRR	V_{EE} - 0.2V < V_{CM} < V_{CC} + 0.2V	MAX4130EUK		62			dB
			MAX4131ESA		76			
			MAX4131EUA/MAX4131EBT		60			
			MAX4132ESA/MAX4133ESD		74			
			MAX4132EUA		58			
			MAX4134ESD		60			
Power-Supply Rejection Ratio	PSRR	V_{CC} = 2.7V to 6.5V			74			dB
Off-Leakage Current	I_{LKG}	$\overline{SHDN}$ < 0.8V, V_{OUT} = 0V to V_{CC}					±12	µA
Large-Signal Voltage Gain	A_V	V_{CC} = 2.7V	V_{OUT} = 0.25V to 2.45V, R_L = 100kΩ		84			dB
			V_{OUT} = 0.4V to 2.3V, R_L = 250Ω		66			
		V_{CC} = 5V	V_{OUT} = 0.25V to 4.75V, R_L = 100kΩ		86			
			V_{OUT} = 0.4V to 4.6V, R_L = 250Ω		68			
Output Voltage Swing	V_O	MAX4130/ MAX4131ESA/ MAX4131EUA	R_L = 100kΩ	V_{CC} - V_{OH}			25	mV
				V_{OL} - V_{EE}			40	
			R_L = 250Ω	V_{CC} - V_{OH}			300	
				V_{OL} - V_{EE}			190	
		MAX4131EBT	R_L = 100kΩ	V_{CC} - V_{OH}			25	
				V_{OL} - V_{EE}			40	
			R_L = 250Ω	V_{CC} - V_{OH}			350	
				V_{OL} - V_{EE}			190	
		MAX4132/ MAX4133/ MAX4134	R_L = 100kΩ	V_{CC} - V_{OH}			35	
				V_{OL} - V_{EE}			50	
			R_L = 250Ω	V_{CC} - V_{OH}			350	
				V_{OL} - V_{EE}			250	

DC ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = -40°C to +85°C**, unless otherwise noted.) (Note 2)

PARAMETER	SYMBOL	CONDITIONS			MIN	TYP	MAX	UNITS
$\overline{SHDN}$ Logic Threshold	V_{IL}	MAX4131–MAX4134		Low			0.8	V
	V_{IH}			High	2.0			
$\overline{SHDN}$ Input Current	I_{IL}	MAX4131–MAX4134					±3	µA
Operating Supply Voltage Range	V_{CC}				2.7		6.5	V
Supply Current per Amplifier	I_{CC}	V_{CM} = V_{OUT} = V_{CC}/2	MAX4131EBT	V_{CC} = 2.7V			1200	µA
				V_{CC} = 5V			1350	
			All other devices	V_{CC} = 2.7V			1100	
				V_{CC} = 5V			1200	
Shutdown Supply Current per Amplifier	$I_{\overline{SHDN}}$	$\overline{SHDN}$ > 0.8V, MAX4131–MAX4134		V_{CC} = 2.7V			50	µA
				V_{CC} = 5V			70	

Note 2: All devices are 100% tested at T_A = +25°C. MAX4130EUK/MAX4131EBT temperature limits are guaranteed by design.

AC ELECTRICAL CHARACTERISTICS

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, $\overline{SHDN}$ ≥ 2V (or open), **T_A = +25°C**, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Gain-Bandwidth Product	GBWP				10		MHz
Phase Margin	θ_M				62		Degrees
Gain Margin	G_M				12		dB
Total Harmonic Distortion	THD	f = 10kHz, V_{OUT} = $2V_{P-P}$ (A_V = 1)			0.003		%
Slew Rate	SR				4		V/µs
Settling Time to 0.01%	t_S	A_V = 1, V_{OUT} = 2V step			2.0		µs
Turn-On Time	t_{ON}	V_{CC} = 0V to 3V step, V_{OUT} = V_{CC}/2			1		µs
$\overline{SHDN}$ Delay		MAX4131–MAX4134, V_{CC} = 3V, V_{OUT} = V_{CC}/2	Enable		1		µs
			Disable		0.2		
Input Capacitance	C_{IN}				3		pF
Input Noise-Voltage Density	e_n	f = 1kHz			22		$nV/\sqrt{Hz}$
Input Noise-Current Density	i_n	f = 1kHz			0.4		$pA/\sqrt{Hz}$
Capacitive-Load Stability	C_L	A_V = 1			160		pF

Typical Operating Characteristics

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC} / 2, T_A = +25°C, unless otherwise noted.)

GAIN AND PHASE vs. FREQUENCY



GAIN AND PHASE vs. FREQUENCY (WITH C_{LOAD})



POWER-SUPPLY REJECTION vs. FREQUENCY



OUTPUT IMPEDANCE vs. FREQUENCY



SUPPLY CURRENT PER AMPLIFIER vs. TEMPERATURE



SHUTDOWN SUPPLY CURRENT vs. TEMPERATURE



OUTPUT LEAKAGE CURRENT vs. TEMPERATURE



INPUT BIAS CURRENT vs. COMMON-MODE VOLTAGE



INPUT BIAS CURRENT vs. TEMPERATURE



Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply, Rail-to-Rail I/O Op Amps

Typical Operating Characteristics (continued)

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC} / 2, T_A = +25°C, unless otherwise noted.)

INPUT OFFSET VOLTAGE vs. TEMPERATURE



MINIMUM OPERATING VOLTAGE vs. TEMPERATURE



COMMON-MODE REJECTION vs. TEMPERATURE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. TEMPERATURE



LARGE-SIGNAL GAIN vs. TEMPERATURE



Typical Operating Characteristics (continued)

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC} / 2, T_A = +25°C, unless otherwise noted.)

MINIMUM OUTPUT VOLTAGE vs. TEMPERATURE



MAXIMUM OUTPUT VOLTAGE vs. TEMPERATURE



TOTAL HARMONIC DISTORTION AND NOISE vs. FREQUENCY



TOTAL HARMONIC DISTORTION AND NOISE vs. PEAK-TO-PEAK SIGNAL AMPLITUDE



CHANNEL SEPARATION vs. FREQUENCY



MAX4131 SMALL-SIGNAL TRANSIENT RESPONSE (NONINVERTING)



MAX4131 SMALL-SIGNAL TRANSIENT RESPONSE (INVERTING)



MAX4131 LARGE-SIGNAL TRANSIENT RESPONSE (NONINVERTING)



MAX4131 LARGE-SIGNAL TRANSIENT RESPONSE (INVERTING)



Pin Description

PIN						NAME	FUNCTION
MAX4130	MAX4131		MAX4132	MAX4133	MAX4134		
	SO/µMAX	UCSP					
1	6	A2	—	—	—	OUT	Output
2	4	A1	4	4	11	V_{EE}	Negative Supply. Connect to GND for single-supply operation.
3	3	B1	—	—	—	IN+	Noninverting Input
4	2	B2	—	—	—	IN-	Inverting Input
5	7	A3	8	14	4	V_{CC}	Positive Supply
—	1, 5	—	—	5, 7, 8, 10	—	N.C.	No Connection. Not internally connected.
—	8	B3	—		—	$\overline{SHDN}$	Shutdown Control. Connect to V_{CC} or leave floating to enable amplifier.
—	—	—	1, 7	1, 13	1, 7	OUT1, OUT2	Outputs for Amps 1 and 2
—	—	—	2, 6	2, 12	2, 6	IN1-, IN2-	Inverting Inputs for Amps 1 and 2
—	—	—	3, 5	3, 11	3, 5	IN1+, IN2+	Noninverting Inputs for Amps 1 and 2
—	—	—	—	6, 9	—	$\overline{SHDN1}$, $\overline{SHDN2}$	Shutdown Control. Provides independent shutdown control for amps 1 and 2. Connect to V_{CC} or leave floating to enable amplifiers.
—	—	—	—	—	8, 14	OUT3, OUT4	Outputs for Amps 3 and 4
—	—	—	—	—	9, 13	IN3-, IN4-	Inverting Inputs for Amps 3 and 4
—	—	—	—	—	10, 12	IN3+, IN4+	Noninverting Inputs for Amps 3 and 4



Figure 1a. Reducing Offset Error Due to Bias Current (Noninverting)



Figure 1b. Reducing Offset Error Due to Bias Current (Inverting)

Applications Information

Rail-to-Rail Input Stage

Devices in the MAX4130–MAX4134 family of high-speed amplifiers have rail-to-rail input and output stages designed for low-voltage, single-supply operation. The input stage consists of separate NPN and PNP differential stages that combine to provide an input common-mode range that extends 0.2V beyond the supply rails. The PNP stage is active for input voltages close to the negative rail, and the NPN stage is active for input voltages near the positive rail. The input offset voltage is typically below 200µV. The switchover transition region, which occurs near V_{CC} / 2, has been extended to minimize the slight degradation in common-mode rejection ratio caused by the mismatch of the input pairs. Their low offset voltage, high bandwidth, and rail-to-rail common-mode range make these op amps excellent choices for precision, low-voltage data-acquisition systems.

Since the input stage switches between the NPN and PNP pairs, the input bias current changes polarity as the input voltage passes through the transition region. Reduce the offset error caused by input bias currents flowing through external source impedances by matching the effective impedance seen by each input (Figures 1a, 1b). High source impedances, together with input capacitance, can create a parasitic pole that produces an underdamped signal response. Reducing the input impedance or placing a small (2pF to 10pF) capacitor across the feedback resistor improves response.

The MAX4130–MAX4134s' inputs are protected from large differential input voltages by 1kΩ series resistors and back-to-back triple diodes across the inputs (Figure 2). For differential input voltages less than 1.8V, input resistance is typically 500kΩ. For differential input voltages greater than 1.8V, input resistance is approximately 2kΩ. The input bias current is given by the following equation:

$$I_{BIAS} = \frac{V_{DIFF} - 1.8V}{2k\Omega}$$



Figure 2. Input Protection Circuit

Rail-to-Rail Output Stage

The minimum output voltage is within millivolts of ground for single-supply operation where the load is referenced to ground (V_{EE}). Figure 3 shows the input voltage range and output voltage swing of a MAX4131 connected as a voltage follower. With a +3V supply and the load tied to ground, the output swings from 0.00V to 2.90V. The maximum output voltage swing depends on the load, but will be within 150mV of a +3V supply, even with the maximum load (500Ω to ground).

Driving a capacitive load can cause instability in most high-speed op amps, especially those with low quiescent current. The MAX4130–MAX4134 have a high tolerance for capacitive loads. They are stable with capacitive loads up to 160pF. Figure 4 gives the stable operating region for capacitive loads. Figures 5 and 6 show the response with capacitive loads and the results of adding an isolation resistor in series with the output (Figure 7). The resistor improves the circuit's phase margin by isolating the load capacitor from the op amp's output.



Figure 3. Rail-to-Rail Input/Output Voltage Range



Figure 4. Capacitive-Load Stability



Figure 5. MAX4131 Small-Signal Transient Response with Capacitive Load



Figure 6. MAX4131 Transient Response to Capacitive Load with Isolation Resistor

Power-Up and Shutdown Mode

The MAX4130–MAX4134 amplifiers typically settle within 1µs after power-up. Figures 9 and 10 show the output voltage and supply current on power-up, using the test circuit of Figure 8.

The MAX4131 and MAX4133 have a shutdown option. When the shutdown pin ($\overline{SHDN}$) is pulled low, the supply current drops below 25µA per amplifier and the amplifiers are disabled with the outputs in a high-impedance state. Pulling $\overline{SHDN}$ high or leaving it floating enables the amplifier. In the dual-amplifier MAX4133, the shutdown functions operate independently. Figures 11 and 12 show the output voltage and supply current responses of the MAX4131 to a shutdown pulse, using the test circuit of Figure 8.



Figure 7. Capacitive-Load Driving Circuit



Figure 8. Power-Up/Shutdown Test Circuit



Figure 9. Power-Up Output Voltage



Figure 10. Power-Up Supply Current



Figure 11. Shutdown Output Voltage



Figure 12. Shutdown Enable/Disable Supply Current

Power Supplies and Layout

The MAX4130–MAX4134 operate from a single +2.7V to +6.5V power supply, or from dual supplies of ±1.35V to ±3.25V. For single-supply operation, bypass the power supply with a 0.1µF ceramic capacitor in parallel with at least 1µF. For dual supplies, bypass each supply to ground.

Good layout improves performance by decreasing the amount of stray capacitance at the op amp's inputs and outputs. Decrease stray capacitance by placing external components close to the op amp's pins, minimizing trace lengths and resistor leads.

UCSP Applications Information

For the latest application details on UCSP construction, dimensions, tape carrier information, PC board techniques, bump-pad layout, and the recommended reflow temperature profile, as well as the latest information on reliability testing results, go to Maxim's website at www.maxim-ic.com/ucsp and search for the Application Note: *UCSP–A Wafer-Level Chip-Scale Package*.

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply, Rail-to-Rail I/O Op Amps

Pin Configurations

TOP VIEW



SOT23

TOP VIEW
BUMPS ON BOTTOM



UCSP



SO/μMAX



SO/μMAX



SO



SO

Ordering Information (continued)

PART	TEMP RANGE	PIN-PACKAGE	TOP MARK
MAX4132ESA	-40°C to +85°C	8 SO	—
MAX4132EUA	-40°C to +85°C	8 µMAX	—
MAX4133C/D	0°C to +70°C	Dice*	—
MAX4133ESD	-40°C to +85°C	14 SO	—
MAX4134ESD	-40°C to +85°C	14 SO	—

**Dice are specified at T_A = +25°C, DC parameters only.*

Chip Information

MAX4130 TRANSISTOR COUNT: 170

MAX4131 TRANSISTOR COUNT: 170

MAX4132 TRANSISTOR COUNT: 340

MAX4134 TRANSISTOR COUNT: 680

Package Information

For the latest package outline information and land patterns (footprints), go to **www.maximintegrated.com/packages**. Note that a "+", "#", or "-" in the package code indicates RoHS status only. Package drawings may show a different suffix character, but the drawing pertains to the package regardless of RoHS status.

PACKAGE TYPE	PACKAGE CODE	OUTLINE NO.	LAND PATTERN NO.
5 SOT23	U5-1	21-0057	90-0174
6 UCSP	B6-3	21-0097	Refer to Application Note 1891
8 µMAX	U8-1	21-0036	90-0092
8 S0	S8-2	21-0041	90-0096
14 SO	S14-1	21-0041	90-0012
14 SO	S14M-6	21-0041	90-0012

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply, Rail-to-Rail I/O Op Amps

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	6/96	Initial release	—
1	1/14	Updated *Electrical Characteristics*	2, 4

Maxim Integrated cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim Integrated product. No circuit patent licenses are implied. Maxim Integrated reserves the right to change the circuitry and specifications without notice at any time. The parametric values (min and max limits) shown in the Electrical Characteristics table are guaranteed. Other parametric values quoted in this data sheet are provided for guidance.

© 2014 Maxim Integrated Products, Inc. Maxim Integrated and the Maxim Integrated logo are trademarks of Maxim Integrated Products, Inc.

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А