SP3T SWITCH GaAs MMIC

■ GENERAL DESCRIPTION

The NJG1804K64 is a GaAs SP3T switch MMIC which is suitable for WLAN(802.11a/b/g/n/ac) and Bluetooth applications. This MMIC switches between a common RF port and three RF ports by three control voltages. The NJG1804K64 features very low insertion loss, high isolation at wide frequency range up to 6.0GHz. The ultra small and ultra thin DFN8-64 package is adopted.

■ PACKAGE OUTLINE



NJG1804K64

■ APPLICATION

- 802.11a/b/g/n/ac WLAN applications
- Bluetooth
- General purpose switching applications

■ FEATURES

● Low control voltage	$V_{CTL(H)}$=1.9V to 5.0V
● Low insertion Loss	0.50dB typ. @f=2.4 to 2.5GHz, 0.60dB typ. @f=4.9 to 5.9GHz
● High isolation	30dB typ. @f=2.4 to 2.5GHz, 26dB typ. @f=4.9 to 5.9GHz
● Ultra small & ultra thin package	DFN8-64 (Package size: 1.5 x 1.5 x 0.375mm)
● RoHS compliant and Halogen free, MSL1	

■ PIN CONFIGURATION

(TOP VIEW)



1. PC
2. NC
3. VCTL1
4. P1
5. P2
6. VCTL2
7. VCTL3
8. P3

Exposed pad: GND

■ TRUTH TABLE

"H"=$V_{CTL(H)}$, "L"=$V_{CTL(L)}$

VCTL1	VCTL2	VCTL3	PATH
H	L	L	PC-P1
L	H	L	PC-P2
L	L	H	PC-P3

NOTE: Please note that any data or drawing in this catalog is subject to change.

■ ABSOLUTE MAXIMUM RATINGS

Ta=+25°C

PARAMETER	SYMBOL	CONDITIONS	RATINGS	UNITS
Input power	P_{IN}	$V_{CTL(H)}$=3.3V, $V_{CTL(L)}$=0V, ON state port	+30	dBm
Control voltage	V_{CTL}		5.0	V
Power dissipation	P_D	Four-layer FR4 PCB without through holes (76.2 x 114.3mm), Tj=150°C	380	mW
Operating temperature	T_{opr}		-40 to +105	°C
Storage temperature	T_{stg}		-55 to +150	°C

■ ELECTRICAL CHARACTERISTICS 1 (DC Characteristics)

General conditions: Ta=+25°C, $V_{CTL(H)}$=3.3V, $V_{CTL(L)}$=0V

PARAMETERS	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Control voltage (HIGH)	$V_{CTL(H)}$		1.9	3.3	5.0	V
Control voltage (LOW)	$V_{CTL(L)}$		-0.2	-	0.2	V
Control current	I_{CTL}		-	4	10	μA

■ ELECTRICAL CHARACTERISTICS 2 (RF Characteristics)

General conditions: Ta=+25°C, $V_{CTL(H)}$=3.3V, $V_{CTL(L)}$=0V, Zs=Zl=50Ω

PARAMETERS	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Insertion loss 1	LOSS1	f=2.4GHz to 2.5GHz	-	0.50	0.70	dB
Insertion loss 2	LOSS2	f=4.9GHz to 5.9GHz	-	0.60	0.80	dB
Isolation 1	ISL1	f=2.4GHz to 2.5GHz	27	30	-	dB
Isolation 2	ISL2	f=4.9GHz to 5.9GHz	24	26	-	dB
Input power at 1dB compression point 1	$P_{-1dB}1$	f=2.4GHz to 2.5GHz	+26	+29	-	dBm
Input power at 1dB compression point 2	$P_{-1dB}2$	f=4.9GHz to 5.9GHz	+26	+29	-	dBm
Return loss 1	RL1	f=2.4GHz to 2.5GHz	15	25	-	dB
Return loss 2	RL2	f=4.9GHz to 5.9GHz	15	20	-	dB
Switching time	T_{SW}	50% CTL to 10%/90% RF	-	80	300	ns

■ TERMINAL INFORMATION

No.	SYMBOL	DESCRIPTION
1	PC	Common RF terminal. An external DC blocking capacitor is required.
2	NC	No connected terminal. This terminal is not connected with internal circuit. This terminal please connects to the PCB ground plane or floating.
3	VCTL1	Control voltage input terminal.
4	P1	RF terminal. An external DC blocking capacitor is required.
5	P2	RF terminal. An external DC blocking capacitor is required.
6	VCTL2	Control voltage input terminal.
7	VCTL3	Control voltage input terminal.
8	P3	RF terminal. An external DC blocking capacitor is required.
Exposed Pad	GND	Ground terminal. Connect exposed pad to ground plane as close as possible for excellent RF performance.

■ ELECTRICAL CHARACTERISTICS













■ ELECTRICAL CHARACTERISTICS

Output Power, ICTL vs Input Power



LOSS, ISL vs Input Power



Output Power, ICTL vs Input Power



LOSS, ISL vs Input Power



Switching Time

(PC-P1/P3 path, VCTL1=3.3/0V, VCTL3=0/3.3V, VCTL2=0V)



■ ELECTRICAL CHARACTERISTICS

Output Power, IM3 vs Input Power



IIP3 vs Input Power



EVM vs Input Power(f=2.5GHz)



EVM vs Input Power(f=5.9GHz)



■ ELECTRICAL CHARACTERISTICS

LOSS, ISL vs Temperature

(PC-P1 ON, $V_{CTL(L)}$=0V, f=2.5GHz, P_{IN}=13dBm)



LOSS, ISL vs Temperature

(PC-P1 ON, $V_{CTL(L)}$=0V, f=5.9GHz, P_{IN}=13dBm)



Return Loss vs Temperature

(P1-PC ON, $V_{CTL(L)}$=0V)



Control Current vs Temperature

(P1-PC ON, $V_{CTL(L)}$=0V)



P_{-1dB} vs Temperature

(P1-PC ON, $V_{CTL(L)}$=0V, f=2.5GHz)



Switching Time(rise) vs Temperature

(PC-P1/P3 path, P1 port, $V_{CTL(L)}$=0V)



■ APPLICATION CIRCUIT



■ RECOMMENDED PCB DESIGN



PCB: FR-4, t=0.2mm
Capacitor size: 0603 (0.6 x 0.3 mm)
Strip line width: 0.38mm
PCB size: 25.8 x 25.8mm
Through hole diameter: 0.2mm

■ Losses of PCB, capacitors and connectors

Frequency (GHz)	Loss (dB)
2.4	0.50
2.5	0.52
4.9	0.87
5.9	1.02

NOTE

The bypass capacitors, C5 to C7 are optional, and are recommended only when the control lines are affected under noisy environment.

■ PARTS LIST

No.	Value	Notes
C1 to C4	27pF	Murata MFG (GRM03 series)
C5 to C7	10pF	

■ PCB LAYOUT GUIDELINE

(TOP VIEW)



PRECAUTIONS

[1] The DC blocking capacitors should be placed at RF terminals. Please choose appropriate capacitance value at the application frequency.
[2] If the bypass capacitors (C5 to C7) are needed, they should be placed as close as possible to VCTL terminals.
[3] For good RF performance, exposed pad should be connected to PCB ground plane as close as possible.

■ RECOMMENDED FOOTPRINT PATTERN (8pin DFN Package 1.5x1.5mm) <Reference>

Package: 1.5mm x 1.5mm
Pin pitch: 0.4mm

: Land
: Mask (Open area) *Metal mask thickness: 100um
: Resist (Open area)



■ PACKAGE OUTLINE (DFN8-64)







Unit	: mm
Board	: Copper
Terminal Treat	: Ni/Pd/Au
Molding Material	: Epoxy resin
Weight	: 2.8mg

Cautions on using this product

This product contains Gallium-Arsenide (GaAs) which is a harmful material.

- Do NOT eat or put into mouth.
- Do NOT dispose in fire or break up this product.
- Do NOT chemically make gas or powder with this product.
- To waste this product, please obey the relating law of your country.

This product may be damaged with electric static discharge (ESD) or spike voltage. Please handle with care to avoid these damages.

[CAUTION]
The specifications on this databook are only given for information , without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

NJR:

NJG1804K64

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А