GM6603

3.0A LOW DROPOUT PRECISION LINEAR REGULATORS

Description

GM6603 of positive adjustable and fixed regulators are designed to provide 3.0A output with low dropout voltage performance.

On-chip trimming adjusts the reference voltage to 2.0%. To work in post regulators or microprocessor power supplies where low voltage operation and fast transient response are required.

Device includes over-current protection and thermal shutdown protection as well.

Pin-to-pin compatible with LT1085 family of regulators, GM6603 is available in TO-252, TO-220, and surface-mount TO-263 packages.

Features


- **Adjustable or Fixed Output**
- **Output Current of 3.0A**
- **Dropout Voltage (typical) 1.15V @ 3.0A**
- **Typical Line Regulation 0.04%**
- **Typical Load Regulation 0.2%**
- **Fast Transient Response**
- **Current Limit Protection**
- **Thermal Shutdown Protection**

Application

Microprocessor Supply
Post Regulators for Switching Supplies
Telecommunication Systems
Printer Supplies
Motherboards


TYPICAL APPLICATION CIRCUITS

(Adjustable Version)



$$V_{OUT} = V_{REF} \times (1 + \frac{R2}{R1}) + I_{ADJ} \times R2$$


(Fixed Version)




Notes:
1. C1 needed if device is far from filter capacitors
2. C2 minimum value required for stability

◆ MARKING INFORMATION & PIN CONFIGURATIONS(Top View)


TO-252(DPAK)



TO-220



TO-263-2 (D^2PAK)



V V, V = Output Voltage(A =Adj,33 = 3.3V)
A = Assembly Location
Y = Year
W W = Weekly

* On fixed versions Pin 1 = GND, on adjustable versions Pin 1 = ADJ
* Tab = V_{OUT}

◆ ORDERING INFORMATION

Ordering Number	Output Voltage	Package	Shipping
GM6603-ATA3T	Adj	TO-263-2	50 Units/ Tube
GM6603-ATA3R	Adj	TO-263-2	800 Units/ Tape&Reel
GM6603-ATC3T	Adj	TO-252	80 Units/ Tube
GM6603-ATC3R	Adj	TO-252	2,500 Units/ Tape & Reel
GM6603-ATB3T	Adj	TO-220	50 Units/ Tube
GM6603-1.5TA3T	1.5	TO-263-2	50 Units/ Tube
GM6603-1.5TA3R	1.5	TO-263-2	800 Units/ Tape&Reel
GM6603-1.5TB3T	1.5	TO-220	50 Units/ Tube
GM6603-1.8TA3T	1.8	TO-263-2	50 Units/ Tube
GM6603-1.8TA3R	1.8	TO-263-2	800 Units/ Tape&Reel
GM6603-1.8TC3T	1.8	TO-252	80 Units/ Tube
GM6603-1.8TC3R	1.8	TO-252	2,500 Units/ Tape & Reel
GM6603-1.8TB3T	1.8	TO-220	50 Units/ Tube
GM6603-2.5TA3T	2.5	TO-263-2	50 Units/ Tube
GM6603-2.5TA3R	2.5	TO-263-2	800 Units/ Tape&Reel
GM6603-2.5TB3T	2.5	TO-220	50 Units/ Tube
GM6603-2.85TA3T	2.85	TO-263-2	50 Units/ Tube
GM6603-2.85TA3R	2.85	TO-263-2	800 Units/ Tape&Reel
GM6603-2.85TB3T	2.85	TO-220	50 Units/ Tube
GM6603-3.0TA3T	3.0	TO-263-2	50 Units/ Tube
GM6603-3.0TA3R	3.0	TO-263-2	800 Units/ Tape&Reel
GM6603-3.0TC3T	3.0	TO-252	80 Units/ Tube
GM6603-3.0TC3R	3.0	TO-252	2,500 Units/ Tape & Reel
GM6603-3.0TB3T	3.0	TO-220	50 Units/ Tube

* For detail Ordering Number identification, please see last page.

◆ ORDERING INFORMATION (Continued)

Ordering Number	Output Voltage	Package	Shipping
GM6603-3.3TA3T	3.3	TO-263-2	50 Units/ Tube
GM6603-3.3TA3R	3.3	TO-263-2	800 Units/ Tape &Reel
GM6603-3.3TC3T	3.3	TO-252	80 Units/ Tube
GM6603-3.3TC3R	3.3	TO-252	2,500 Units/ Tape & Reel
GM6603-3.3TB3T	3.3	TO-220	50 Units/ Tube
GM6603-5.0TA3T	5.0	TO-263-2	50 Units/ Tube
GM6603-5.0TA3R	5.0	TO-263-2	800 Units/ Tape &Reel
GM6603-5.0TC3T	5.0	TO-252	80 Units/ Tube
GM6603-5.0TC3R	5.0	TO-252	2,500 Units/ Tape & Reel
GM6603-5.0TB3T	5.0	TO-220	50 Units/ Tube


* For detail Ordering Number identification, please see last page.

◆ ABSOLUTE MAXIMUM RATINGS


PARAMETER	SYMBOL	VALUE	UNIT
Power Dissipation	P_D	Internally limited	W
Input Voltage	V_{IN}	15	V
Operating Junction Temperature Range Control Section Power Transistor	T_J	 0 to 125 0 to 150	°C
Lead Temperature(Soldering, 10sec)	T_{LEAD}	300	°C
Storage Temperature Range	T_{STG}	-65 to + 150	°C

BLOCK DIAGRAM

(Adjustable Version)



(Fixed Version)



◆ ELECTRICAL CHARACTERISTICS

(Typicals and limits appearing in normal type apply for T_J = 25°C)

Parameter		Symbol	Condition	Min	Typ	Max	Unit
Reference Voltage	GM6603-Adj	V_{REF}	I_{OUT}=10mA, V_{IN}-V_{OUT}=1.5V 10mA ≤ I_{OUT} ≤ 3A, 3.3V ≤ V_{IN} ≤ 7V	1.238 1.230	1.250 1.250	1.262 1.270	V
Output Voltage	GM6603-1.8	V_O	I_{OUT}=10mA, V_{IN}=3.3V 10mA ≤ I_{OUT} ≤ 3A, 3.3V ≤ V_{IN} ≤ 7V	1.782 1.764	1.800 1.800	1.818 1.836	V
	GM6603-2.5		I_{OUT}=10mA, V_{IN}=4V 10mA ≤ I_{OUT} ≤ 3A, 4V ≤ V_{IN} ≤ 7V	2.475 2.450	2.500 2.500	2.525 2.550	V
	GM6603-3.3		I_{OUT}=10mA, V_{IN}=4.8V 10mA ≤ I_{OUT} ≤ 3A, 4.8V ≤ V_{IN} ≤ 7V	3.267 3.234	3.300 3.300	3.333 3.366	V
	GM6603-5.0		I_{OUT}=10mA, V_{IN}=6.5V 10mA ≤ I_{OUT} ≤ 3A, 6.5V ≤ V_{IN} ≤ 7V	4.950 4.900	5.000 5.000	5.050 5.100	V
Line Regulation	GM6603-Adj	REG_{LINE}	I_{OUT}=10mA,		0.04	0.20	%
	GM6603-1.8		I_{OUT}=10mA, 3.3V ≤ V_{IN} ≤ 7V		0.04	0.20	
	GM6603-2.5		I_{OUT}=10mA, 4V ≤ V_{IN} ≤ 7V		0.04	0.20	
	GM6603-3.3		I_{OUT}=10mA, 4.8V ≤ V_{IN} ≤ 7V		0.04	0.20	
	GM6603-5.0		I_{OUT}=10mA, 6.5V ≤ V_{IN} ≤ 7V		0.04	0.20	
Load Regulation	GM6603-Adj	REG_{LOAD}	V_{IN}-V_{OUT}=1.5V, 10mA ≤ I_O ≤ 3A		0.2	0.40	%
	GM6603-1.8		V_{IN}=3.8V, 10mA ≤ I_O ≤ 3A		0.2	0.40	
	GM6603-2.5		V_{IN}=4.5V, 10mA ≤ I_O ≤ 3A		0.2	0.40	
	GM6603-3.3		V_{IN}=5.3V, 10mA ≤ I_O ≤ 3A		0.2	0.40	
	GM6603-5.0		V_{IN}=7V, 10mA ≤ I_O ≤ 3A		0.2	0.40	
Dropout Voltage		V_D	I_{OUT}=3A		1.15	1.3	V
Current Limit		I_{CL}	V_{IN}-V_{OUT}=3V	3	4		A
Minimum Load Current	GM6603-Adj	$I_{O\ MIN}$	V_{IN}=5V		1.7	5	mA
Quiescent Current	GM6603-1.8	I_Q	V_{IN}=3.3V, 10mA ≤ I_O ≤ 3A		5	10	mA
	GM6603-2.5		V_{IN}=4.0V, 10mA ≤ I_O ≤ 3A		5	10	
	GM6603-3.3		V_{IN}=4.8V, 10mA ≤ I_O ≤ 3A		5	10	
	GM6603-5.0		V_{IN}=6.5V, 10mA ≤ I_O ≤ 3A		5	10	
Adjust Pin Current	GM6603-Adj	I_{ADJ}	I_{OUT}=10mA, 2.65V ≤ V_{IN} ≤ 7V		55	90	μA
Temperature Coefficient		T_C	V_{IN}-V_{OUT}=1.5V, I_{OUT}=10mA		0.005		%/°C
Ripple Rejection		R_A	V_{IN}-V_{OUT}=1.5V, I_{OUT}=3A	60	72		dB

◆ APPLICATION INFORMATION

GM6603 series linear regulators provide fixed and adjustable output voltages at currents up to 3.0A. These regulators are protected against over current conditions and include thermal shutdown protection. GM6603 has a composite PNP-PN output transistor and require an output capacitor for stability.

A detailed procedure for selecting this capacitor is as followed.

Stability Considerations

The output compensation capacitor helps to determine three main characteristics of a linear regulator's performance: start-up delay, load transient response, and loop stability. The capacitor value and type is based on cost, availability, size, and temperature constraints. A tantalum or aluminum electrolytic capacitor is preferred, as a film or ceramic capacitor with almost zero ESR can cause instability. An aluminum electrolytic capacitor is the least expensive type. But when the circuit operates at low temperatures, both the value and ESR of the capacitor will vary widely. For optimum performance over the full operating temperature range, a tantalum capacitor is the best. A 22μF tantalum capacitor will work fine in most applications. But with high current regulators, such as GM6603 higher capacitance values will improve the transient response and stability. Most applications for the GM6603's involve large changes in load current, so the output capacitor must supply instantaneous load current. The ESR of the output capacitor causes an immediate drop in output voltage given by:

$$V = I \times ESD$$


In microprocessor applications an output capacitor network of several tantalum and ceramic capacitors in parallel is commonly used. This reduces overall ESR and minimizes the instantaneous output voltage drop under transient load conditions. The output capacitor network should be placed as close to the load as possible for the best results.

Protection Diodes


When large external capacitors are used with most linear regulator, it is wise to add protection diodes. If the input voltage of the regulator is shorted, the output capacitor will discharge into the output of the regulator. The discharge current depends on the value of capacitor, output voltage, and rate at which V_{IN} drops.

FIGURE 1 [(a),(b)]. Protection Diode Scheme for Large Output Capacitors

(a) Fixed Version



(b) Adjustable Version



In GM6603 linear regulators, the discharge path is through a large junction, and protection diodes are normally not needed. However, if the regulator is used with large output capacitance values and the input voltage is instantaneously shorted to ground, damage can occur. In this case, a diode connected as shown above in Figure 1.

Output Voltage Sensing

GM6603 series is three terminal regulator, so they cannot provide true remote load sensing. Load regulation is limited by the resistance of the conductors connecting the regulator to the load. For best results, GM6603 should be connected as shown in Figure 2.




FIGURE 2 [(a),(b)] Conductor Parasitic Resistance Effects are Minimized by this Grounding Scheme For Fixed and Adjustable Output Regulators

Calculating Power Dissipation and Heat Sink Requirements

GM6603 series precision linear regulators include thermal shutdown and current limit circuitry to protect the devices. However, high power regulators normally operate at high junction temperatures so it is important to calculate the power dissipation and junction temperatures accurately to be sure that you use and adequate heat sink. The case is connected to V_{OUT} on GM6603 so electrical isolation may be required for some applications. Thermal compound should always be used with high current regulators like the GM6603.

The thermal characteristics of an IC depend on four factors:
1. Maximum Ambient Temperature T_A (°C)
2. Power Dissipation P_D (Watts)
3. Maximum Junction Temperature T_J (°C)
4. Thermal Resistance Junction to ambient R_{JA} (°C/W)

These relationship of these four factors is expressed by equation (1):

$$T_J = T_A + P_D \text{ X } R_{JA}$$

Maximum ambient temperature and power dissipation are determined by the design while the maximum junction temperature and thermal resistance depend on the manufacturer and the package type.

The maximum power dissipation for a regulator is expressed by equation (2):

$$P_{D(max)}=\{V_{IN(max)}-V_{OUT(min)}\} I_{OUT(max)} + V_{IN(max)}I_Q$$

where:
$V_{IN(max)}$ is the maximum input voltage,
$V_{OUT(min)}$ is the minimum output voltage,
$I_{OUT(max)}$ is the maximum output current
I_Q is the maximum quiescent current at $I_{OUT(max)}$.

A heat sink effectively increases the surface area of the package to improve the flow of heat away from the IC into the air. Each material in the heat flow path between the IC and the environment has a thermal resistance. Like series electrical resistances, these resistances are summed to determine R_{JA}, the total thermal resistance between the junction and the air. This is expressed by equation (3):

$$R_{JA} = R_{JC} + R_{CS} + R_{SA}$$

Where all of the following are in °C/W:
R_{JC} is thermal resistance of junction to case,
R_{CS} is thermal resistance of case to heat sink,
R_{SA} is thermal resistance of heat sink to ambient air

The value for R_{JA} is calculated using equation (3) and the result can be substituted in equation (1). The value for R_{JC} is 3.5°C/W for a given package type based on an average die size. For a high current regulator such as GM6603, the majority of the heat is generated in the power transistor section.

◆ Typical Performance Characteristics




Figure 3. Dropout Voltage vs. Output Current




Figure 4. Bandgap Reference Voltage Deviation vs. Temperature




Figure 5. Ripple Rejection vs. Frequency






Figure 6. Minimum Load Current vs. V_{IN} - $V_{OUT(V)}$

◆ TO-220 PACKAGE OUTLINE DIMENSIONS




Unit: mm

◆ TO-263-2 PACKAGE OUTLINE DIMENSIONS




Unit: mm

◆ TO-252 PACKAGE OUTLINE DIMENSIONS



◆ ORDERING NUMBER



GAMMA Micro, and are registered trademarks of GAMMA MICROELECTRONICS INC. GAMMA reserves the right to make changes without further notice to any products herein.

Information provided herein is alleged to be exact and consistent and this publication surpasses and replaces all information previously supplied.

GAMMA makes no warranty the suitability of its products for any particular purpose, nor does GAMMA assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability including without limitation special, consequential or incidental damages.

GAMMA products are not authorized for using as critical components in life support devices or systems without prior written approval from GAMMA MICROELECTRONICS INC.

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А