19-1087; Rev 1; 8/97

MAXIM

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply Rail-to-Rail I/O Op Amps

General Description

The MAX4122–MAX4129 family of operational amplifiers combines wide bandwidth and excellent DC accuracy with Rail-to-Rail® operation at the inputs and outputs. These devices require only 650µA per amplifier, and operate from either a single supply (+2.7V to +6.5V) or dual supplies (±1.35V to ±3.25V) with a common-mode voltage range that extends 250mV beyond V_{EE} and V_{CC}. They are capable of driving 250Ω loads. The MAX4122/MAX4123/MAX4126/MAX4127/MAX4129 have a 5MHz gain bandwidth product, while the decompensated MAX4124/MAX4125/MAX4128 (stable at closed-looped gains of 10 or greater) have a 25MHz gain bandwidth product. In addition, the MAX4123/MAX4125/MAX4127 feature a shutdown mode in which the outputs are placed in a high-impedance state and the supply current is reduced to only 25µA per amplifier.

With their rail-to-rail input common-mode range and output swing, these amplifiers are ideal for low-voltage single-supply operation. Although the minimum operating voltage is specified at 2.7V, the devices typically operate down to 1.8V. In addition, low offset voltage and high speed make them the ideal signal-conditioning stages for precision, low-voltage, data-acquisition systems. **The MAX4122 and MAX4124 come in the space-saving 5-pin SOT23-5 package.**

Applications

Battery-Powered Instruments

Portable Equipment

Data-Acquisition Systems

Signal Conditioning

Low-Power, Low-Voltage Applications

Selection Table

PART	BW (MHz)	AMPS PER PKG.	SHUT-DOWN MODE	PIN-PACKAGE
MAX4122	5	1	—	5 SOT23-5
MAX4123	5	1	Yes	8 SO/µMAX
MAX4124	25	1	—	5 SOT23-5
MAX4125	25	1	Yes	8 SO/µMAX
MAX4126	5	2	—	8 SO/µMAX
MAX4127	5	2	Yes	14 SO
MAX4128	25	2	—	8 SO/µMAX
MAX4129	5	4	—	14 SO

Rail-to-Rail is a registered trademark of Nippon Motorola, Ltd.

Features

- ♦ **5-Pin SOT23 Package (MAX4122/4)**
- ♦ **+2.7V to +6.5V Single-Supply Operation**
- ♦ **Rail-to-Rail Input Common-Mode Voltage Range**
- ♦ **Rail-to-Rail Output Voltage Swing**
- ♦ **5MHz Gain-Bandwidth Product (MAX4122/3/6/7/9)**
  25MHz Gain-Bandwidth Product (MAX4124/5/8)
- ♦ **650µA Quiescent Current per Amplifier**
- ♦ **25µA Shutdown Function (MAX4123/5/7)**
- ♦ **200µV Offset Voltage**
- ♦ **No Phase Reversal for Overdriven Inputs**
- ♦ **Drive 250Ω Loads**
- ♦ **Stable with 500pF Capacitive Loads**
- ♦ **Unity-Gain Stable (MAX4122/3/6/7/9)**
  Stable at Gains ≥ 10V/V (MAX4124/5/8)

Ordering Information

PART	TEMP. RANGE	PIN-PACKAGE	MARKING INFO.
MAX4122EUK	-40°C to +85°C	5 SOT23-5	AAAZ
MAX4123C/D	0°C to +70°C	Dice*	—
MAX4123ESA	-40°C to +85°C	8 SO	—
MAX4123EUA	-40°C to +85°C	8 µMAX	—

Ordering Information continued at end of data sheet.

**Dice are specified at T_A = +25°C, DC parameters only.*

Pin Configurations appear at end of data sheet.

Typical Operating Circuit



For free samples & the latest literature: http://www.maxim-ic.com, or phone 1-800-998-8800.
For small orders, phone 408-737-7600 ext. 3468.

ABSOLUTE MAXIMUM RATINGS

Supply Voltage (V_{CC}-V_{EE}).....7.5V
IN+, IN-, $\overline{SHDN}$ Voltage .....(V_{CC} + 0.3V) to (V_{EE} - 0.3V)
Output Short-Circuit Duration (Note 1).....Continuous
(short to either supply)
Continuous Power Dissipation (T_A = +70°C)
5-pin SOT23-5 (derate 7.1mW/°C above +70°C) 571mW
8-pin SO (derate 5.88mW/°C above +70°C).....471mW
8-pin µMAX (derate 4.10mW/°C above +70°C) 330mW
14-pin SO (derate 8.00mW/°C above +70°C).....640mW

Operating Temperature Range
MAX412_E__ .....-40°C to +85°C
Maximum Junction Temperature .....+150°C
Storage Temperature Range .....-65°C to +160°C
Lead Temperature (soldering, 10sec) .....+300°C

Note 1: Provided that the maximum package power-dissipation rating is met.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

DC ELECTRICAL CHARACTERISTICS

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = +25°C**, unless otherwise noted.)

PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
Input Offset Voltage	V_{CM} = V_{EE} to V_{CC}	MAX4123ESA/MAX4125ESA		±0.20	±0.60	mV
		MAX4122EUK/MAX4124EUK		±0.35	±1.50	
		MAX4123EUA/MAX4125EUA		±0.35	±1.20	
		MAX4126ESA/MAX4127ESD/MAX4128ESA		±0.25	±0.75	
		MAX4126EUA/MAX4128EUA		±0.40	±1.50	
		MAX4129ESD		±0.35	±1.50	
Input Bias Current	V_{CM} = V_{EE} to V_{CC}			±50	±150	nA
Input Offset Current	V_{CM} = V_{EE} to V_{CC}			±1	±12	nA
Differential Input Resistance	-1.5V < V_{DIFF} < 1.5V			500		kΩ
Common-Mode Input Voltage Range			V_{EE} - 0.25		V_{CC} + 0.25	V
Common-Mode Rejection Ratio	(V_{EE} - 0.25) < V_{CM} < (V_{CC} + 0.25V)	MAX4123ESA/MAX4125ESA	78	98		dB
		MAX4122EUK/MAX4124EUK	67	90		
		MAX4123EUA/MAX4125EUA	68	88		
		MAX4126ESA/MAX4127ESD/MAX4128ESA	74	94		
		MAX4126EUA/MAX4128EUA	66	86		
		MAX4129ESD	64	84		
Power-Supply Rejection Ratio	V_{CC} = 2.7V to 6.5V		78	100		dB
Output Resistance	A_V = 1			0.1		Ω
Off-Leakage Current	$\overline{SHDN}$ < 0.8V, V_{OUT} = 0V to V_{CC}			±0.1	±1	µA
Large-Signal Voltage Gain	V_{CC} = 2.7V	V_{OUT} = 0.25V to 2.45V, R_L = 100kΩ	92	104		dB
		V_{OUT} = 0.4V to 2.3V, R_L = 250Ω	72	80		
	V_{CC} = 5V	V_{OUT} = 0.25V to 4.75V, R_L = 100kΩ	94	106		
		V_{OUT} = 0.4V to 4.6V, R_L = 250Ω	75	84		

DC ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = +25°C**, unless otherwise noted.)

PARAMETER	CONDITIONS			MIN	TYP	MAX	UNITS
Output Voltage Swing	MAX4122/ MAX4123/ MAX4124/ MAX4125	R_L = 100kΩ	V_{CC} - V_{OH}		12	20	mV
			V_{OL} - V_{EE}		20	35	
		R_L = 250Ω	V_{CC} - V_{OH}		240	290	
			V_{OL} - V_{EE}		125	170	
	MAX4126/ MAX4127/ MAX4128/ MAX4129	R_L = 100kΩ	V_{CC} - V_{OH}		15	30	
			V_{OL} - V_{EE}		25	40	
		R_L = 250Ω	V_{CC} - V_{OH}		280	330	
			V_{OL} - V_{EE}		180	230	
Output Short-Circuit Current					50		mA
$\overline{SHDN}$ Logic Threshold	MAX4123/MAX4125/MAX4127		Low			0.8	V
			High	2.0			
$\overline{SHDN}$ Input Current	MAX4123/MAX4125/MAX4127				±1	±3	µA
Operating Supply-Voltage Range				2.7		6.5	V
Supply Current per Amplifier	V_{CM} = V_{OUT} = V_{CC}/2		V_{CC} = 2.7V		650	750	µA
			V_{CC} = 5V		725	825	
Shutdown Supply Current per Amplifier	$\overline{SHDN}$ > 0.8V, MAX4123/MAX4125/MAX4127		V_{CC} = 2.7V		25	40	µA
			V_{CC} = 5V		40	60	

DC ELECTRICAL CHARACTERISTICS

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = -40°C to +85°C**, unless otherwise noted.)

PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
Input Offset Voltage	V_{CM} = V_{EE} to V_{CC}	MAX4123ESA/MAX4125ESA			±0.75	mV
		MAX4122EUK/MAX4124EUK			±3.50	
		MAX4123EUA/MAX4125EUA			±4.40	
		MAX4126ESA/MAX4127ESD/MAX4128ESA			±0.95	
		MAX4126EUA/MAX4128EUA			±4.70	
		MAX4129ESD			±4.00	
Input Offset Voltage Tempco				±2		µV/°C
Input Bias Current	V_{CM} = V_{EE} to V_{CC}				±160	nA
Input Offset Current	V_{CM} = V_{EE} to V_{CC}				±18	nA
Common-Mode Input Voltage Range			V_{EE} - 0.20		V_{CC} + 0.20	V
Common-Mode Rejection Ratio	(V_{EE} - 0.2V) < V_{CM} < (V_{CC} + 0.2V)	MAX4123ESA/MAX4125ESA	76			dB
		MAX4122EUK/MAX4124EUK	62			
		MAX4123EUA/MAX4125EUA	60			
		MAX4126ESA/MAX4127ESD/MAX4128ESA	74			
		MAX4126EUA/MAX4128EUA	58			
		MAX4129ESD	60			

DC ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, V_{CM} = 0V, V_{OUT} = V_{CC}/2, R_L tied to V_{CC}/2, $\overline{SHDN}$ ≥ 2V (or open), **T_A = -40°C to +85°C**, unless otherwise noted.)

PARAMETER	CONDITIONS			MIN	TYP	MAX	UNITS
Power-Supply Rejection Ratio	V_{CC} = 2.7V to 6.5V			74			dB
Off-Leakage Current	$\overline{SHDN}$ < 0.8V, V_{OUT} = 0V to V_{CC}					±12	µA
Large-Signal Voltage Gain	V_{CC} = 2.7V	V_{OUT} = 0.25V to 2.45V, R_L = 100kΩ		84			dB
		V_{OUT} = 0.4V to 2.3V, R_L = 250Ω		66			
	V_{CC} = 5V	V_{OUT} = 0.25V to 4.75V, R_L = 100kΩ		86			
		V_{OUT} = 0.4V to 4.6V, R_L = 250Ω		68			
Output Voltage Swing	MAX4122/ MAX4123/ MAX4124/ MAX4125	R_L = 100kΩ	V_{CC} - V_{OH}			25	mV
			V_{OL} - V_{EE}			40	
		R_L = 250Ω	V_{CC} - V_{OH}			300	
			V_{OL} - V_{EE}			190	
	MAX4126/ MAX4127/ MAX4128/ MAX4129	R_L = 100kΩ	V_{CC} - V_{OH}			35	
			V_{OL} - V_{EE}			50	
		R_L = 250Ω	V_{CC} - V_{OH}			350	
			V_{OL} - V_{EE}			250	
$\overline{SHDN}$ Logic Threshold	MAX4123/MAX4125/MAX4127		Low			0.8	V
			High	2.0			
$\overline{SHDN}$ Input Current	MAX4123/MAX4125/MAX4127					±3	µA
Operating Supply-Voltage Range				2.7		6.5	V
Supply Current per Amplifier	V_{CM} = V_{OUT} = V_{CC}/2		V_{CC} = 2.7V			775	µA
			V_{CC} = 5V			850	
Shutdown Supply Current per Amplifier	$\overline{SHDN}$ < 0.8V, MAX4123/MAX4125/MAX4127		V_{CC} = 2.7V			50	µA
			V_{CC} = 5V			70	

AC ELECTRICAL CHARACTERISTICS

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, $\overline{SHDN}$ ≥ 2V (or open), **T_A = +25°C**, unless otherwise noted.)

PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
Gain-Bandwidth Product	MAX4122/23/26/27/29		5		MHz
	MAX4124/25/28 (A_V ≥ 10)		25		
Phase Margin	MAX4122/23/26/27/29		64		degrees
	MAX4124/25/28 (A_V ≥ 10)		60		
Gain Margin	MAX4122/23/26/27/29		12		dB
	MAX4124/25/28 (A_V ≥ 10)		10		
Total Harmonic Distortion	f = 10kHz, V_{OUT} = 2Vp-p, MAX4122/23/26/27/29 (A_V = 1)		0.003		%
Slew Rate	MAX4122/23/26/27/29		2		V/µs
	MAX4124/25/28 (A_V ≥ 10)		10		
Settling Time to 0.01%	MAX4122/23/26/27/29 (A_V = 1), V_{OUT} = 2V step		2.0		µs
	MAX4124/25/28 (A_V ≥ 10), V_{OUT} = 2V step		1.3		
Turn-On Time	V_{CC} = 0V to 3V step, V_{OUT} = V_{CC}/2		1		µs

AC ELECTRICAL CHARACTERISTICS (continued)

(V_{CC} = +2.7V to +6.5V, V_{EE} = 0V, $\overline{SHDN}$ ≥ 2V (or open), **T_A = +25°C**, unless otherwise noted.)

PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
$\overline{SHDN}$ Delay	V_{CC} = 3V, V_{OUT} = V_{CC}/2, MAX4123/25/27	Enable		1		µs
		Disable		0.2		
Input Capacitance				3		pF
Input Noise Voltage Density	f = 1kHz			22		nV/√Hz
Input Noise Current Density	f = 1kHz			0.4		pA/√Hz
Amp-Amp Isolation	MAX4126/27/28/29			135		dB
Capacitive Load Stability	MAX4122/23/26/27/29 (A_V = 1)			500		pF
	MAX4124/25/28 (A_V ≥ 10)			500		

Typical Operating Characteristics

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC}/2, T_A = +25°C, unless otherwise noted.)

MAX4322/26/29
GAIN AND PHASE vs. FREQUENCY



MAX4122/23/26/27/29
GAIN AND PHASE vs. FREQUENCY
(WITH C_{LOAD})



MAX4122/23/26/27/29
POWER-SUPPLY REJECTION
vs. FREQUENCY



MAX4124/25/28
GAIN AND PHASE vs. FREQUENCY



MAX4124/25/28
GAIN AND PHASE vs. FREQUENCY
(WITH C_{LOAD})



MAX4124/25/28
POWER-SUPPLY REJECTION
vs. FREQUENCY



Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply Rail-to-Rail I/O Op Amps

Typical Operating Characteristics (continued)

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC}/2, T_A = +25°C, unless otherwise noted.)

MAX4126/27/28/29
CHANNEL SEPARATION vs. FREQUENCY



MAX4122/23/26/27/29
OUTPUT IMPEDANCE
vs. FREQUENCY



MAX4124/25/28
OUTPUT IMPEDANCE
vs. FREQUENCY



SUPPLY CURRENT PER AMPLIFIER
vs. TEMPERATURE



MAX4323/MAX4327
SHUTDOWN SUPPLY CURRENT
vs. TEMPERATURE



OUTPUT LEAKAGE CURRENT
vs. TEMPERATURE



INPUT OFFSET VOLTAGE
vs. TEMPERATURE



INPUT BIAS CURRENT
vs. COMMON-MODE VOLTAGE



INPUT BIAS CURRENT
vs. TEMPERATURE



Typical Operating Characteristics (continued)

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC}/2, T_A = +25°C, unless otherwise noted.)

COMMON-MODE REJECTION vs. TEMPERATURE



MINIMUM OUTPUT VOLTAGE vs. TEMPERATURE



MAXIMUM OUTPUT VOLTAGE vs. TEMPERATURE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. TEMPERATURE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. OUTPUT VOLTAGE



LARGE-SIGNAL GAIN vs. TEMPERATURE



Typical Operating Characteristics (continued)

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC}/2, T_A = +25°C, unless otherwise noted.)

MAX4123
MINIMUM OPERATING VOLTAGE vs. TEMPERATURE



MAX4122/23/26/27/29 TOTAL HARMONIC DISTORTION AND NOISE vs. FREQUENCY



MAX4123
TOTAL HARMONIC DISTORTION AND NOISE vs. PEAK-TO-PEAK SIGNAL AMPLITUDE



MAX4122/23/26/27/29
SMALL-SIGNAL TRANSIENT RESPONSE (NONINVERTING)



MAX4122/23/26/27/29
SMALL-SIGNAL TRANSIENT RESPONSE (INVERTING)



MAX4122/23/26/27/29
LARGE-SIGNAL TRANSIENT RESPONSE (NONINVERTING)



MAX4122/23/26/27/29
LARGE-SIGNAL TRANSIENT RESPONSE (INVERTING)



MAX4124/25/28
SMALL-SIGNAL TRANSIENT RESPONSE (NONINVERTING)



MAX4124/25/28
SMALL-SIGNAL TRANSIENT RESPONSE (INVERTING)



Typical Operating Characteristics (continued)

(V_{CC} = +5V, V_{EE} = 0V, V_{CM} = V_{CC}/2, T_A = +25°C, unless otherwise noted.)

MAX4124/25/28
LARGE-SIGNAL TRANSIENT
RESPONSE (NONINVERTING)



MAX4124/25/28
LARGE-SIGNAL TRANSIENT
RESPONSE (INVERTING)



Pin Description

PIN					NAME	FUNCTION
MAX4122 MAX4124	MAX4123 MAX4125	MAX4126 MAX4128	MAX4127	MAX4129		
1	6	—	—	—	OUT	Output
2	4	4	4	11	V_{EE}	Negative Supply. Ground for single-supply operation.
3	3	—	—	—	IN+	Noninverting Input
4	2	—	—	—	IN-	Inverting Input
5	7	8	14	4	V_{CC}	Positive Supply
—	1, 5	—	5, 7, 8, 10	—	N.C.	No Connect
—	8	—	—	—	$\overline{SHDN}$	Shutdown Control. Tie high or leave floating to enable amplifier.
—	—	1, 7	1, 13	1, 7	OUT1, OUT2	Outputs for Amps 1 and 2
—	—	2, 6	2, 12	2, 6	IN1-, IN2-	Inverting Inputs for Amps 1 and 2
—	—	3, 5	3, 11	3, 5	IN1+, IN2+	Noninverting Inputs for Amps 1 and 2
—	—	—	6, 9	—	$\overline{SHDN1}$, $\overline{SHDN2}$	Shutdown Control for Amps 1 and 2. Tie high or leave floating to enable amplifier.
—	—	—	—	8, 14	OUT3, OUT4	Outputs for Amps 3 and 4
—	—	—	—	9, 13	IN3-, IN4-	Inverting Inputs for Amps 3 and 4
—	—	—	—	10, 12	IN3+, IN4+	Noninverting Inputs for Amps 3 and 4



Figure 1a. Reducing Offset Error Due to Bias Current (Noninverting)



Figure 1b. Reducing Offset Error Due to Bias Current (Inverting)



Figure 2. Input Protection Circuit

Applications Information

Rail-to-Rail Input Stage

Devices in the MAX4122–MAX4129 family of high-speed amplifiers have rail-to-rail input and output stages designed for low-voltage single-supply operation. The input stage consists of separate NPN and PNP differential stages, which combine to provide an input common-mode range extending 0.2V beyond the supply rails. The PNP stage is active for input voltages close to the negative rail, and the NPN stage is active for input voltages near the positive rail. The input offset voltage is typically below 200µV. The switchover transition region, which occurs near $V_{CC}/2$, has been extended to minimize the slight degradation in CMRR caused by the mismatch of the input pairs. Their low offset voltage, high bandwidth, and rail-to-rail common-mode range make these op amps excellent choices for precision low-voltage data-acquisition systems.

Since the input stage switches between the NPN and PNP pairs, the input bias current changes polarity as the input voltage passes through the transition region. To reduce the offset error caused by input bias currents flowing through external source impedances, match the effective impedance seen by each input (Figures 1a, 1b). High source impedances, together with the input capacitance, can create a parasitic pole that produces an underdamped signal response. Reducing the input impedance or placing a small (2pF to 10pF) capacitor across the feedback resistor improves the response.

The MAX4122–MAX4129's inputs are protected from large differential input voltages by 1kΩ series resistors and back-to-back triple diodes across the inputs (Figure 2). For differential input voltages less than 1.8V the input resistance is typically 500kΩ. For differential input voltages greater than 1.8V the input resistance is approximately 2kΩ, and the input bias current is determined by the following equation:

$$I_{BIAS} = \frac{V_{DIFF} - 1.8V}{2k\Omega}$$

Rail-to-Rail Output Stage

The minimum output voltage will be within millivolts of ground for single-supply operation where the load is referenced to ground (V_{EE}). Figure 3 shows the input voltage range and output voltage swing of a MAX4123 connected as a voltage follower. With a +3V supply and the load tied to ground, the output swings from 0.00V to 2.90V. The maximum output voltage swing depends on the load, but will be within 150mV of a +3V supply, even with the maximum load (500Ω to ground).



Figure 3. Rail-to-Rail Input /Output Voltage Range



Figure 4. Capacitive-Load Stability

Driving a capacitive load can cause instability in most high-speed op amps, especially those with low quiescent current. The MAX4122–MAX4129 have a high tolerance for capacitive loads. They are stable with capacitive loads up to 500pF. Figure 4 gives the stable operating region for capacitive loads. Figures 5–8 show the response with capacitive loads, and the results of adding an isolation resistor in series with the output (Figure 9). The resistor improves the circuit's phase margin by isolating the load capacitor from the op amp's output.

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply Rail-to-Rail I/O Op Amps



Figure 5. MAX4122/23/26/27/29 Small-Signal Transient Response with Capacitive Load



Figure 6. MAX4124/25/28 Small-Signal Transient Response with Capacitive Load



Figure 7. MAX4122/23/26/27/29 Transient Response to Capacitive Load with Isolation Resistor



Figure 8. MAX4124/25/28 Transient Response to Capacitive Load with Isolation Resistor



Figure 9. Capacitive-Load-Driving Circuit



Figure 10. Power-Up/Shutdown Test Circuit



Figure 11. Power-Up Output Voltage



Figure 12. Power-Up Supply Current



Figure 13. Shutdown Output Voltage



Figure 14. Shutdown Enable/Disable Supply Current

Power-Up and Shutdown Mode

The MAX4122–MAX4129 amplifiers typically settle within 1µs after power-up. Using the test circuit of Figure 10, Figures 11 and 12 show the output voltage and supply current on power-up.

The MAX4123, MAX4125, and MAX4127 have a shutdown option. When the shutdown pin ($\overline{SHDN}$) is pulled low, the supply current drops below 25µA per amplifier and the amplifiers are disabled with the outputs in a high-impedance state. Pulling $\overline{SHDN}$ high or leaving it floating enables the amplifier. In the dual-amplifier MAX4129, the shutdown functions operate independently. Figures 13 and 14 show the output voltage and supply current responses of the MAX4123 to a shutdown pulse.

Power Supplies and Layout

The MAX4122–MAX4129 operate from a single +2.7V to +6.5V power supply, or from dual supplies of ±1.35V to ±3.25V. For single-supply operation, bypass the power supply with a 0.1µF ceramic capacitor in parallel with at least 1µF. For dual supplies, bypass each supply to ground.

Good layout improves performance by decreasing the amount of stray capacitance at the op amp's inputs and outputs. To decrease stray capacitance, minimize trace lengths and resistor leads by placing external components close to the op amp's pins.

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply Rail-to-Rail I/O Op Amps

Pin Configurations

TOP VIEW



SOT23-5



SO/μMAX



SO/μMAX



SO



SO

Ordering Information (continued)

PART	TEMP. RANGE	PIN-PACKAGE	MARKING INFO.
MAX4124EUK	-40°C to +85°C	5 SOT23-5	AABA
MAX4125ESA	-40°C to +85°C	8 SO	—
MAX4125EUA	-40°C to +85°C	8 µMAX	—
MAX4126ESA	-40°C to +85°C	8 SO	—
MAX4126EUA	-40°C to +85°C	8 µMAX	—
MAX4127C/D	0°C to +70°C	Dice*	—
MAX4127ESD	-40°C to +85°C	14 SO	—
MAX4128ESA	-40°C to +85°C	8 SO	—
MAX4128EUA	-40°C to +85°C	8 µMAX	—
MAX4129ESD	-40°C to +85°C	14 SO	—

**Dice are specified at T_A = +25°C, DC parameters only.*

Chip Topographies

MAX4123/ MAX4125



TRANSISTOR COUNT: 170

SUBSTRATE CONNECTED TO V_{EE}

MAX4127/ MAX4128



TRANSISTOR COUNT: 340

SUBSTRATE CONNECTED TO V_{EE}

Single/Dual/Quad, Wide-Bandwidth, Low-Power, Single-Supply Rail-to-Rail I/O Op Amps

Package Information



SYMBOL	MIN	MAX
A	0.90	1.45
A1	0.00	0.15
A2	0.90	1.30
b	0.35	0.50
C	0.08	0.20
D	2.80	3.00
E	2.60	3.00
E1	1.50	1.75
L	0.35	0.55
e	0.95 REF	
e1	1.90 REF	
a	0°	10°

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 1997 Maxim Integrated Products Printed USA MAXIM is a registered trademark of Maxim Integrated Products.

OCEAN CHIPS
Океан Электроники
Поставка электронных компонентов

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «**JONHON**», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «**FORSTAR**».

AVIC JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели, кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).

FORSTAR®

Телефон: 8 (812) 309-75-97 (многоканальный)
Факс: 8 (812) 320-03-32
Электронная почта: ocean@oceanchips.ru
Web: http://oceanchips.ru/
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А