

4V Drive Pch MOSFET

RSD140P06

●Structure

Silicon P-channel MOSFET

●Features

- 1) Low on-resistance.
- 2) Fast switching speed.
- 3) Drive circuits can be simple.
- 4) Parallel use is easy.

●Application

Switching

●Packaging specifications

Type	Package	Taping
	Code	TL
	Basic ordering unit (pieces)	2500
RSD140P06		○

●Absolute maximum ratings ($T_a = 25^\circ\text{C}$)

Parameter		Symbol	Limits	Unit
Drain-source voltage		V_{DSS}	-60	V
Gate-source voltage		V_{GSS}	± 20	V
Drain current	Continuous	I_D	± 14	A
	Pulsed	I_{DP}^{*1}	± 28	A
Source current (Body Diode)	Continuous	I_S	-14	A
	Pulsed	I_{SP}^{*1}	-28	A
Power dissipation		P_D^{*2}	20	W
Channel temperature		T_{ch}	150	$^\circ\text{C}$
Range of storage temperature		T_{stg}	-55 to +150	$^\circ\text{C}$


 $*1 P_w \leq 10\mu\text{s}$, Duty cycle $\leq 1\%$
 $*2 T_c = 25^\circ\text{C}$

●Thermal resistance


Parameter	Symbol	Limits	Unit
Channel to Case	$R_{th(ch-c)}^{*}$	6.25	$^\circ\text{C} / \text{W}$

 $* T_c = 25^\circ\text{C}$

●Dimensions (Unit : mm)



●Inner circuit



●Electrical characteristics ($T_a = 25^\circ\text{C}$)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Gate-source leakage	I_{GSS}	-	-	± 10	μA	$V_{GS} = \pm 20\text{V}$, $V_{DS} = 0\text{V}$
Drain-source breakdown voltage	$V_{(BR)DSS}$	-60	-	-	V	$I_D = -1\text{mA}$, $V_{GS} = 0\text{V}$
Zero gate voltage drain current	I_{DSS}	-	-	-1	μA	$V_{DS} = -60\text{V}$, $V_{GS} = 0\text{V}$
Gate threshold voltage	$V_{GS(th)}$	-1.0	-	-3.0	V	$V_{DS} = -10\text{V}$, $I_D = -1\text{mA}$
Static drain-source on-state resistance	$R_{DS(on)}^*$	-	60	84	$\text{m}\Omega$	$I_D = -14\text{A}$, $V_{GS} = -10\text{V}$
		-	73	103		$I_D = -14\text{A}$, $V_{GS} = -4.5\text{V}$
		-	77	108		$I_D = -14\text{A}$, $V_{GS} = -4.0\text{V}$
Forward transfer admittance	$ Y_{fs} ^*$	10	-	-	S	$I_D = -14\text{A}$, $V_{DS} = -10\text{V}$
Input capacitance	C_{iss}	-	1900	-	pF	$V_{DS} = -10\text{V}$
Output capacitance	C_{oss}	-	200	-	pF	$V_{GS} = 0\text{V}$
Reverse transfer capacitance	C_{rss}	-	100	-	pF	$f = 1\text{MHz}$
Turn-on delay time	$t_{d(on)}^*$	-	20	-	ns	$I_D = -7.0\text{A}$, $V_{DD} = -30\text{V}$
Rise time	t_r^*	-	45	-	ns	$V_{GS} = -10\text{V}$
Turn-off delay time	$t_{d(off)}^*$	-	240	-	ns	$R_L = 4.3\Omega$
Fall time	t_f^*	-	110	-	ns	$R_G = 10\Omega$
Total gate charge	Q_g^*	-	27	-	nC	$V_{DD} = -30\text{V}$
Gate-source charge	Q_{gs}^*	-	4.5	-	nC	$I_D = -14\text{A}$,
Gate-drain charge	Q_{gd}^*	-	5.0	-	nC	$V_{GS} = -10\text{V}$

*Pulsed

●Body diode characteristics (Source-Drain) ($T_a = 25^\circ\text{C}$)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Forward Voltage	V_{SD}^*	-	-	-1.2	V	$I_S = -14\text{A}$, $V_{GS} = 0\text{V}$

*Pulsed

●Electrical characteristic curves (Ta=25°C)

Fig.1 Typical Output Characteristics (I)




Fig.2 Typical Output Characteristics (II)




Fig.3 Static Drain-Source On-State Resistance vs. Drain Current




Fig.4 Static Drain-Source On-State Resistance vs. Drain Current




Fig.5 Static Drain-Source On-State Resistance vs. Drain Current




Fig.6 Static Drain-Source On-State Resistance vs. Drain Current




Fig.7 Forward Transfer Admittance vs. Drain Current




Fig.8 Typical Transfer Characteristics




Fig.9 Source Current vs. Source-Drain Voltage




Fig.10 Static Drain-Source On-State Resistance vs. Gate-Source Voltage




Fig.11 Switching Characteristics




Fig.12 Dynamic Input Characteristics




Fig.13 Typical Capacitance vs. Drain-Source Voltage




Fig.14 Maximum Safe Operating Area





Fig.15 Normalized Transient Thermal Resistance v.s. Pulse Width



● Measurement circuits




Fig.1-1 Switching Time Measurement Circuit




Fig.1-2 Switching Waveforms




Fig.2-1 Gate Charge Measurement Circuit




Fig.2-2 Gate Charge Waveform

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

<http://www.rohm.com/contact/>

Компания «Океан Электроники» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Поставка оригинальных импортных электронных компонентов напрямую с производств Америки, Европы и Азии, а так же с крупнейших складов мира;
- Широкая линейка поставок активных и пассивных импортных электронных компонентов (более 30 млн. наименований);
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Помощь Конструкторского Отдела и консультации квалифицированных инженеров;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Поставка электронных компонентов под контролем ВП;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- При необходимости вся продукция военного и аэрокосмического назначения проходит испытания и сертификацию в лаборатории (по согласованию с заказчиком);
- Поставка специализированных компонентов военного и аэрокосмического уровня качества (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Actel, Aeroflex, Peregrine, VPT, Syfer, Eurofarad, Texas Instruments, MS Kennedy, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Компания «Океан Электроники» является официальным дистрибьютором и эксклюзивным представителем в России одного из крупнейших производителей разъемов военного и аэрокосмического назначения «JONHON», а так же официальным дистрибьютором и эксклюзивным представителем в России производителя высокотехнологичных и надежных решений для передачи СВЧ сигналов «FORSTAR».



JONHON

«JONHON» (основан в 1970 г.)

Разъемы специального, военного и аэрокосмического назначения:

(Применяются в военной, авиационной, аэрокосмической, морской, железнодорожной, горно- и нефтедобывающей отраслях промышленности)

«FORSTAR» (основан в 1998 г.)

ВЧ соединители, коаксиальные кабели,
кабельные сборки и микроволновые компоненты:

(Применяются в телекоммуникациях гражданского и специального назначения, в средствах связи, РЛС, а так же военной, авиационной и аэрокосмической отраслях промышленности).



Телефон: 8 (812) 309-75-97 (многоканальный)

Факс: 8 (812) 320-03-32

Электронная почта: ocean@oceanchips.ru

Web: <http://oceanchips.ru/>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, д. 2, корп. 4, лит. А